

LBP6030w / LBP6030B / LBP6030

Important Safety Instructions	5
Installation	6
Power Supply	8
Handling	9
Maintenance and Inspections	11
<u>Consumables</u>	12
Basic Operations	14
Parts and Their Functions	15
Front Side	16
Back Side	10
Interior	18
	18
Multi-Purpose Tray	-
Printer Status Window	20
Turning the Power ON and OFF	23
Saving Power	24
Setting Sleep Mode	25
Setting Auto Shutdown	26
Loading Paper	27
Loading Paper in the Multi-Purpose Tray	29
Loading Envelopes	31
Loading Preprinted Paper	33
Printing	34
Basic Print Operations	35
Canceling Print Jobs	37
Checking the Print Status	39
Various Print Settings	40
Enlarging or Reducing	41
Collating Printouts by Page	43
Printing Multiple Pages Onto One Sheet	44
Printing Posters	45
	46
Printing Borders	
Printing Dates and Page Numbers	47
Printing Watermarks	48
Printing According to the Document Type	50
Saving Toner	51
Combining and Printing Multiple Documents	52
Configuring Print Settings to Your Needs	55
Registering Combinations of Frequently Used	-
Changing Default Settings	58
Network	59
Connecting to a Network	60
Connecting to a Wireless LAN	61
Setting IP Addresses	63
Setting IPv4 Address	64
Setting IPv6 Addresses	66
Viewing Network Settings	69
Configuring for Printing from a Computer	71
Configuring Printing Protocols and Web Service	
Configuring Printer Ports	75
	-
Downloaded from ManualsPrinter com Manuals	2 / 210

Downloaded from ManualsPrinter.com Manuals 2 / 219

Configuring the Machine for Your Network Environment	79
Changing the Maximum Transmission Unit	80
Setting a Wait Time for Connecting to a Network	82
Configuring DNS	84
Configuring WINS	88
Configuring NetBIOS	90
Configuring SNTP	92 05
Monitoring and Controlling the Machine with SNMP	95
Configuring SLP Communication with imageWARE	99 101
Security	101
Protecting the Machine from Unauthorized Access	102
Setting System Manager Passwords	103
Restricting Communication by Using Firewalls	105
Changing Port Numbers	108
Enabling SSL Encrypted Communication for the Remote UI	
Configuring Settings for Key Pairs and Digital Certificates	113 114
Generating Key Pairs	
Using CA-issued Key Pairs and Digital Certificates	116
Verifying Key Pairs and CA Certificates	119 121
Using the Remote UI	121
Starting the Remote UI	122
Remote UI Screens	124
Managing Documents and Checking the Machine Status	120
Changing Machine Settings	129
<u>Setting Menu List</u> <u>Troubleshooting</u>	130 140
<u>Clearing Paper Jams</u>	141
When an Error Message Appears	143
<u>Common Problems</u>	147
Installation/Settings Problems	147
Printing Problems	140
When You Cannot Print Properly	150
Printing Results Are Not Satisfactory	152
Paper Creases or Curls	155
Paper Is Fed Incorrectly	160
When a Problem Cannot Be Solved	161
Maintenance	162
Cleaning the Machine	163
Replacing Toner Cartridges	165
Using Up All of the Toner	167
How to Replace Toner Cartridges	169
Printing Setting Lists	171
Viewing the Page Counter Value	173
Initializing Settings	174
Initializing Preferences Settings	175
Initializing System Management Settings	176
Initializing Key and Certificate Settings	178
Relocating the Machine	180
Appendix	181

Feature Highlights	182
Going Green and Saving Money	183
Improving Efficiency	184
So Much More	186
Specifications	188
Machine Specifications	189
Wireless LAN Specifications	191
Paper	192
Consumables	194
Manuals Included with the Machine	195
<u>Using the e-Manual</u>	196
Installing the e-Manual	197
Uninstalling the e-Manual	200
Screen Layout of the e-Manual	202
Viewing the e-Manual	206
Other	207
Basic Windows Operations	208
For Mac OS Users	213
Notice	214
Office Locations	219

Important Safety Instructions

This chapter describes important safety instructions for the prevention of injury to users of this machine and others, and damage to property. Read this chapter before using the machine, and follow the instructions to use the machine properly. Do not perform any operations not described in this manual. Canon will not be responsible for any damages resulting from operations not described in this manual. Canon will not be responsible for any damages resulting from operations not described in this manual, improper use, or repair or changes not performed by Canon or a third party authorized by Canon. Improper operation or use of this machine could result in personal injury and/or damage requiring extensive repair that may not be covered under your Limited Warranty.

Installation

To use this machine safely and in a trouble-free way, carefully read the following precautions and install the machine in an appropriate location.

A WARNING

Do not install in a location that may result in a fire or electrical shock

- A location where the ventilation slots are blocked
- (too close to walls, beds, sofas, rugs, or similar objects)
- A damp or dusty location
- A location exposed to direct sunlight or outdoors
- A location subject to high temperatures
- A location exposed to open flames
- Near alcohol, paint thinners or other flammable substances

Other warnings

- Do not connect unapproved cables to this machine. Doing so may result in a fire or electrical shock.
- Do not place necklaces and other metal objects or containers filled with liquid on the machine. If foreign substances come in contact with electrical parts inside the machine, it may result in a fire or electrical shock.
- Do not use near medical equipment. Radio waves emitted from this machine may interfere with medical equipment, which may result in malfunctions and accidents.
- If any foreign substance falls into this machine, unplug the power plug from the AC power outlet and contact your local authorized Canon dealer.

CAUTION

Do not install in the following locations

The machine may drop or fall, resulting in injury.

- An unstable location
- A location exposed to vibrations



Other cautions

- When carrying this machine, follow the instructions in this manual. If carried improperly, it may fall, resulting in injury.
- When installing this machine, be careful not to get your hands caught between the machine and the floor or walls. Doing so may result in injury.

IMPORTANT

Do not install in the following locations

Doing so may result in damage to the machine.

- A location subject to dramatic changes in temperature or humidity
- A location near equipment that generates magnetic or electromagnetic waves
- . A laboratory or location where chemical reactions occur



- A location exposed to corrosive or toxic gases
- A location that may warp from the weight of the machine or where the machine is liable to sink (a carpet, etc.)

Avoid poorly ventilated locations

This machine generates a slight amount of ozone and other emissions during normal use. These emissions are not harmful to health. However, they may be noticeable during extended use or long production runs in poorly ventilated rooms. To maintain a

comfortable working environment, it is recommended that the room where the machine operates be appropriately ventilated. Also avoid locations where people would be exposed to emissions from the machine.

Do not install in a location where condensation occurs

Water droplets (condensation) may form inside the machine when the room where the machine is installed is heated rapidly, and when the machine is moved from a cool or dry location to a hot or humid location. Using the machine under these conditions may result in paper jams, poor print quality, or damage to the machine. Let the machine adjust to the ambient temperature and humidity for at least 2 hours before use.

When using wireless LAN (LBP6030w)

- . Install the machine at a distance of 50 m or less from the wireless LAN router.
- As far as possible, install in a location where communication is not blocked by intervening objects. The signal may be degraded when passing through walls or floors.
- Keep the machine as far as possible from digital cordless phones, microwave ovens, or other equipment that emits radio waves.

In altitudes of 3,000 m or above sea level

Machines with a hard disk may not operate properly when used at high altitudes of about 3,000 meters above sea level, or higher.

Power Supply

This machine is compatible with voltages of 220 to 240 V, and electrical frequency of 50/60 Hz.

WARNING

- Use only a power supply that meets the specified voltage requirements. Failure to do so may result in a fire or electrical shock.
- Do not use power cords other than the one provided, as this may result in a fire or electrical shock.
- Do not modify, pull, forcibly bend, or perform any other act that may damage the power cord. Do not place heavy objects on the power cord. Damaging the power cord may result in a fire or electrical shock.
- Do not plug in or unplug the power plug with wet hands, as this may result in an electrical shock.
- Do not use extension cords or multi-plug power strips with the machine. Doing so may result in a fire or electrical shock.
- Do not wrap the power cord or tie it in a knot, as this may result in a fire or electrical shock.
- Insert the power plug completely into the AC power outlet. Failure to do so may result in a fire or electrical shock.
- Remove the power plug completely from the AC power outlet during a thunder storm. Failure to do so may result in a fire, electrical shock, or damage to the machine.

CAUTION

Do not obstruct the power outlet where this machine is connected, so that you can unplug the power plug easily in an emergency.

IMPORTANT

When connecting power

- Do not connect the power cord to an uninterruptible power source.
- If you plug this machine into an AC power outlet with multiple sockets, do not use the remaining sockets to connect other devices.
- Do not connect the power cord to the auxiliary AC power outlet on a computer.

Other precautions

Electrical noise may cause this machine to malfunction or lose data.

dill-

Handling

WARNING

- Immediately unplug the power plug from the AC power outlet and contact an authorized Canon dealer if the machine makes an unusual noise, emits an unusual smell, or emits smoke or excessive heat. Continued use may result in a fire or electrical shock.
- Do not disassemble or modify this machine. There are high-voltage and hightemperature components inside the machine. Disassembly or modification may result in a fire or electrical shock.
- Place the machine where children will not come in contact with the power cord and other cables or gears and electrical parts inside the machine. Failure to do so may result in unexpected accidents.
- Do not use flammable sprays near this machine. If flammable substances come into contact with electrical parts inside this machine, it may result in a fire or electrical shock.
- When moving this machine, be sure to turn OFF the power of this machine and your computer, and then unplug the power plug and interface cables. Failure to do so may damage the power cord or interface cables, resulting in a fire or electrical shock.
- When plugging or unplugging a USB cable when the power plug is plugged into an AC power outlet, do not touch the metal part of the connector, as this may result in an electrical shock.

If you are using a cardiac pacemaker

This machine generates a low level magnetic flux. If you use a cardiac pacemaker and feel abnormalities, please move away from this machine and consult your physician immediately.

CAUTION

- Do not place heavy objects on this machine as they may fall, resulting in injury.
- For safety, unplug the power plug if the machine will not be used for a long period of time.
- Use caution when opening and closing covers to avoid injury to your hands.
- Keep hands and clothing away from the rollers in the output area. If the rollers catch your hands or clothing, this may result in personal injury.
- The inside of the machine and the output slot are very hot during and immediately after use. Avoid contact with these areas to prevent burns. Also, printed paper may be hot immediately after being output, so use caution when handling it. Failure to do so may result in burns.




Laser beam

This machine is classified as a Class 1 Laser Product under IEC 60825-1: 2007, EN60825-1: 2007. The laser beam can be harmful to the human body. The laser beam is confined in the laser scanner unit by a cover, so there is no danger of the laser beam escaping during normal machine operation. Read the following remarks and instructions for safety.

- Never open covers other than those indicated in this manual.
- Do not remove the caution label attached to the cover of the laser scanner unit.

If you operate the machine in manners other than the control, adjustment, and operating procedures prescribed in this manual, this may result in hazardous radiation exposure.

If the laser beam should escape and enter your eyes, exposure may cause damage to your eyes.



IMPORTANT

When transporting the machine

To prevent damage to the machine during transport, do the following.

- Remove the toner cartridge.
- Securely pack the machine in the original box with the original packing materials.

Other precautions

- Follow the instructions on the caution label attached to this machine.
- Do not subject the machine to strong shocks or vibration.
- Do not forcibly open and close doors, covers, and other parts. Doing so may result in damage to the machine.
- Do not touch the contacts (
 Doing so may result in damage to the machine.



Do not turn OFF the machine during printing. Also, do not open and close the cover and do not remove or insert paper during printing. Doing so can cause paper jams.

Maintenance and Inspections

Clean this machine periodically. If dust accumulates, the machine may not operate properly. When cleaning, be sure to observe the following. If a problem occurs during operation, see **Croubleshooting**. If the problem cannot be resolved or you feel the machine requires an inspection, see **CWhen a Problem Cannot Be Solved**.

WARNING

- Before cleaning, turn OFF the power and unplug the power plug from the AC power outlet. Failure to do so may result in a fire or electrical shock.
- Unplug the power plug periodically and clean with a dry cloth to remove dust and grime. Accumulated dust may absorb humidity in the air and may result in a fire if it comes into contact with electricity.
- Use a damp, well wrung-out cloth to clean the machine. Dampen cleaning cloths with water only. Do not use alcohol, benzenes, paint thinners, or other flammable substances. Do not use tissue paper or paper towels. If these substances come into contact with electrical parts inside the machine, they may generate static electricity or result in a fire or electrical shock.
- Check the power cord and plug periodically for rust, bent prongs, fraying, cracks, or excessive heat generation. Use of poorlymaintained power cord or plug may result in a fire or electrical shock.

CAUTION

- The inside of the machine has high-temperature and high-voltage components. Touching these components may result in injury or burns. Do not touch any part of the machine that is not indicated in the manual.
- When loading paper or removing jammed paper, be careful not to cut your hands with the edges of the paper.

IMPORTANT

When removing jammed paper or replacing toner cartridges, be careful not to get any toner on your hands or clothing. If toner gets on your hands or clothing, wash them immediately with cold water.

Consumables

🗥 WARNING

- Do not dispose of used toner cartridges in open flames. Also, do not store toner cartridges or paper in a location exposed to open flames. This may cause the toner or paper to ignite, and result in burns or fire.
- If you accidentally spill or scatter toner, carefully sweep it up or wipe it up with a damp cloth, and avoid inhaling any toner dust. Do not use a vacuum cleaner to clean up loose toner unless it is equipped with safety measures to prevent dust explosions. Doing so may cause damage to the vacuum cleaner or result in a dust explosion due to static discharge.

If you are using a cardiac pacemaker

Toner cartridges generate a low level magnetic flux. If you use a cardiac pacemaker and feel abnormalities, please move away from toner cartridges and consult your physician immediately.


CAUTION

- Use caution not to inhale any toner. If you should inhale toner, consult a physician immediately.
- Use caution so that toner does not get into your eyes or mouth. If toner should get into your eyes or mouth, immediately wash it away with cold water and consult a physician.
- Use caution so that toner does not come into contact with your skin. If it should, wash it off with soap and cold water. If your skin is irritated, consult a physician immediately.
- Keep toner cartridges and other consumables out of the reach of small children. If toner is ingested, consult a physician or poison control center immediately.
- Do not disassemble or modify the toner cartridge. Doing so may cause the toner to scatter.
- Remove the sealing tape of the toner cartridge completely without using excessive force. Doing so may cause the toner to scatter.


IMPORTANT

Handling the toner cartridge

Be sure to use the holder to hold the toner cartridge.



Do not touch the electrical contacts (a) or toner cartridge memory (b). Do not open the drum protection shutter(c). Doing so risks scratching the drum surface or exposing it to light.



The toner cartridge is a magnetic product. Keep it away from floppy disks, disk drives, and other devices that can be affected by magnetism. Failure to do so may result in data loss.

Storing toner cartridges

- To ensure safe and satisfactory performance, store toner cartridges under the following environmental conditions. Storage temperature range: 0 to 35 °C
- Storage humidity range: 35 to 85% RH (relative humidity), no condensation*
- Store without opening until the toner cartridge is to be used.
- When removing the toner cartridge from this machine for storage, place the removed toner cartridge into the original

protective bag or wrap it with a thick cloth.

- When storing the toner cartridge, do not store it upright or upside down. The toner may solidify and not return to its original condition even if it is shaken.
- * Even within the storable humidity range, water droplets (condensation) may develop inside the toner cartridge if there is a difference of temperature inside and outside the toner cartridge. Condensation inside the toner cartridge will adversely affect print quality.

Do not store the toner cartridge in the following locations

- Locations exposed to open flames
- . Locations exposed to direct sunlight or bright light for five minutes or more
- Locations exposed to excessive salty air
- Locations where there are corrosive gases (i.e. aerosol sprays and ammonia)
- Locations subject to high temperature and high humidity
- Locations subject to dramatic changes in temperature and humidity where condensation may easily occur
- Locations with a large amount of dust
- Locations within the reach of children

Be careful of counterfeit toner cartridges

Please be aware that there are counterfeit Canon toner cartridges in the marketplace. Use of counterfeit toner cartridge may result in poor print quality or machine performance. Canon is not responsible for any malfunction, accident or damage caused by the use of counterfeit toner cartridge.

For more information, see http://www.canon.com/counterfeit.

Availability of repair parts and toner cartridges

Repair parts and toner cartridges for this machine will be available for at least seven (7) years after production of this machine model has been discontinued.

Toner cartridge packing materials

- Save the protective bag for the toner cartridge. It is required when transporting this machine.
- Packing materials may be changed in form or placement, or may be added or removed without notice.
- Dispose of removed sealing tape according to local regulations.

Disposal of used toner cartridges

Place the toner cartridge into its protective bag to prevent the toner from scattering, and then dispose of the toner cartridge according to local regulations.

Basic Operations

This chapter describes the parts of the machine and basic operations, such as how to load paper.

Parts and Their Functions

This section describes the names and functions of the exterior and interior parts of the machine. **Parts and Their Functions**



Printer Status Window

This section explains how to use the "Printer Status Window" utility to check the machine's status and make machine settings. **©Printer** Status Window



■Turning the Power ON and OFF

This section explains how to turn the power ON and OFF. OTurning the Power ON and OFF



Saving Power

This section explains how to reduce the machine's power consumption. **Osaving Power**



Loading Paper

This section explains how to load paper into the multi-purpose tray. OLOading Paper




Parts and Their Functions

This section describes the parts of the machine (exterior, front and back side, and interior) and how they function. It also describes the parts of the machine used for basic operations such as loading paper and replacing the toner cartridge, and explains the meaning of indications by the keys and indicators on the front side. Read this section for tips on how to use the machine properly.



Front Side
Back Side
Interior
Multi-Purpose Tray

Front Side



🚺 Top cover

Open the top cover to replace the toner cartridge or clear a paper jam. **Ohow to Replace Toner Cartridges Oclearing Paper Jams**

<u> (</u>(h) (Wi-Fi) indicator (LBP6030w)

Lights up when the machine is connected to a wireless LAN.

🛐 (⑾) (Wi-Fi) key (LBP6030w)

Use this key when setting up a wireless LAN connection by using the WPS push-button method.

NOTE:

You can also keep the (m) (Wi-Fi) key pressed while turning ON the power to initialize the system management settings. **Initializing by Using the Wi-Fi Key**

🗿 👍 (Power) indicator

Lights up when the machine is powered ON.

<u>5</u> 🛓 (Paper) key

Flashes when the machine is out of paper, when the paper is the wrong size, and after other errors when the paper needs to be checked. Reset the paper and press the key to restart printing.

NOTE:

You can also use the \downarrow (Paper) key to print a list of network settings (with the machine ready to print, press the key and hold it down for 3 seconds). **Viewing Network Settings**

👩 Power switch

Turns the power ON or OFF. OTurning the Power ON and OFF


🛜 Output tray

Open this tray before printing. Printed paper is output to the output tray.

8 Multi-purpose tray

Load the paper to print in this tray. OLoading Paper in the Multi-Purpose Tray

Back Side



Ventilation slots

Air from inside the machine is vented out to cool down the inside of the machine. Note that placing objects in front of the ventilation slots prevents ventilation. **DINSTALLATION**

🔁 Rating label

The label shows the serial number, which is needed when making inquiries about the machine. **OWhen a Problem Cannot Be Solved**


USB port

Connect a USB cable when connecting the machine and a computer.

🗿 Power socket

Connect the power cord.

Interior




Toner cartridge guide

When loading a toner cartridge, align the protrusions on the left and right sides of the cartridge with the guide. OHOW to Replace Toner Cartridges

LINKS

©Replacing Toner Cartridges

Multi-Purpose Tray



🚹 Paper guides

Adjust the paper guides to exactly the size of the loaded paper to ensure that paper is fed straight into the machine.

LINKS

OLoading Paper in the Multi-Purpose Tray

Printer Status Window

The Printer Status Window is a utility that allows you to check the machine's status, view error information, and make settings related to the machine, such as power saving settings. You can also use it for operations such as cancelling a print job or printing a list of the machine's settings. The Printer Status Window utility is installed on your computer automatically when you install the printer driver (Printer Driver Installation Guide).



Displaying the Printer Status Window
Parts of the Screen and Their Functions

Displaying the Printer Status Window

Select the machine by clicking $\mathbf{\underline{B}}$ in the system tray.



NOTE

Automatic Display of the Printer Status Window

The Printer Status Window is displayed automatically when an error occurs during printing.

* You can change the setting that determines when the Printer Status Window is displayed automatically. Change it with the [Options] menu [Preferences (Users)] or [Preferences (Administrators)] dialog box of the Printer Status Window. For details, see the Help. [Preferences (Administrators)] dialog box of the Printer Status Window.

If you are using Windows 8/Server 2012


Display the Printer Status Window after moving to the desktop.

Displaying from the Printer Driver Click

A4 [Scaling: Auto]	or	•	
Vew Settings Restore Defaults			
		OK Carcal	Help

Parts of the Screen and Their Functions

This section provides an outline of the main screen. For detailed descriptions of the dialog boxes that can be displayed with the controls and menus in this screen, see the Help. **O[Help] menu**



🚺 [Job] menu

Allows you to check documents that are printing or waiting. You can also select documents and cancel printing.

👩 [Options] menu

Allows you to execute maintenance functions, such as printing setting lists or cleaning the fixing unit, and to make machine settings, such as power saving settings. You can also check information such as the total number of pages printed.

🛐 [Help] menu

Displays Help about the Printer Status Window and version information.

NOTE:

You can also display the Printer Status Window Help by clicking the [Help] button in the various dialog boxes. However, some dialog boxes do not have a [Help] button.

[Toolbar

(Print Queue)

Displays the print queue, a Windows function. See the Windows Help for more information about the print queue.

(Refresh)

Refreshes the Printer Status Window with the latest information.

(Wireless LAN Status) (LBP6030w)

Allows you to check the connection status (signal strength) of the wireless LAN.

🗞 (Remote UI) (LBP6030w)

Starts the Remote UI. OUsing the Remote UI

6 Animation area

Displays animations and illustrations about the machine's status. After an error occurs, this area may also display a simple explanation of how to deal with the error.

👩 Icon

Displays an icon that indicates the machine's status. The normal status is \square but when an error occurs, the display changes to one of \square / \square , depending on the message.

🛜 Message area

Displays messages about the machine's status. If an error or warning occurs, this area displays an explanation beneath the error message or warning, together with information about how to deal with the problem. **OWhen an Error Message Appears**

[Troubleshooting Details]

Displays troubleshooting information for problems described by messages.

[Print Job Information]

Displays information about the document that is currently being printed.

🔞 [* (Cancel Job)

Cancels the printing of the document currently being printed.

(Continue/Retry)

When an error has occurred, but printing can be continued, this button allows you to clear the error and resume printing. However, if you use the Continue/Retry function to resume printing, partially printed pages or other improper printing may occur.

[Purchase Consumables]

If you click [Purchase Consumables] > select your country or region > click [OK], a Canon Web site page is displayed where you can find information about purchasing consumables.

<u> Status</u> bar

Displays the connection destination (port name) of the Printer Status Window.


Turning the Power ON and OFF

Use the power switch on the front side of the machine to turn the power ON and OFF. To restart the machine, turn the machine OFF, wait for at least 10 seconds, and turn it back ON.

Turning the Power ONTurning the Power OFF

Turning the Power ON

When you press the power switch, the 🕁 (Power) indicator lights and the machine is ready for printing.




NOTE

A blank sheet of paper may be output when you turn ON the power for the first time after purchasing the machine. This is not a malfunction.

Turning the Power OFF

When you press the power switch, the 0 (Power) indicator goes out and the power is turned OFF.



NOTE

Even when the power is turned OFF, the machine continues to consume a small amount of power. To reduce power consumption to zero, unplug the power plug from the AC power outlet.

Saving Power

You can save power by setting up the machine to automatically enter sleep mode or turn itself OFF after it remains idle for a certain length of time.



Setting Sleep ModeSetting Auto Shutdown

Setting Sleep Mode

The sleep mode function reduces the amount of power consumed by the machine by temporarily stopping some internal operations. You can set up the machine to enter sleep mode automatically when it remains idle for a certain length of time. The factory default setting for the amount of time that elapses before the machine enters sleep mode is 1 minute. We recommend using the factory default setting to save the most power. If you want to change the amount of time that elapses before the machine enters sleep mode, follow the procedure below in the Printer Status Window.

NOTE

Situations in which the machine does not enter sleep mode

- The machine does not enter sleep mode when it is receiving print data from a computer, when a cover is open, when a toner cartridge is not loaded, and in some other situations.
- Depending on your environment, the machine may not enter sleep mode when it is connected to a wireless LAN network.

Select the machine by clicking 🔐 in the system tray.



2 Select [Options] > [Device Settings] > [Sleep Settings].



3 Make sleep mode settings, and click [OK].



[Auto Sleep after Fixed Period]

Select the check box to enter sleep mode after the time specified with [Enter Auto Sleep After].

[Enter Auto Sleep After]

Specify the length of time after which the machine enters sleep mode. You can select from 1 to 180 minutes.

Setting Auto Shutdown

You can set up the machine to automatically turn itself OFF after it remains idle for a certain length of time. This prevents wasted power consumption caused by forgetting to turn the machine OFF. The factory default setting for the amount of time that elapses before the power is turned OFF is 4 hours. If you want to change this setting, perform the following procedure in the Printer Status Window.

NOTE

If you set the time until the power is turned OFF to a time shorter than the factory default setting, the lifetime of the toner cartridge may be shorter.

Select the machine by clicking 🔐 in the system tray.



2 Select [Options] ▶ [Device Settings] ▶ [Auto Shutdown Settings].

references (Administrators)	- H		
Counter Information			
Vireless LAN Status			
Aliity	· ·		*
Nevice Settings		Settings to Disable Wi-Fi Key	
Management Settings	•	Sileen Settinos	
lemote UE		Auto Shutdown Settings	
		Warning Usplay Settings	1
(efresh	_	Assisting Print Settings	
	Vireless LAN Status Aläity Device Settings Management Settings	Vireless LAN Status Jäfity + Device Settings + Janagement Settings + Itemote UI	Virdess LAN Datan Nitry Nitry Arragement Settings Larrote UK Larrote UK Larrote UK Larrote LAN Larrote LAN LAN LAN LAN LAN LAN LAN LAN

3 Make auto shutdown settings, and click [OK].

uto Shutdown Settings		
Auto Shutdown alter Field Period		ר
Auto Shuldown After:	4 •	н.
	Cancel	Hab

[Auto Shutdown after Fixed Period]

Select the check box to enable auto shutdown after the time specified with [Auto Shutdown After].

[Auto Shutdown After]

Specify the length of time until the machine executes auto shutdown, starting from the time when the machine enters sleep mode. You can select from 1 hour to 8 hours, in units of 1 hour.

Loading Paper

This section explains how to load paper into the multi-purpose tray. See **Paper** for information about available paper sizes.



Paper Type and Printer Driver Paper Settings

Before printing, refer to the table below and make the appropriate paper settings in the printer driver, according to the type of paper that you have loaded. See **OBasic Print Operations** for detailed information about paper settings, and see **OPaper** for information about the number of sheets that can be set.

	Paper Type	Printer Driver Paper Setting
Plain paper *1	60 to 63 g/m ²	[Plain L]
Раш рарет ±	64 to 89 g/m²	[Plain]
Heavy paper	90 to 163 g/m ²	[Heavy] [Heavy H] *2
Transparency *3 *4		[Transparency]
Labels *4		[Labels]
Envelope		[Envelope]

 *1 Recycled paper can be used.

 *2 If toner is not fully fixed and printouts are faded when you select [Heavy], select this instead.

*3 Use laser printer transparencies.

*4 Use A4 or Letter size only.

IMPORTANT

Do not use the following types of paper:

- Wrinkled or creased paper
- Ourled or rolled paper
- Torn paper
- Damp paper
- Very thin paper
- Paper printed by a thermal transfer printer
- Paper with a coarse texture
- Glossy paper

Paper handling and storage

- Store paper on a flat surface.
- Keep paper wrapped in its original package to protect the paper from moisture or dryness.
- Do not store paper in a way that may cause it to curl or fold.
- Do not store paper vertically or stack too many packages of paper.
- Do not store paper in direct sunlight, or in a place subject to high humidity, dryness, or drastic changes in temperature or humidity.

NOTE

When printing on paper that has absorbed moisture Steam may be emitted from the paper output area, or water droplets may form around the paper output area. This is not a malfunction. It occurs when the heat used to fix toner on the paper causes moisture in the paper to evaporate (most likely to occur at low room temperatures).


Loading Paper in the Multi-Purpose Tray

Load the paper to print in the multi-purpose tray.

IMPORTANT


Always load paper in portrait orientation

Paper cannot be loaded in landscape orientation. Be sure to load paper in portrait orientation, as shown in the illustration below.












3 Load the paper and slide it all the way in, until it touches the back side.


- Load the paper in portrait orientation (with the short edge toward the machine) and the print side face up. Paper cannot be loaded in landscape orientation.
- Before loading it, fan the paper stack well, and tap it on a flat surface to align the edges.



IMPORTANT:

Keep the paper stack within the load limit guides.

Make sure that the paper stack does not exceed the load limit guides (6). Loading too much paper can cause paper jams.



NOTE:

When loading envelopes or preprinted paper, see **OLOading Envelopes** or **OLOading Preprinted Paper**.

4 Align the paper guides against the edges of the paper.

Align the paper guides securely against the edges of the paper.



IMPORTANT:

Align the paper guides securely against the paper

Paper guides that are too loose or too tight can cause misfeeds or paper jams.

NOTE

After reloading paper that has run out during printing, or resetting the paper after a paper error notification, press the 📋 (Paper) key to restart printing.

Printing on the Back Side of Printed Paper (Manual 2-Sided Printing)

You can print on the back side of printed paper. Flatten any curls on the printed paper and insert it into the multi-purpose tray with the side to print face up (previously printed side face down).

- Load only one sheet of paper each time you print.
- You can use only paper printed with this machine.
- You cannot print on the side that has been previously printed.

LINKS

Paper

Loading Envelopes

Make sure to flatten any curls on envelopes before loading them. Also pay attention to the orientation of envelopes and which side is face up.

Before Loading Envelopes

Control Con

NOTE

This section explains how to load envelopes in the orientation you want, as well as preparations that you need to complete before loading envelopes. For a complete description of the procedure for loading envelopes in the multi-purpose tray, see **CLOADING Paper in the Multi-Purpose Tray**.

Before Loading Envelopes

Follow the procedure below to prepare the envelopes before loading.

1 Close the flap of each envelope.



2 Press down to expel air from the envelopes and make sure that the folds on all four sides are sharp and that the stack is flat.



Remove curls by flexing the stiff sections at the four corners.



4 Tap the stack on a flat surface to even the edges of the envelopes.




Loading Envelopes in the Multi-Purpose Tray

Load the envelopes Monarch, No. 10 (COM10), DL, or C5 in portrait orientation (with the short edge toward the machine), with the nonglued side (front side) face up. You cannot print on the reverse side of envelopes.

NOTE

Load the envelopes so that the edge with the flap is toward the left side as shown in the illustration.



Loading Preprinted Paper

When you use paper that has been preprinted with a logo or other information, pay attention to the orientation of the paper when loading. Load the paper with the logo side (the side on which to print the document) face up and in the proper orientation for the layout of the document.



NOTE


This section explains how to load preprinted paper with the proper orientation and the right side face up. For a complete description of the procedure for loading paper in the multi-purpose tray, see **Complete Paper** in the Multi-Purpose Tray.

Printing Paper with a Logo in Portrait Orientation






Printing Paper with a Logo in Landscape Orientation



Printing

You can print documents made with applications on your computer by using the printer driver. There are useful settings in the printer driver, such as enlarging/reducing and poster printing, that enable you to print your documents in various ways. Before you can use these functions, you need to install the printer driver on your computer and complete some other preparations. For details, see Printer Driver Installation Guide.



NOTE

Depending on the operating system and the type or version of the printer driver you are using, the printer driver screens in this manual may differ from your screens.

About the Printer Driver Help

Clicking [Help] on the printer driver screen displays the Help screen. On this screen, you can see detailed descriptions that are not in the e-Manual.

A4 [Scaling: Auto]	or	-
Vew Settings		
Restore Defaults		
	P.,	
		OK Cancel He

Basic Print Operations


This section explains how to print a document on your computer by using the printer driver.



Open a document in an application and display the print dialog box.

How to display the print dialog box differs for each application. For more information, see the instruction manual for the application you are using.

Select this machine and click [Preferences] or [Properties].



The screen that is displayed differs depending on the application you are using.

3 Set the paper size.

Printing Preferences		
Basic Settings Page Setup Rhishing	Paper Source Quality	
Profile:	Default Settings 🔹	Add(1) Edit(2)
Output Method: 🚔 P	wit -	
	Page Size: Ad	Copies(2): 1 (1 to 990) • Oteration • A @ Potrst A @ Landscape
	Page Layout:	Manual Scaing Scaing 100 ☆ ≈ (25 to 200)
	Binding Location:	
	Long Edge [Left]	- Guter
	Frishing:	

[Page Size]


Select the size that you used when you created the document in the application.

[Output Size]

Select the paper size to be used in the actual printing. If you select a size that differs from [Page Size], the printer driver will automatically enlarge or reduce the data to match the [Output Size]. **Denlarging or Reducing**

4 In the [Paper Source] tab, select the paper type.

Set [Paper Type] according to the type of paper to be used in the printing. OPaper Type and Printer Driver Paper Settings



5 Set other printing preferences as necessary. **O**Various Print Settings

NOTE:

You can register the settings you specified in this step as a "profile" and use the profile whenever you print. This eliminates the need to specify the same settings every time you print. **OREGISTERING COMBINATIONS of Frequently Used Print Settings**

6 Click [ОК].

A4 (Scaling: Auto)	
Vew Settings	
	Restore Defaults
	OK Cancel Help

7 Click [Print] or [OK].

🖶 Print	
General	
Select Plinter	Microsoft XPS Documen
(#g)Canon LEP6030/6040/6018L	
x	P.
Status: Ready Location:	Print to file Preferences
Comment:	Pind Partier
Page Range	
@ AI	Number of copies: 1 🚭
Selection Current Page	
Pagea: 1-65535	Colors - CO-CO-CO
Enter either a single page number or a single page range. For example, 5-12	11 22 33
	nt Cancel Apply

Important Printing starts. On some applications, a screen like the one shown below appears.



If a screen like the one shown above appears, you can cancel printing by clicking [Cancel]. If the screen disappears or is never displayed, you can cancel printing in other ways. Canceling Print Jobs

IMPORTANT

Do not touch printed pages

Do not touch newly printed sheets with your fingers or a cloth. You may get your fingers or the cloth dirty, and the toner may smear or come off the page.

NOTE

When printing from a Windows Store app in Windows 8/Server 2012

• Display the charms on the right side of the screen, and proceed as follows.

Windows 8/Server 2012
Tap or click [Devices] ▶ the machine you are using ▶ [Print].
Windows 8.1/Server 2012 R2
Tap or click [Devices] ▶ [Print] ▶ the machine you are using ▶ [Print].
When you print in this way, you can only use some of the print settings.

• If the message <The printer requires your attention. Go to the desktop to take care of it.> is displayed, go to your desktop and follow the instructions in the dialog box on the screen. This message is displayed when you need to enter your user name before printing, or when there is some other setting that requires your attention.

LINKS

Checking the Print Status

Canceling Print Jobs

You can cancel print jobs from the Printer Status Window.

1 Select the machine by clicking 🚇 in the system tray.



The Printer Status Window is displayed.

2 Cancel the print job.

To cancel a print job that is currently printing

Click 📑.

Canon LBP6030/6040/6018L			
lob Options Help			
C) 66 🚱			
	Printing		*
			*
			Troubleshooting Details .
	# Job Information		
	ocument Name:	Document 1.rf	
U	ser Name:	User01	
Pi	inted Pages:	0	
			2 (*)

Printing of the current document is canceled.

To cancel a print job that is waiting

1 Select [Job] ▶ [Job Status].

Ganon LBP6030/6040/6018L	G 📕
ob Options Help	
Continue/Retry	
Cancel Job	
Job Status	
Print Queue	*

2 Select the document that you want to cancel, and click [Delete].

ob Status		-
Job Liot		
Document Name	Liber Name	Status
Document 1 st	U per 01	Printing
Document 2.tf	U ser01	Waiting
I LOCUMEN 3.10	U ser01	Waiting
		Reliesik Delete
		OK. Help

This screen displays up to five documents.

3 Click [OK].

Delete Job	
0	The selected job will be deleted. Click [OK] to delete the job and close the [Job Status] dialog box.
	OK Cancel

Printing of the selected document is canceled.

NOTE

Several pages may be output after you cancel printing.

TIPS

Canceling from the Remote UI (LBP6030w)

You can cancel printing from the [Job Status] page on the Remote UI. OChecking the Current Status of Print Documents

Canceling from an application

On some applications, a screen like the one shown below is displayed during printing. You can cancel printing by clicking [Cancel].



LINKS

Basic Print OperationsChecking the Print Status

Checking the Print Status

You can check the current print status in the Printer Status Window. This is convenient if you have been waiting for a long time for your document to be printed, and you want to see a list of the documents waiting to be printed.



2 Select [Job] ▶ [Job Status].

Canon LBP6030/6040/6018L	- C 🔀
Options Help	
Continue/Retry	
Cancel Job	
Job Status	
Print Queue	*
- III Goode	

➡ A list of up to 5 documents appears, showing documents that are being printed or waiting to be printed.

locument Name	Litter Name	Shukan
Document 1.#	Use01	Printing
Document 2.#	Used01	Waiting
Document 3.#	User01	Waiting
		Retron

TIPS

Checking from the Remote UI (LBP6030w)

You can check the print status on the [Job Status] page of the Remote UI. OChecking the Current Status of Print Documents

Checking the history of printed documents (LBP6030w)

You can check the history of documents that have been printed on the [Job Log] page of the Remote UI. When you cannot find printouts that you thought had been printed, you may want to check whether an error has occurred. Checking the History of Printed Documents

LINKS

Basic Print Operations
Canceling Print Jobs

Various Print Settings

There are a variety of print settings that you can use, such as enlarged/reduced printing and poster printing. Select the settings that you need for the document that you want to print.



©Enlarging or Reducing



OPrinting Posters



Printing Watermarks



Combining and Printing Multiple Documents



Collating Printouts by Page



OPrinting Borders



Printing According to the Document Type



Printing Multiple Pages Onto One Sheet



OPrinting Dates and Page Numbers



Saving Toner

Enlarging or Reducing




You can make enlarged or reduced printouts by using a preset print ratio, such as A5 to A4, or a custom print ratio that you set in increments of 1%.

Specifying the Print Ratio by Specifying the Original Document and Paper Size (Preset Ratio)

The print ratio is set automatically based on the document and paper size you have selected.

[Basic Settings] tab > Select the document size in [Page Size] > Select the paper size in [Output Size] > [OK]



Specifying the Print Ratio in Increments of 1%

[Basic Settings] tab > Select the [Manual Scaling] check box > Enter the print ratio in [Scaling] > [OK]

ł	Printing Preferences		
C	Basic Settings age Setup Rnishi	g Paper Source Quality	
	Profile:	<change> Default Settings - Add(1)</change>	Edit(2)
	Output Method: 🔛	Print -	
		Page Size:	Copies(G): 1 (1 to 999)
		Output Sze: Metch Page Sze	A @ Potrat A © Landscape
		Page Layout:	Manual Scaing
		1 1on 1 -	Scaling: 📃 🔅 1; [25 to 200]
		Binding Location:	
	🤪 🛄	Long Edge (Left)	Gutter
		Finishing:	
	A4 [Scaing: 707.]	or •	
	Vew Settings]	
	Restore Defaults		
			OK Cancel Help

NOTE

- Depending on the selected paper size, you may not be able to set an appropriate enlarging/reducing ratio. For example, there may be large blank spaces on your printout, or portions of the document may be missing.
- The enlarging/reducing settings on some applications take priority over those of the printer driver.

LINKS

Collating Printouts by Page



When printing copies of multi-page documents, you can use the collate function to print complete sets in sequential page order. This function is useful when preparing handouts for meetings or presentations.




[Basic Settings] tab > Select [Collate] or [Group] in [Finishing] > [OK]

Profile :	Change> Default Settings	→ Add(1) Edm(2)
Dutput Method:	🚔 Pint	-
9	Page Size:	Copies(G): 1 1 (1 to 999)
	- M	 Orientation
	Output Sae:	A @ Potrst A Clandscape
	Match Page Size	•
	Page Layout:	Manual Scaling
	1 1on 1	 Scaling: 100 (*)/(x) % (25 to 200)
	Binding Location:	
🤪 🕒	Long Edge [Left]	- Gutter
	Frishing	
A4 [Scaling: Auto]	Colure	•
Vew Settings		
Restore Defaults		
10,446 05 000	(B)	

👩 [Finishing]

Specify the sorting method of the printouts when printing multiple-page documents.



NOTE:

If you select [Off], whether the printouts are collated or not depends on the setting made in the application.

LINKS

Printing Multiple Pages Onto One Sheet



You can print multiple pages onto a single sheet. For example, you can print four or nine pages onto a single sheet by using [4 on 1] or [9 on 1]. Use this function if you want to save paper or to view your document in thumbnails.



[Basic Settings] tab \blacktriangleright In [Page Layout], select the number of page to print onto a single sheet \blacktriangleright In [Page Order], select the page distribution layout \blacktriangleright [OK]

	Printing Preferences	
ſ	Basic Settings age Setup F	nishing Paper Source Quality
ľ	Profile:	🖋 «Change» Default Settings 🔹 Add(1) Edit(2)
	Output Method:	- Post -
		Image: Page Size: Capier(S): 1(): [11:0:595] Image: Page Size: Operation Operation Operation Image: Page Size: Image: Page Size: Image: Page Size: Image: Page Size:
	3 4	Page Layout: Across from Left
	a 🗋	Fraing:
	A4 [Scaling: Auto]	or -
	Vew Settings Restore Defaults	P.
		OK Carcal Halp

[Page Layout]

Select the number of pages to print onto a single sheet from [1 on 1] to [16 on 1]. For example, to print 16 pages onto a single sheet, select [16 on 1].



NOTE:

- For options such as [Poster [2 x 2]], see OPrinting Posters.
- Printing may not be performed properly if you combine this setting with an application setting for collating printouts.

[Page Order]

Select a page distribution layout. For example, if you select [Across from Left], the first page is printed on the top left, and then the rest of the pages are arranged rightward.



LINKS


Printing Posters



You can print parts of a single document page onto multiple pages, which can then be combined to make a poster. For example, if you divide an A4 page into nine parts, print each part nine times larger, and then combine the parts, you will have a poster as large as nine A4 pages.



[Basic Settings] tab \triangleright In [Page Layout], select a poster size by specifying the number of parts to be printed, for example [Poster [3 x 3]] \triangleright [OK]



- There are four size settings: [Poster [1 x 2]], [Poster [2 x 2]], [Poster [3 x 3]], and [Poster [4 x 4]].
- Select the [Print Border] check box to add borders on your printouts. The borders are helpful if you want to paste the printouts together or cut off the margins.

LINKS

Basic Print Operations
 Enlarging or Reducing


Printing Borders



You can add borders, such as broken lines or double lines, in the margins of printouts.



[Page Setup] tab > Click [Page Options] > Select the border type in [Edging] > [OK] > [OK]



[Edging]

Selects the type of border to add to the document.

🚯 Preview

Displays a preview with the selected border.

LINKS

Basic Print Operations
 Printing Dates and Page Numbers
 Printing Watermarks


Printing Dates and Page Numbers



You can print information such as dates or page numbers, and you can specify where to print this information on the document (upper left, lower right, etc.).



[Page Setup] tab > Click [Page Options] > Select the printing position for the date, user name, and page number > [OK] (OK]



[Print Date]

Specifies the printing position for the print date.

[Print User Name]

Specifies the position to print the user name (logon name) of the person using the computer that printed the document.

[Print Page Number]

Specifies the position to print the page number.

Changing the Print Format of Dates and Page Numbers

You can change formatting details such as font and font size when printing dates, logon names, or page numbers. Click [Format Settings] on the [Page Options] screen shown above to specify the details.

LINKS

Basic Print Operations
 Printing Borders
 Printing Watermarks

Printing Watermarks

You can print watermarks such as "COPY" or "CONFIDENTIAL" on the document. You can create new watermarks or use pre-registered watermarks.



[Page Setup] tab > Select [Watermark] check box > Select the watermark type with [Watermark Name] > [OK]

Basic Setting	Page Setup	nishing Paper Source Quality		_
		Change> Default Settings	 Add(1) Edt(2) 	
Output Method	t:	🚔 Pint	•	
8		Page Size:	M	
		Output Size:	Match Page Size	•
		Copies:	1 (1 to 999)	
	1	Orientation	trat 🔺 🔿 Landscape	
	<u>h</u>	Page Layout:	1 1 on 1	•
-1.4		Manual Scaling		
A4 [Scaling: A	luto]	Scaling	100 🗇 🎘 (25 to 200)	
W	ew Settings	Watemark Watemark Name:	CONFIDENTIAL	
	(Edit Watermark	
		Custon Paper Size	Page Options Restore Defaults	

[Watermark]/[Watermark Name]

Select the [Watermark] check box to display a list of watermarks in the [Watermark Name] drop-down list. Select a watermark to use from the list.

🚯 [Edit Watermark] 🗾

Displays the screen to create or edit watermarks.

Edit Watermark		×
	Watemaik Liet 4CDPY 4CDPY 4FLE COPY 4FLE COPY 4FRELINNERY 4FRELI	Add
None: Atributes Algement Print Style	Sangle	
Test: Font:	Sample	
Style:	Regular -	
Silet	72 Points [1 to 500]	
Color	Medium Gray -	
	05	Cancel Help

[Add] 📀

Click to create a new watermark. Up to 50 watermarks can be registered.

🔞 [Name]

Enter the name of the new watermark.

[Attributes]/[Alignment]/[Print Style]

Click each tab to specify the text, color, or print position of the watermark name. For more information about the settings, click [Help] on the printer driver screen.

LINKS

Printing BordersPrinting Dates and Page Numbers

Printing According to the Document Type



You can specify the document type to ensure optimal image quality. There are different settings for photo documents, documents that have charts or graphs, and documents that have design drawings with fine lines.



[Quality] tab > Select the document type in [Objective] > [OK]

Printing Preferences Basic Settings Page Setup	Rnishing Paper Sours	
Profile:	🖋 «Change» Default Settings	Add(1) Edit(2)
Cuput Method:	Part	General Placatione Guptes Designs [CAD] The node is best suited for priving photo images.
View Settings	🖭 Manud Grancele Settings	Advanced Settings Gregoratio Settings Root. Pedice Details
		OK Cancel Help

[Objective]

Select an option that suits the document type or purpose of printing. For example, select [General] for general use, or select [Photos] when you want to print photo images in optimal print quality.

[General]	A versatile option that is suitable when printing most documents.
[Publications]	Suitable when printing documents that have a mix of photo images, charts, and graphs.
[Graphics]	Suitable when printing documents that have charts or graphs.
[Photos]	Suitable when printing photo images.
[Designs [CAD]]	Suitable when printing design drawings that have many fine lines.

NOTE:

To specify detailed settings for each item selected with [Objective], click [Advanced Settings]. For more information about the settings, click [Help] on the printer driver screen.

LINKS

Saving Toner



You can set the printer driver to print documents using less toner.

IMPORTANT

When the save toner setting is enabled, fine lines and sections with lighter density may be less sharp that normal.



[Quality] tab \blacktriangleright Select the document type in [Objective] \blacktriangleright Click [Advanced Settings] \blacktriangleright Select [Toner Save] in the [Advanced Settings] screen \blacktriangleright Select [On] from the drop-down list \blacktriangleright [OK] \blacktriangleright [OK]

Printing Preferences		
Basic Settings Page Setup	Rnishing Paper Sourc Quality	
Profile:	🖊 «Change» Default Settings	✓ Add(1) Edt (2)
Output Method:	🛱 Rint	•
	Clastive:	[Senera] Autocolorus Gaphics Patar Desgra (CAO)
	1	This mode is best suited for printing publications that include photo images and graphics.
		Advanced Settings
Vew Settings	Manual Grayscale Settings	Grayscale Settings
		About Restore Defaults
		OK Cencel Help

setting Item	Contents
Tendering Flate	248PP
I diagona	E-street 1
Conser Slaves	ûn
una pany	DIO INDI HAQAN
wavenoed Sneoothing	Smooth 1
Tensity Fine Adjustment	0 (Standard)
3 utput: Adjustment Mode	On
THE S AVE:	
'n	•

[Objective] OPrinting According to the Document Type

Selects the document type for which you want to enable the save toner setting.

[Advanced Settings]

Displays a screen with a list of advanced settings. Click [Toner Save] and select [On] from the drop-down list at the bottom of the screen.

NOTE:

- You can specify whether to enable the save toner setting for each document type. Specify the save toner setting for each document type listed in [Objective].
- In the [Advanced Settings] screen, you can specify various print settings other than [Toner Save] settings. For more information about the settings, click [Help] on the printer driver screen.

LINKS

Combining and Printing Multiple Documents




By using Canon PageComposer, you can combine multiple documents into one print job and print the job with specified print settings. For example, this function enables you to combine documents made with different applications and print all of the pages in the same paper size.

1 Open a document in an application and display the print dialog box.

How to display the print dialog box differs for each application. For more information, see the instruction manual for the application you are using.

2 Select this machine and click [Preferences] or [Properties].



3 Select [Edit and Preview] in [Output Method].

■ Click [OK] on the [Information] pop-up screen ► Click [OK] in the printer driver screen.

Printing Preferences
Basic Settings Page Setup Rnishing Paper Source Quality
Prolie: • Default Settings • Add(1) Edit(2)
Dulput Method:
Capitad Capital Capita
At [Scaling: Aite] Off
Vew Setings Resour Dotaits
OK Carcal Hep

4 Click [Print] or [OK].

🖶 Print	×
General	
Select Plinter	
物-Add Printer 間 Canon LBP6030/6040/6018L 曲Fax	Microsoft XPS Document
<	P
Status: Ready	Print to file Preferences
Location: Comment:	Find Pinter
Page Range	
® AI	Number of copies: 1 🚔
Selection Current Page	
Pagea: 1-65535	Color -Q-Q-Q
Enter either a single page number or a single page range. For example, 5-12	11 22 33
Per	t Cancel Apply

Canon PageComposer starts. Printing does not start in this step.



The documents are added in Canon PageComposer.

유명의 대학	电隙度群		
Document Name	Pages	Layout Informati. Comments	
Document 1.rtf	1	1 on 1	
Document 2.rtf	1	1 on 1	
Document 3.tf	1	1 on 1	

6 From the [Document Name] list, select the documents to combine, and click

• To select multiple documents, click the documents while holding down the [SHIFT] key or [CTRL] key.

🖉 Canon PageComposer - Canon LBP6030/6040/6018L - User01				
File Edit Moveto Help	_			
42% F0 🕒	2) IF B	P L		
Document Name	Pages	Layout Informati. Comments		
Document 1.tf	1	1 on 1		
Document 2.rtf	1	1 00 1		
Document 3.rtf	1	1 on 1		
1				

7 Change the settings as necessary, and click [Combine].

The documents selected in step 6 are combined.

Combine				
Document Name:	Combined Documents 1			
Sheets: 2	44 A4		Debte	a
Document List Pr	ist Settings			e
Copies:	1 🖈 [1 to 999]	Output Size Consistency:	A4 •	
Print Style:	1-Sided Printing	Cayout Consistency:	2 on 1 •	ſ.
		Page Order		-
		Print Next Document from	Same Side 🔹	
			Detalo	C
		Restore Defaults	Combine Cancel Help	

[Print Preview]

Displays a preview of the document to be printed.

[Document List]/[Print Settings]

Click the [Document List] tab to display the documents added in steps 1 to 4. You can remove documents by selecting them in the list and clicking [Delete from List].

Document Name	Pages	Layout Information	
Document 1.vt	1	2 on 1	
Document 2 nt		2 on 1	12
Document 3./f	i	2 on 1	50 20 32
			Delete from Lid

Click the [Print Settings] tab to display the screen for specifying print settings such as the number of copies. The settings specified here are applied to the whole print job.

	Print Setting:		Pint Preview.
Document Li Copies:	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	Output Size Consistency:	A4 •
Print Style:	1-Sided Printing	Leyout Consistency:	2 on 1 •
		Page Order	Left to Right -
		Print Next Document from	Same Side 🔹
			Detailo
		Restore Defaults	Combine Cancel Help

NOTE:

For more information, click [Help] on the Canon PageComposer screen.

ឲ [Details]

Displays the print settings screen of the printer driver. There are fewer settings available than when using the ordinary printing method.

8 In the [Document Name] list, select the combined-document print job you want to print, and click 🖳



Printing starts.


To cancel printing, see Canceling Print Jobs.

LINKS

Basic Print OperationsPrinting Multiple Pages Onto One Sheet

Configuring Print Settings to Your Needs

You can register combinations of settings as "profiles" to suit your different printing objectives. Also, you can register the settings that you frequently use as the default settings. Once the default settings are registered, they are displayed automatically in the printer driver screen, and you can skip the operations to specify them and proceed to printing immediately.



Registering Combinations of Frequently Used Print Settings

Specifying combinations of settings such as "1-sided landscape orientation on A4 size paper in save toner mode" every time you print is time consuming. If you register your frequently used combinations of print settings as "profiles," you can specify print settings simply by selecting one of the profiles from the list. This section explains how to register profiles and how to print using profiles.

Registering a Profile Selecting a Profile

Registering a Profile

1 Change the settings that you want to register as a profile, and click [Add].

Make print settings as required on the [Basic Settings], [Page Setup], [Finishing], [Paper Source], and [Quality] tabs. OVarious **Print Settings**

Printing Preferences		
Basic Settings Page Set.	p Rnishing Paper Source Quality	
Profile :	🖋 «Change» Default Settings	- Add(1) Edit(2)
Output Method:	🛗 Pivit	-
0.0	Page Size:	Copies(Q): 1 (\$ 110 999)
	A 100 M	 Orientation



2 Enter a profile name in [Name], select an icon, and then click [OK].

- As necessary, enter comments about the profile in [Comment].
- Olick [View Settings] to see the settings that will be registered.



NOTE

Editing a profile

By clicking [Edit] on the right side of [Profile] on the screen shown in step 1, you can change the name, icon, or comment of the profiles you have previously registered. However, you cannot edit the pre-registered profiles.

Selecting a Profile

Simply select the profile that suits your objective, and click [OK].

Printing Preferences		
Basic Settings Page Setup Rhishing	Paper Source Quality	
Prolle:	Sample - Add(1)	Edtr(2)
Output Method: 🚊 P	int -	
	Page Son. Ad * Odgot Son. Match Page Son * Match Page Son * * Page Leynut: 2 2 con 1 * Brindry London: tong Edge [fred] *	Copen(2): 1 () 1 999(Overlation A @ Potent A Condicage Page Order: Laft to Rigit Catter
At [Scaling: Auto]	Finishing:	
Vew Settings Restore Defaults		
		OK Cancal Help

NOTE

Changing the settings of the currently selected profile

You can change the settings of the currently selected profile. In addition, the changed settings can be registered as another profile.

LINKS

Basic Print OperationsChanging Default Settings


Changing Default Settings

The default settings are the settings that are first displayed whenever you open the print settings screen of the printer driver. You can change these settings to the settings that you use most often. For example, if you always want to print 2 document pages on each printout page, set [2 on 1] as the default page layout setting. From the next time that you open the printer driver screen, the setting will always be [2 on 1], eliminating the need to change this setting every time you make prints.

IMPORTANT

To perform the following procedure, log on to your computer with an administrator account.

- **Open the printer folder.** Open the Printer Folder
- 2 Right-click the icon of the machine and then click [Printing preferences].



- 3 Change the settings on the printing preferences screen, and click [OK].
 - Make print settings as required on the [Basic Settings], [Page Setup], [Finishing], [Paper Source], and [Quality] tabs. Various Print Settings

Basic Settings Page Setup Rnir	hing Paper Source Quality	
Profile:	Change> Default Settings	- Add(1) Edit(2)
Output Method:	g Pilet	•
9	Page Size	Copies(Q): 1 1 [1 to 999]
	* A4	Orientation
	Output Stee:	A @ Potrat A C Landscape
1 2	Match Page Size Page Layout:	Page Order:
	2 2 on 1	- Left to Right -
	Briding Location:	
	Long Edge [Top]	Guter
	Finishing:	
A4 [Scaling: Auto]	or in the second	
Vew Settings		
Restore Defaults		
_		
		OK Cancel Apply Help

LINKS

Basic Print Operations

Registering Combinations of Frequently Used Print Settings

Network LBP6030w

This machine has been designed for flexibility of use across a variety of environments. In addition to basic network features, it includes advanced network technologies. Make the required settings depending on your network environment. Do not worry if you are not a network expert, because the machine has also been designed for convenience and ease of use. Relax and proceed with the network setup one step at a time.

Connecting to a Computer/Viewing the Machine's Network Settings




Connecting to a Network



OViewing Network Settings



Configuring for Printing from a Computer



Customizing the Machine for a More Convenient Network Experience

Configuring the Machine for Your Network Environment

Connecting to a Network LBP6030w

You can connect the machine to a wireless LAN network, and you can use a unique IP address within the network. For specific IP address settings, contact your Internet service provider or network administrator.



IMPORTANT

If the machine is connected to an unsecured network, your personal information might be leaked to a third party.

NOTE

- The machine does not come with a router. Have a router ready as necessary.
- If you are not sure whether your router supports wireless LAN, see the instruction manual provided with the router, or contact the manufacturer.

Before You Start

Follow these steps to connect the machine to a network.



Check the device and network settings.

- Have the computer and the router been connected properly? For more information, see the instruction manuals for the devices you are using, or contact the device manufacturers.
- Make sure that the network settings have been completed on the computer. If the network has not been set up properly, you will not be able to use the machine on the network, even if you perform the rest of the procedure below.

NOTE:

To check the machine's MAC address **OViewing Network Settings**



Connect to the wireless LAN. Connecting to a Wireless LAN



Set the IP address as necessary.

This step is required when you want to assign a specific IP address to the machine or change the dynamic IP addressing protocol from the default DHCP.

Setting IP Addresses

Connecting to a Wireless LAN LBP6030w

Wireless routers (or access points) connect the machine to a computer via radio waves. If your wireless router is equipped with Wi-Fi Protected Setup (WPS), you can configure your network with a simple button push. If your networking devices do not support automatic configuration, or if you want to specify authentication and encryption settings in detail, you need to set up the connection manually. To make wireless settings for this machine, use the MF/LBP Network Setup Tool from your computer. Make sure that your computer is correctly connected to the network.



IMPORTANT

Log on as an administrator

To perform the following procedure, log on to your computer with an administrator account.

Risk of information leak

Use wireless LAN connection at your own discretion and at your own risk. If the machine is connected to an unsecured network, your personal information might be leaked to a third party because radio waves used in wireless communication can go anywhere nearby, even beyond walls.

Wireless LAN security standards

This machine supports the following wireless LAN security standards. For the wireless security compatibility of your wireless router, see the instruction manual or contact the manufacturer.

- 128 (104)/64 (40) bit WEP
- WPA-PSK (TKIP/AES-CCMP)
- WPA2-PSK (TKIP/AES-CCMP)


NOTE

Required devices for wireless LAN connection

- The machine does not come with a wireless router. Have the router ready as necessary.
- The wireless router must conform to the IEEE 802.11b/g/n standards and be able to communicate in the 2.4 GHz band. For more information, see the instruction manual for your wireless router or contact the manufacturer.

Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.

Click [Start Software Programs].




NOTE:

- If the above screen does not appear ODisplaying the [CD-ROM/DVD-ROM Setup] Screen
- If [AutoPlay] is displayed, click [Run MInst.exe].

3 Click [Start] for [MF/LBP Network Setup Tool].




4 Follow the on-screen instructions to configure the wireless LAN settings.



NOTE:

If there is something you do not understand

Click [Useful Tips] at the bottom left of the screen to display troubleshooting tips.




LINKS

Connecting to a Network

Setting IP Addresses LBP6030w

Connecting the machine to a network requires an IP address that is unique in that network. There are two types of IP addresses: IPv4 and IPv6. Use the type required by your network environment. Note that before you can use an IPv6 address, you first need to properly configure an IPv4 address.




Setting IPv4 Address LBP6030w



The machine's IPv4 address can be either assigned automatically by a dynamic IP addressing protocol, such as DHCP, or entered manually.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].



3 Click [Network Settings] ▶ [TCP/IP Settings].

C 0 2 http://132.168.0.215/m_1 LUPE030wr5011	etwork/ster/ w/LUPS009w8010w/		P = E C X () () To Portel Login User: System Manager Log
Settings/Registration			Mail to System Manag
Preferences = Display Settings = Timer Settings	SettingsRegistration. System W Network Settings	aragement Seltings. Network Settings	
dig uternet Maintenance © Unity Mane System Management Settings © System Management © System Management © Network Settings © Instacto Setting Promaten	TCAVE Settings	Ph-1 Settings III-U Settings UKD Settings UKD Verit Settings Net Discher Settings Net Discher Settings Physicistic Settings Settings Settings KHTP Settings Million Settings	

4 Click [Edit] in [IPv4 Settings].



5 Set the IP address.

C C R http://182.068.0.215/m.net	work instation		P-BCK 0 1
	rLIP6030w6010wJ	To Portal	Login User: System Menager Log Ox
Settings/Registration			Mail to System Manager
relerences	Settings/Registration System Manager	ment Settings: Network Settings > TCP/IP Set	tings > Edit IPv4 Settings
= Display Settings	Edit IPv4 Settings		2
Timer Settings djustment/Maintenance	Change the following settings. Changes will be effective after the m	ain power is turned CFF and ON.	
Utility Menu ystem Management Settings			OK Cancel
System Management	IP Address Settings		
Security Settings	Auto Acquire		
Network Settings	"JAuto Acquire] will be Off if [Select Pr	stoce[] and [Auto IP] are set to [Off].	
Initialize Setting Information	Select Protocol	C#	
	Auto IP:	0# -	
	IP Address:	192.168.0.215	
	Subnet Mask:	255 255 255 D	
	Galeway Address:	0.0.00	
	DNS Sottings		
	Primary DNS Server Address:	0.00	
	Secondary DNS Server Address	0.0.0.0	
	Host Name:	Carent2tant73	

Automatically assigning an IP address

1 In the [Select Protocol] list, select [DHCP], [BOOTP], or [RARP].

NOTE:

If you do not want to use DHCP/BOOTP/RARP to assign an IP address automatically

Select [Off]. If you select the [DHCP], [BOOTP], or [RARP] protocol when these services are unavailable, the machine will waste time and communications resources searching the network for these services.

2 Check that [Auto IP] is set to [On].

If [Off] is selected, change the setting to [On].

NOTE:

Even if Auto IP is enabled, IP addresses assigned via DHCP/BOOTP/RARP override an address obtained via Auto IP.

Manually entering an IP address

- **1** Select [Off] for [Select Protocol] and [Auto IP].
- 2 Set the [IP Address], [Subnet Mask], and [Gateway Address] fields.

6 Click [ОК].

Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

NOTE

Checking whether the settings are correct

Make sure that the Remote UI screen can be displayed with your computer. Starting the Remote UI

If you change the IP address after installing the printer driver

If you are using an MFNP port, and the machine and the computer are in the same subnet, then the connection will be maintained. You do not need to add a new port. If you are using a standard TCP/IP port, then you need to add a new port. **Configuring Printer Ports**

* If you are not sure which type of port you are using, see [] Checking the Printer Port.

LINKS

Setting IPv6 Addresses
 Viewing Network Settings
 Configuring WINS

Setting IPv6 Addresses LBP6030w



Use the Remote UI to set IPv6 addresses. Before setting IPv6 addresses, make sure that the IPv4 address has been set correctly (**Viewing Network Settings**). You can register up to nine of the following IPv6 addresses.


Туре	Maximum number available	Description
Link-local address	1	An address that is valid only within a subnet or link and cannot be used to communicate with devices beyond a router. A link-local address is set automatically when the IPv6 function of the machine is enabled.
Manual address	1	An address that is entered manually. Specify the prefix length and default router address.
Stateless address	6	An address that is generated automatically using the MAC address of the machine and a network prefix that is advertised by the router. Stateless addresses are discarded when the machine is restarted (or turned ON).
Stateful address	1	An address obtained from a DHCP server using DHCPv6.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

hanang,	Device Name: Product Name: Location:	LBP5030w/5018w LBP5030w/6018w	Login User: System Manager Log O
Remote UI: Portal			Mail to System Manage
		Last Updated 01/01 2015 03 34:20 PM	Status Monitor/Cancel
Jevice Basic Information			V
Device Status			SettinguRegistration
Printer: Roady to print.			470
Error Information			
No errore.			
Sepport Link			
Support Link:			

3 Click [Network Settings] ▶ [TCP/IP Settings].



4 Click [Edit] in [IPv6 Settings].

			0.5 2
C C C R http://182.068.0.215/m_net	work_topip.html		P+B6X 0 0 0
	DHCP Option Settings		
	Acquire Host Name:	On	
	DNS Dynamic Update:	017	
	IPv6 Settings		
			Ed.
	P Address Settings		
	Use Pv6:	08	
	WINS Settings		
			Edt.
	WINS Resolution	08	
	LPD Print Settings		
			Eas-

5 Select the [Use IPv6] check box and configure the required settings.

System Management			
Security Settings	IP Address Settings		
Network Settings	Use Pv6	0000.0000.0000.0000.0000.0000.0000	
initialize Setting Information	Link-Local Address:	0000:3333.0656.0000-3332.6666.3030.3333	
	Prefix Length:	1	
	Statoloss Addross		
	Stateless Address 1:	0000.0000.0000.0000.0000.0000.0000	
	Prefix Length 1:	0	
	Stateless Address 2:	0000.0000.0000.0000.0000.0000.0000	
	Prefix Longih 2:	0	
	Stateless Address 3:	0000:0000:0000:0000:0000:0000:0000	
	Prefix Length 3:	0	
	Stateless Address 4:	0000.0000.0000.0000.0000.0000.0000	
	Prefix Length 4:	0	
	Stateless Address 5:	0000.0000.0000.0000.0000.0000.0000	
	Prefix Length 5:	0	
	Stateless Address 6:	0000.0000 0000 0000 0000 0000 0000 0000	
	Prefix Length 6:	0	
	Use Manual Address		
	IP Addreas:	0000 0000 0000 0000 0000 0000	
	Prefix Length:	64 (0-128)	
	Default Router Address:	000 0000 0000 0000 0000 0000	
	11 Use DHCPv6		
	State M Address	0000-0000-0000-0000-0000-0000-0000	
	Prefix Length:	0	
	DNS Settings		
	Primary DNS Server Address:	0000.0000.0000.0000.0000.0000.0000.000	
	Secondary DNS Server Address:	0000-0000-0000-0000-0000-0000-0000	
	2 Une Same Host Name/Domain	Namo as IP+4	

[Use IPv6]

Select the check box to use IPv6 on the machine. Clear the check box if you do not want to use IPv6.

[Stateless Address]

Check to use stateless addresses. Clear the check box if you do not want to use stateless addresses.

[Use Manual Address]

When you want to enter an IPv6 address manually, select the check box and enter values in the [IP Address], [Prefix Length], and [Default Router Address] text boxes. Clear the check box if you do not want to enter a manual address.

[IP Address]

Enter an IPv6 address. Addresses that start with "ff" (multicast addresses) and the loopback address (::1) cannot be entered.

[Prefix Length]

Enter the length (number of bits) of the network portion of the address.

[Default Router Address]

Specify the default router address, as necessary. Addresses that start with "ff" (multicast addresses) and the loopback address (::1) cannot be entered.

[Use DHCPv6]

Select the check box to use the stateful address. Clear the check box if you do not want to use the stateful address.

6 Click [ОК].

LUPGODwr9010w	LEP5030w/6010w J	To Portal Login User: System Manager Log		
Settings/Registration		Meil to System Mere		
Preferences	Settings/Registration: System Ma	nagement Settings. Network Settings > TCP/IP Settings > Edit IPv6 Settings		
Display Settings Timer Settings	Edit IPv6 Settings			
AdjustmentMaintenance Utility Mene System Management Settings U System Management		the main power is turned OFF and ON		
Security Settings	IP Address Settings			
Network Sellings Initialize Setling Information	Use IPv6 Link-Local Address: Prafix Length: IV Statelees Address	0000-0000 1000 0000 0000 1000 0000 0000		
	Stateless Address 1:	0000.0000.0000.0000.0000.0000.0000		
	Profix Longth 1:	0		

Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

NOTE

Checking whether the settings are correct

Make sure that the Remote UI screen can be displayed with your computer by using the IPv6 address of the machine. Starting the Remote UI

If you change IP addresses after installing the printer driver


You need to add a new port. Configuring Printer Ports

LINKS

Setting IPv4 AddressViewing Network Settings

Viewing Network Settings LBP6030w

Press this machine's 🛓 (Paper) key and hold it down for 3 seconds to print a partial list of network settings. This allows you to check IPv4 settings, the MAC address, and wireless LAN settings. The setting list is formatted to print on A4 size paper. Before printing, load A4 size paper in the multi-purpose tray. OLoading Paper in the Multi-Purpose Tray



Output example:

	sas User Data List see	

Controller ROM Version		
Main Controller		
Boot ROM		
Language		
DCON	0.00	
***************************************	ireless LAN Error Information	,
	No errors, (01)	

***********************	**********	
1.Product Information		
1.Product Information Product Name	LBP8030#/6018#	
Product Name	LBP6030w/8018w	
Product Name 2.TCP/IP Settings	LBP8030w/8018w	
Product Name 2.TCP/IP Settings	LBP6030w/6018w	
Product Name 2.TCP/IP Settings IPv4 Settings Auto Obtain Select Protocol	011 011	
Product Name 2. TCP/IP Settings IPv4 Settings Auto Obtain Select Protocol Auto IP	off off off	
Product Name 2.TCP/ID Settings 104 Settings Auto Obtain Select Protocol Auto IP IP Address	off off off 192.168.0.215	
Product Name 2.TFP/IP.Setfings Auto Obtain Select Protocol Auto IP IP Address Submet Mask	0ff 0ff 0ff 192.168.0.215 235.255.0	
Product Name 2.TCP/IP Settings IPv4 Settings Auto IP IP Address	off off off 192.168.0.215	
Product Name 2.TFP/IP.Setfings Auto Obtain Select Protocol Auto IP IP Address Submet Mask Gateway Address	0ff 0ff 0ff 192.168.0.215 235.255.0	
Product Name 2.TFP/IP.Setfings Auto Obtain Select Protocol Auto IP IP Address Submet Mask Gateway Address	0ff 0ff 0ff 192.168.0.215 235.255.0	
Product Name 2. TCP/ID Settings Auto Obtain Select Protocol Auto IP IP Address Submet Mask Gateway Address 3. Wireless LAN Settings	0ff 0ff 0ff 192.168.0.215 235.255.0	
Product Name 2.TFP4/IP.SetLines IP4 SetLines Auto Obtain Select Protocol Auto IP IP Address Subnet Mask Gateway Address MAC Address SSID SetLings Security	0ff 0ff 0ff 192.168.0.215 235.255.0	
Product Name 2.TCP/IP Settings Auto Obtain Select Protocol Auto IP IP Address Subnet Mask Gateway Address 3.Wireless LAN Settings MAC Address SSID Settings SSID Settings SSID Settings SSID Settings	0ff 0ff 122.168.0.213 255.255.255.0 0.0.0.0	
Product Name 2.TCP/ID Sattings Auto Obtain Select Protocol Auto IP IP Address Subnet Mask Gateway Address 3.Wireless LAN Settings MAC Address SSID Settings Security WFA/WFA2-PSK Settings Encryption for WFA/WFA2	0ff 0ff 192.168.0.215 255.255.0 0.0.0.0 WPA/WPA2-PSK Auto	
Product Name 2.TCP/IP Settings Auto Obtain Select Protocol Auto IP IP Address Subnet Mask Gateway Address 3.Wireless LAN Settings MAC Address SSID Settings SSID Settings SSID Settings SSID Settings	0ff 0ff 122.168.0.213 255.255.255.0 0.0.0.0	

6 IPv4 Settings

Lists IPv4 settings.

Auto Obtain

Displays whether the IP address is assigned automatically by a protocol such as DHCP. "On" is displayed if automatic addressing is enabled.

Select Protocol

Displays the protocol used to assign the IP address automatically.

Auto IP

Displays whether Auto IP is enabled or disabled.

IP Address

Displays the IP address.

Subnet Mask

Displays the subnet mask.

Gateway Address

Displays the gateway address.

NOTE:

- The IP address is not correctly configured if it is displayed as "0.0.0.0".
- Connecting the machine to multiple switching hubs or bridges for redundancy may result in a connection failure even when the IP address is correctly configured. This problem can be solved by setting a certain interval before the machine starts communicating. **Osetting a Wait Time for Connecting to a Network**

() Wireless LAN Settings

Displays MAC address and wireless LAN settings.

MAC Address

Displays the MAC address.

SSID Settings

Displays SSID settings.

Security

Displays the currently applied security settings. If the security settings have not been configured, "None" is displayed.

Wireless LAN Status

Displays the connection status (signal strength) of the wireless LAN. If the machine is not connected, "Inactive" or "Disconnected" is displayed.

NOTE

Note that you cannot check IPv6 settings and some other network settings on this setting list. If you want to check all network settings, print them by selecting [Network Status Print] in the Printer Status Window. **Printing Setting Lists**

LINKS

Connecting to a Wireless LAN Setting IPv4 Address

Configuring for Printing from a Computer LBP6030w

When using the machine as a network printer, you can configure the protocols and ports used for printing. Before starting, make sure that you have completed all basic preparations for printing (Printer Driver Installation Guide).



NOTE

- Printing protocols are rules for delivering document data created on a computer to the machine. You can select them according to the printing purpose or the network environment.
- Ports are gateways for passing printing data from a computer to the machine. Incorrect port settings are often the cause when documents cannot be printed from a network computer.

Setting Up a Print Server

By setting up a print server on the network, you can reduce the load on the computer that you print from. This also makes it possible to install printer drivers over the network, which saves the trouble of installing the drivers on each computer by using the CD-ROM/DVD-ROM. For information about how to set up a print server, see Printer Driver Installation Guide.

Configuring Printing Protocols and Web Services LBP6030w

The following explains how to configure printing protocols for printing documents from computers. The protocols supported by the machine are LPD, RAW, and WSD (Web Services on Devices).

NOTE

To change protocol port numbers **OChanging Port Numbers**

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

laments,	LIP6000w5019w LBP6000w5019w	Login User: System Manager Log (
Remote UI: Portal		Mail to System Manag
	Last Updated 01101 2015 03 34:20 PM	Status Monitos/Cancel
Jevice Basic Information		V
Device Status		SettinguRegistration
Printet: Roady to print.		470
Error Information		
No errore.		
Sepport Link		
Support Link:		

3 Click [Network Settings] ▶ [TCP/IP Settings].

Color Report 182 2660 215 im, not LUPCOLORISOLDW Settings/Registration	venkhani / LEP5039w/8010w3		P = 0 C X C C C C C C C C C C C C C C C C C
Preferences Daylay Definings Trace Settings AdjustmethAltreance 0 UBIN Mercapement Settings System Kanagement 0 Secretar Settings Neurob Settings Neurob Settings Neurob Settings	SedrogaTegintakint System W Richardk Sottlingin Richardk Sottlingin Richardk Sottlingin (TEAR Bellingin	In agenesit Sellings, Network, Settings Invis Hartings Invis Hartings Invis Hartings UKID Sellings NetWither Sellings Web Oxford Set, Sellings Autor Sellings Setting Sections Matter Sellings	
	SMMP Settings	ENNIPY1 Detings	

4 Configure the printing protocols.

Configuring LPD or RAW

1 Click [Edit] in [LPD Print Settings] or [RAW Print Settings].

-			
C 🕞 😵 http://182.068.0.215/m_netw	ork,topip.html		P-26× 0 ℃ 0
	WINS Resolution:	01	*
	LPD Print Settings		
			Edt.
	Use LPD Printing:	On	
	NetBIOS Settings		
			Edt
	NetBIOS Name:		
	Workgroup Name:		
	RAW Print Sottings		
			Edi.
	Use RAW Printing	On	
	WSD Settings		

2 Configure the settings as necessary.

C	twork, (pd, adit.html	P-16X 0 0
LUP6030wr6010v	/1.0P5030w/6018w3	To Postal Login User: System Manager Log On
(A) Settings/Registration		Mail to System Manager
Peterences Dialysis Settings Trace Settings Adjustment Maintenance Utility Mane System Management Settings System Management Settings Network Settings Instruct	Selfregal Registration System Warapeneet Selfreg Cent LPD Free Sentrage Charges will be effective after the main power in LPD Privat Sentrage Status D'Privates Sector Sector Secto	n Notosh Betrigs > TCPNP Betrigs > Edit UPD Part Settings tuned OPP and ON.
		Copyright CAVCIV INC. 2013

[Use LPD Printing]

Select the check box to print using LPD. Clear the check box if you do not want to use LPD printing.

[Use RAW Printing]

Select the check box to print using RAW. Clear the check box if you do not want to use RAW printing.

3 Click [OK].

Configuring WSD

1 Click [Edit] in [WSD Settings].

			P-10 X
🗧 💿 🔞 http://182.068.0.215/m_netv	rork, topip html		P-BdX 0 00
	Use RAW Printing:	On	
	WSD Settings		Est.
	Use WSD Printing:	On	
	Use WSD Browsing	On	
	Use Multicast Discovery:	On	
	SSI. Settings		
			Key and Certificate
	Key and Certificate Settings	Not set.	
	Functions that use SSL		
	Remote UI		
	Multicast Discovery Settings		

2 Configure the settings as necessary.

C 84 http://182.068.0.215/vvneb	reikuvaduelikäted	P-16X 0 0 0
LIPG030w/6015w	(LBP5839w/6018w.)	To Portal Login User: System Manager Log Out
(i) Settings/Registration		Mail to System Manager
Professoria -> Display Settings -> Trace Settings -> Other Settings -> UB3 More -> UB3 More -> System Settings -> Securb Settings -> Initiatize Setting Information	Settings/Englishtalan System Konogeneed Settings Network Settings - Coll (RS) Sectings Changes & Collecting Settings, Changes will be effective after file root power is turned CPT and CN WISD Settings (Une WISD Settings (Une WISD Settings) (Une WISD Settings) (Une WISD Settings) (Une WISD Settings) (Une WISD Settings) (Une WISD Settings)	CDRIP Settings > Edit VSD Settings
		Our control (10 000)

[Use WSD Printing]

Select the check box to print using WSD. Clear the check box if you do not want to use WSD printing.

[Use WSD Browsing]

Select the check box to obtain information about the machine from a computer via WSD. This check box is selected automatically when the [Use WSD Printing] check box is selected.

[Use Multicast Discovery]

Select the check box to set the machine to reply to multicast discovery messages. If the check box is cleared, the machine stays in sleep mode even when it receives a multicast discovery message from the network.

3 Click [OK].

Restart the machine.

Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

NOTE

Setting up WSD network devices on Windows Vista/7/8

Install the printer driver according to the procedure using WSD ports described in the Printer Driver Installation Guide.

LINKS

Configuring Printer Ports


Configuring Printer Ports LBP6030w

Printing errors can occur when the print protocol settings of the machine have been changed, or when a printer has been added via the Windows printer folder. These errors are typically caused by incorrect printer port settings, for example when a computer specifies an incorrect printer port number or type in the printer driver. To fix this type of problem, configure the printer port settings on the computer.


IMPORTANT

To perform the following procedure, log on to your computer with an administrator account.

- **Open the printer folder.** Open the Printer Folder
- 2 Right-click the icon of the machine and click [Printer properties] or [Properties].



3 Click the [Ports] tab and configure the required settings.



Adding a port

When an incorrect port was selected while installing a printer driver from the Windows printer folder, add a new port. There are two types of port: "MFNP Port" and "Standard TCP/IP Port." Select the port type according to your environment.

MFNP Port	This is a port that allows the IP address of the machine to be detected automatically. Even if the IP address of the machine is changed, the connection is maintained, provided that the machine and the computer are in the same subnet. You do not need to add a new port every time the IP address is changed. If you are using the machine in an IPv4 environment, you should normally select this type of port.
(only for IPv4	IMPORTANT:
environment)	You can add an MFNP port only when you installed the printer driver from the User Software CD-ROM/DVD-ROM, or when you downloaded and installed the printer driver from the Canon website.
Standard TCP/IP Port	This is a standard Windows port. When you use this type of port, you need to add a new port every time that the IP address of the machine is changed. Select this type of port when you are using the machine in an IPv6 environment and when you cannot add an MFNP port.

Adding an MFNP port 🗾

- 1 Click [Add Port].
- 2 Select [Canon MFNP Port] in [Available port types] and click [New Port].



3 Select [Auto Detect] and select the machine when it is detected, and then click [Next].



NOTE:

If the machine is not detected

Click [Refresh]. If the problem persists, select [IP address] or [MAC address], enter the IP address or MAC address of the machine (**Viewing Network Settings**) and then click [Next].

	Loolect (P address) or (MAC address) in the required information. If you refeat (Auto the list
P address MAC address	192 . 160 . 0 . 215
Auto Detect Nodel	NAC address IP address
	Stop Refresh
Help	Next> Cancel

- 4 Click [Add] > [Finish].
- 5 Click [Close].

Adding a standard TCP/IP port 🗾

- 1 Click [Add Port].
- 2 Select [Standard TCP/IP Port] in [Available port types] and click [New Port].

Printer Ports	
Available port types	
Canon MFNP Port	
Standard TCP/IP Pert	
New Port Type	New Port Cancel

- **3** Click [Next].
- 4 Enter the IP address or the DNS name of the machine, and click [Next].
 The [Port Name] is entered automatically. If necessary, you can change it.



NOTE:

When the next screen is displayed, follow the instructions on the screen.

	formation required id not be identified.	1
The device is not	found on the network. Be sure that:	
1. The device is t		
 The network is The device in r 	connected. properly configured.	
	n the previous page is correct.	
 The address of If you think the ac 	Idress is not correct, click Back to return to the previ rm another search on the network. If you are sure t	
 The address of you think the ac address and performed 	Idress is not correct, click Back to return to the previ rm another search on the network. If you are sure t	
 The address of you think the ac address and performed device type below 	Idress is not correct, click Back to return to the previ rm another search on the network. If you are sure t	

* When you select the [Device Type], select [Canon Network Printing Device with P9100] under [Standard].

5 Click [Finish].

6 Click [Close].

Changing the port type or number

If the printing protocol (LPD or RAW) has been changed on the machine side (**Configuring Printing Protocols and Web Services**) or the port number has been changed (**Changing Port Numbers**), the corresponding settings on the computer must also be configured. This operation is not needed for WSD ports.

MFNP port 🔽

- **1** Click [Configure Port].
- 2 Under [Protocol Type], select [RAW] or [LPR], and change the [Port Number].



3 Click [OK].

Standard TCP/IP port 🗾

- 1 Click [Configure Port].
- 2 Under [Protocol], select [Raw] or [LPR].
 - If you selected [Raw], change the [Port Number].
 - If you selected [LPR], enter "lp" in [Queue Name].


		192.168.0.215
rinter Neme or IP Add	THE SEC	192.168.0.215
Protocol		⊖ LPR
Rew Settings		
Part Number:	9100	
LPR Settings		
Queue Name:	lp.	
LPR Byte Counting	g Enabled	
SNMP Status Enab	led	
Community Name:	public	
samming ments		

3 Click [OK].

4 Click [Close].

Configuring the Machine for Your Network Environment LBP6030w

The size and configuration of a network varies depending on the purpose of the network. This machine has been designed to be compatible with as many network configurations as possible, and it is equipped with a variety of network technologies. Consult your network administrator and set a configuration to suit your network environment.



Changing the Maximum Transmission Unit LBP6030w


In most Ethernet networks, the maximum size of a packet that can be sent is 1500 bytes. A packet refers to a small chunk of data. The original data is divided into packets before being sent. The maximum transmission unit (MTU) may vary on each network. Change the settings of the machine as necessary. For more information, contact your network administrator.

Start the Remote UI and log on in System Manager Mode. Starting the Remote UI

2 Click [Settings/Registration].

interest.	Device Name: Product Name: Location:	LBPR000w5019w LBP5000w5019w	Login User: System Manager Log
Remote UI: Portal			Mail to System Manu
		Last Updated 01101 2013 03:34:26 PM	Status Moniton/Cancel
levice Basic Information			
Device Status			SettinguRegistration
Printer:			
Error Information			
No errore.			
Sepport Link			
Support Link:			






4 Click [Edit] in [MTU Size Settings].

- Col 62 http://182.068.0.215	Sim_network_topip.html		P-ECX 0 0
	195W.	9100	
	HTTP:	80	
	SNMP:	161	
	WSD Multicast Discovery:	3102	
	Multicast Discovery:	427	
	MTU Size Settings		
			E4L.
	MTU Size:	1500	
	SNTP Settings		
			Edt.
	Line SNTP:	08	
	Check NTP Server		
	Check NTP Server		

5 Select the maximum packet size, and then click [OK].

LIPE030wi6013-	/LBPGDIwG018w3	To Portal Login User: System Manager Log On
Settings/Registration		Mail to System Manage
Preferences = Display Settings = Timer Settings lefustment/Maintenance = Utility Mane	Settings/Registration: System Maragenesit Settings, N Exit MTU Size Settings Change the following settings, Changes will be effective after the main power is fam	HANSK Sellings > TCHVP Sellings > Edit MTU Size Sellings Hell OFF and ON.
System Management Settings :: System Management :: Security Settings :: Initialize Setting Information	MTU Size Settings MTU Size:)



• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

LINKS

Setting a Wait Time for Connecting to a Network

Setting a Wait Time for Connecting to a Network LBP6030w

When a network is designed with multiple switching hubs or bridges in order to provide redundant connectivity, it must have a mechanism to prevent packets from looping. One effective solution is to define the role of each switch port. However, communication may still be disrupted for a certain time immediately after you change the network, for example by adding a new device. If this type of problem occurs, set a wait time for connecting the machine to the network.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI


2 Click [Settings/Registration].

lamang,	Device Name: Product Name: Location:	LBP6030wf618w LBP6030wf618w	Login Ucor: System Manager Log O
Remote UI: Portal			Mail to System Manag
		Last Updated 01/01 2015 03 34:20 PM	Status Monitor/Cancel
Nevice Basic Information			
Device Status			Settingu Registration
Printet: Roady to print.			470
Error Information			
No orrani.			
iepport Link			
Support Link:			


Click [Network Settings] > [Waiting Time for Connection at Startup].

	13w / LIBP58339w/6018w J	To Posta	Login User: System Manager Log 0
Settings/Registration			Mail to System Manage
references	Settings/Registration: System Mana	pement Settings. Network Settings	
Display Settings	Network Settings		
Timer Settings	Network Settings		
djustment/Maintenance			
Utility Meno System Management Sellinge System Management Servick Settinge Network Settinge Network Settings minister Sensing monitation	TCN/E Settinge	PH-6 Strategis HM-6 Strategis LUPD-PH-6 Strategis NetP-REIDE Strategis NetP-PH-6 Strategis NetW-PH-6 Strategis NetW-PH-6 Strategis NetW-PH-6 Strategis NetW-PH-6 Strategis Statis Fashings Martina Strategis Statis Fashings	
	SNMP Settings Dedicated Port Settings Waiting Time for Connection at S Winkless LAN Settings	Shelihyi betinga Shelihyi betinga	

4 Click [Edit].



5 Enter the time to wait before beginning communication with the network, and then click [OK].



LINKS

Changing the Maximum Transmission Unit

Configuring DNS LBP6030w


DNS (Domain Name System) provides a service for name resolution that associates a host (or domain) name with an IP address. Configure the DNS, mDNS, or DHCP option settings as necessary according to your network. Note that the procedures for configuring DNS are different for IPv4 and IPv6.



- 1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI
- 2 Click [Settings/Registration].

issenty,	Device Name: Product Name: Location:	LBP5030w5018w LBP5030w5018w	Login User: System Manager Log
Remote UI: Portal			Mail to System Manag
		Last Updated 01/01 2013 00:34:26	PN D Status Monitor/Cancel
evice Basic Information			
Device Status			Settings/Registration
Printet: Roady to print.			47
Error Information			
No errore.			
apport Link			
Support Link:			

3 Click [Network Settings] > [TCP/IP Settings].



4 Configure the DNS settings.

Configuring IPv4 DNS settings

1 Click [Edit] in [IPv4 Settings].



2 Configure the IPv4 DNS settings.

			u 6 🖬
C 😧 🖓 http://152168.0.215/m_metive	d_ipsthind		0 12 6 × 0 8 - 9
	Gateway Address:	0.0.0.0	
	DNS Settings		
	Primary DNS Server Address:	0.0.0	
_	Secondary DNS Server Address:	0.0.0.0	
a	Host Name:	Canor2tee73	
_	Domain Name:		
	ONS Dynamic Update		
	DNS Dynamic Update Interval:	24 Mr. (0-48)) a
	mDNS Settings		
6	Use mDNS		
-	mDNS Name:	Canon LISP0030w/9218w	
	DHCP Option Settings		
C	Acquire Host Name:		
-	DNS Dynamic Update		
	*		

[DNS Settings]

[Primary DNS Server Address]

Enter the IP address of the DNS server.

[Secondary DNS Server Address]

When there is a secondary DNS server, enter its IP address.

[Host Name]

Enter up to 47 alphanumeric characters for the host name of the machine that is to be registered with the DNS server.

[Domain Name]

Enter up to 47 alphanumeric characters for the name of the domain the machine belongs to (such as "example.com").

[DNS Dynamic Update]

Select the check box to automatically update the DNS records whenever the association between the machine's IP address and its host name changes (for example, in a DHCP environment). To specify the interval between updates, enter the time in hours in the [DNS Dynamic Update Interval] text box. Clear the check box if you do not want to use dynamic updating.

[mDNS Settings]

[Use mDNS]

Adopted by services such as Bonjour, mDNS (multicast DNS) is a protocol for associating a host name with an IP address without using DNS. Select the check box to enable mDNS and enter the mDNS name in the [mDNS Name] text box. Clear the check box if you do not want to use mDNS.

[DHCP Option Settings]

[Acquire Host Name]

Select the check box to enable Option 12 to obtain the host name from the DHCP server. Clear the check box if you do not want to use this function.

[DNS Dynamic Update]

Select the check box to enable Option 81 to dynamically update the DNS records through the DHCP server instead of through this machine. Clear the check box if you do not want to use this function.

3 Click [OK].

-		
C 8 http://182.068.0.215/m.ne	twork_ipv4.html	0 🗅 🔿 x5=-9.
LUPG030w/6018v	x / LEPSEXEw/5018w /	To Portal Login User: System Manager Log Out
Settings/Registration		Mail to System Manager
Preferences Display Settings Traner Settings AdjustmentMaintenance Utility Mane System Kanagement Settings	Edit IPv4 Settings Change the following settings	Integrated Settings Network Settings > TGVIP Settings > Edit IPv4 Settings A The main power is turned OFF and ON. COR Concer
 System Management Socurity Settings Network Settings Initiatize Setting Information 	Select Protocol Auto IP: IP Address:	ekci Photocelj and [Main IP] are sot to [DB] (OP m) (OP m) 112 1080 215
	Subnet Mask	

Configuring IPv6 DNS settings

1 Click [Edit] in [IPv6 Settings].

C C C R http://182.068.0.215/m_net	rork,topip.html		P-EdX 0 🗘 8
	DHCP Option Settings		
	Acquire Host Name:	On	
	DNS Dynamic Update:	on	
	IPv6 Settings		
			Ed.
	IP Address Settings		
	Use IPv6:	07	
	WINS Settings		
			Edt
	WINS Resolution	08	
	LPD Print Settings		
			Edt.

2 Configure the IPv6 DNS settings.

The [Use IPv6] check box must be selected to configure the settings. Setting IPv6 Addresses

C (1) 10 http://102.0666.2215/m, network, jp.6.html	P-10X 000
Ibs: DHCPv6 State/ul Addres: 0000.0000.0000.0000.0000.0000.0000 Parlie Langth: 0	
DNS Settings	
Primary DNS Server Address. DDDD 0000 0000 0000 0000 0000 0000 0	100
Secondary DNS Server Address: 0000.0000.0000.0000.0000.0000.0000.0	00
[2] Use Same Host Name/Domain Name as IP+4	
Host Name. CarceJbas73	
Consin Name:	
E DNS Dynamic Update	
Register Nerual Address	
Register Statulul Address	
Register Statuless Address ENSI Dynamic Update Interval: 24 Int. (0-48)	
Entro Dynamic Opcase anterval. 2.4 Inc. (0-44)	
mDNS Settings	
Use mDNS	
nONS Namer Caron LBP6030w/6018w	
I.	

[DNS Settings]

[Primary DNS Server Address]

Enter the IP address of the DNS server. Addresses that start with "ff" (multicast addresses) and the loopback address (::1) cannot be entered.

[Secondary DNS Server Address]

When there is a secondary DNS server, enter its IP address. Addresses that start with "ff" (multicast addresses) and the loopback address (::1) cannot be entered.

[Use Same Host Name/Domain Name as IPv4]

Select the check box to use the same settings as in IPv4. The host name and domain name used in IPv4 will be set automatically after the machine restarts. Clear the check box if you want to use different settings from IPv4.

[Host Name]

Enter up to 47 alphanumeric characters for the host name of the machine that is to be registered with the DNS server.

[Domain Name]

Enter up to 47 alphanumeric characters for the name of the domain the machine belongs to (such as "example.com").

[DNS Dynamic Update]

Select the check box to automatically update the DNS records whenever the association between the machine's IP address and its host name changes (for example, in a DHCP environment). To specify the addresses you want to register with the DNS server, select one or more of the check boxes for [Register Manual Address], [Register Stateful Address], and [Register Stateless Address]. To specify the interval between updates, enter the time in hours in the [DNS Dynamic Update Interval] text box. Clear the check box if you do not want to use dynamic updating.

[mDNS Settings]

[Use mDNS]

Adopted by services such as Bonjour, mDNS (multicast DNS) is a protocol for associating a host name with an IP address without using DNS. Select the check box to enable mDNS. Clear the check box if you do not want to use mDNS.

[Use Same mDNS Name as IPv4]

Select the check box to use the same settings as in IPv4. The mDNS name used in IPv4 will be set automatically after the machine restarts. Clear the check box and enter a name in [mDNS Name] if you want to use different settings from IPv4.

3 Click [OK].

-		
🗲 💿 😵 http://182.068.0.215/m_net	tvork, jové hámi	P-EdX 0 10
LIPS020wi9010w	/ LEPSEDEw/6018w/	To Portal Login User: System Menager Log Out
Settings/Registration		Mail to System Manager
Preferences	Settings/Registration: System Ma	ragement Settings. Network Settings > TCP/IP Settings > Edit IPv6 Settings
Display Settings	Edit IPv6 Settings	
= Timer Settings Adjustment/Maintenance = Utility Manu System Management Settings	Change the following satings. Changes will be effective after t	he main power is turned OFF and ON.
System Management	IP Address Settings	
 Security Settings Network Settings Initialize Setting Information 	Use IPv6 Link-Local Address: Prata Length: If Statoloss Address Stateless Address 1: Prata Length 1:	00000 3000 8000 0000 0000 8000 0000 000

Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

Setting IPv4 Address
 Setting IPv6 Addresses
 Viewing Network Settings

Configuring WINS LBP6030w

Windows Internet Name Service (WINS) is a name resolution service that associates a NetBIOS name (a computer or printer name in a NetBIOS network) with an IP address. To use WINS, a WINS server must be specified.

IMPORTANT


- To register this machine with a WINS server, a NetBIOS name and workgroup name must be set. OConfiguring NetBIOS
- This function is not available in an IPv6 environment.


1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI


2 Click [Settings/Registration].

🔹 😨 http://182.068.0.215/portal;	top Hemi	ρ-acx 0.00
lanary,	Device Name: LBP5030w/918w Product Name: LBP5030w/918w Location:	Login User: System Manager Log O
Remote UI: Portal		Mail to System Manage
	Last Updated 01/01 201	S 03 34 20 PM
Device Basic Information		×
Device Status		Settings/Registration
Printer: Roady to print.		4
Error Information		
No errore.		
Support Link		
Support Link:		

3 Click [Network Settings] > [TCP/IP Settings].







5 Select the [WINS Resolution] check box and enter the required information.

C 10 10 102 2080 215 m. no	work wire, edit html		P-86X 0 00
	r LEPGEDBw/6018wJ	To Portal Log	in User: System Manager Log On Mail to System Manager
Preferences Daplay Sellings Trans-Sellings AdjusteenMikirkananca URMy Mana System Maragement Sellings System Maragement Sellings System Maragement Network Sellings Distributes	Edit WHS Settings Change the following settings. Change will be effective after the main pos- many of the effective after the main pos- WHS Settings WHS Resolution	etings Network, Setings > TCNYP Setings > er is tamed CPF and CN.	Ldt WINS Setings
	×		Copyright O/WON INC. 2013

[WINS Resolution]

Select the check box to use WINS for name resolution. When not using WINS, clear the check box.

[WINS Server Address]

Enter the IP address (IPv4) of the WINS server.

IMPORTANT:

If the IP address of the WINS server is obtained from a DHCP server, the obtained IP address overrides the IP address entered in the [WINS Server Address] text box.

[Scope ID] If the network is divided into several groups with scope IDs (identifiers for groups of devices in the network), enter up to 63 alphanumeric characters for the scope ID. Leave the text box blank if there is no scope ID set for your computer.

6 Click [OK].

Restart the machine.

Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

LINKS

Setting IPv4 Address

Configuring NetBIOS LBP6030w


To register this machine with a WINS server, a NetBIOS name and workgroup name must be set.

1 Start the Remote UI and log on in System Manager Mode. **Starting the Remote UI**

2 Click [Settings/Registration].

haven'ny,	Device Name: Product Name: Location:	LBP5030w5018w LBP5030w5018w	Login User: System Manager Lo
Remote UI: Portal			Mail to System Ma
		Last Updated 01/01 2013 03:34:26 PM	Status Monitor/Cancel
Device Basic Information			4
Device Status			SettingeRegistration
Printet: Roady to print.			47
Error Information			
No errore.			
Sepport Link			
Support Link:			





4 Click [Edit] in [NetBIOS Settings].





LUP6030w/6010	w/L8P6838w/6018wJ	To Portal Login User: System Manager Log (
Settings/Registration		Mail to System Manag
telerences = Display Settings = Timer Settings Idjustment/Maintenance = Utility Mana Iyalem Managoment Settings	Settings/Registration: System Varagement Sett Edit Net/ROS Settings Change the following settings. Changes will be effective after the main power	rgs Network Settings > TCPVP Settings > Edit NetBIOS Settings is larved CFF and CN. OK Cancel
 System Management Socurity Settings Network Settings Initialize Setting Information 	NetSIOS Settinav NetBIOS Name: Workgroup Name:	

[NetBIOS Name]

Enter up to 15 alphanumeric characters for the NetBIOS name of the machine.

[Workgroup Name] Enter up to 15 alphanumeric characters for the name of the workgroup that the machine belongs to. IMPORTANT:

NetBIOS or workgroup names that start with an asterisk (*) cannot be registered with a WINS server.

6 Click [OK].

7 Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

LINKS

Configuring WINS

Configuring SNTP LBP6030w



Simple Network Time Protocol (SNTP) enables you to adjust the system clock by using a time server on the network. When you use SNTP, the system checks the timer server periodically, so that the system clock is always accurate. The time is based on Coordinated Universal Time (UTC), so specify the time zone setting before configuring SNTP (**©Timer Settings**).

NOTE


The SNTP of the machine supports both NTP (version 3) and SNTP (versions 3 and 4) servers.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

😂 🔞 http://182.068.0.215/portel,			P-16X 01
anany.	Device Name: Product Name: Location:	LBP5030wf6119w LBP5030wf6119w	Login Ucor: System Manager Log
Remote UI: Portal			Mail to System Man
		Last Updated 01/01 2013 00.	04.26 PM 🔹 Status Monitor/Cancel
evice Basic Information			6
Device Status			Settingu/Registration
Printer: 🔵 Roady to print.			47
Error Information			
No errore.			
spport Link			
Support Link:			

3 Click [Network Settings] ▶ [TCP/IP Settings].





(a) 82 http://182.068.0.2	15 m. network train.html		0 ×55-Q
Col	NW.	9100	2.1001
	HITP:	00	
	SNMP	161	
	WSD Multicast Discovery	3/02	
	Wulticast Discovery:	427	
	MTU Size Settings		
			844
	MTU Sime	1500	
	SNTP Settings		
			Ede
	Une SNTP:	08	
	Check NTP Server		
	Check NTP Server		

5 Select the [Use SNTP] check box and enter the required information.

C	to the state of th		P-16× 0 10
LIPEODeviSitov / LIPEODeviSitov /			To Portel Login User: System Manager Log On
Settings/Registration			Mail to System Manager
Preferences = Doplary Bellings = Trans Bellings AdjustvestMaintenance = Urblig Mens System Management Settings = System Management = Security Settings = Network Settings = Installes Settings Harmaden	SetingsTrepstation System Vi Cell SNTP Settings Change the following ustings SNTP Settings ID Use SNTP NTP Service Name: Poling Mercut	regeneed Settings Network Settings > TC 24 hours (1-45)	TVP Setlerge > Edd SNTP Setlerge
			Copyright CANCIN INC. 281

[Use SNTP]

Select the check box to use SNTP for synchronization. Clear the check box if you do not want to use this function.

[NTP Server Name]

Enter the IP address of the NTP or SNTP server. If a DNS server is available on the network, you can enter "<host name>.<domain name>" (FQDN) of up to 255 alphanumeric characters instead (example: "ntp.example.com").

[Polling Interval]

Enter an interval from 1 to 48 hours to specify how often to poll the time server.

6 Click [OK].

NOTE

Testing communication with the NTP/SNTP server

You can test whether the machine is communicating with the registered time server via SNTP. Click [Settings/Registration] [Network Settings] [TCP/IP Settings] to display [SNTP Settings], and then click [Check NTP Server]. If a proper connection has been established, the result is displayed as shown below. (Note that this operation only checks the connection. It does not adjust the system clock.)

On
ntp.example.com
24 hr.
OK

Synchronizing to the time set on the computer


You can notify the machine of the time set on your computer, and synchronize to that time. Make time notification settings in the Printer Status Window.

Custorrize.	Canon LEPP033/0540/00181
□ al 4) 0000 05/03/2013	□ 40 € 00,001/2013
2 Select [Options] > [Pref	erences (Administrators)].
L ¹ /L Carene LEPOS230.9504/05028. 3bb [200005] Help Derforment (Administration) Caruter Deformation Winders LAN Status UBity Device Strings Managament Sattings	
3 Select the [Notify the P	inter of the Timel check box and c
3 Select the [Notify the Pr	rinter of the Time] check box and c

Downloaded from ManualsPrinter.com Manuals 94 / 219

Monitoring and Controlling the Machine with SNMP LBP6030w

Simple Network Management Protocol (SNMP) is a protocol for monitoring and controlling communication devices in a network by using a Management Information Base (MIB) database. The machine supports SNMPv1 and security-enhanced SNMPv3. They allow you to check the status of the machine from a computer when you print documents or use the Remote UI. You can enable either SNMPv1 or SNMPv3, or both at the same time. Specify the settings for each version to suit your network environment and the purpose of use.



SNMPv1

SNMPv1 uses data called a "community string" (in effect a kind of password) to define the scope of SNMP communication. Because this information is exposed to the network in plain text, your network will be vulnerable to attacks. If you want to ensure network security, disable SNMPv1 and use SNMPv3.

SNMPv3

With SNMPv3, you can implement network device management that is protected by robust security features. Use the Remote UI to make settings. Before starting, enable SSL (**Senabling SSL Encrypted Communication for the Remote UI**).

NOTE:

- The machine does not support the trap notification feature of SNMP.
- To change the SNMP port numbers Changing Port Numbers
- SNMP management software enables you to configure, monitor, and control the machine remotely from the computer where the software is installed. For more information, see the instruction manuals for your management software.


Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

interest.	Device Name: Product Name: Location:	LBP6030w5919w LBP5030w5919w	Login User: System Manager Log
Remote UI: Portal			Mail to System Manag
		Last Updated 01/01 2015 03:34:20 PM 👩	Status Moniton/Cancel
Jevice Basic Information			
Device Status			Settings/Registration
Printer: Roady to print.			470
Error Information			
No errore.			
iepport Link			
Support Link:			

2

Click [Network Settings] > [SNMP Settings].



4 Click [Edit].

Settings/Registration Pretences Setings/Registration System Wangement Setings = Darking Settings Setings/Registration System Wangement Setings - Constraint/Informance Setings/Registration System Wangement Setings	Mail to Spatem Manage Network Settings > SNMP Settings
Display Settings SNMP Settings Timer Settings	Network Settings > SNMP Settings
	Est.
Chilly Mane System Konzgenest Esteps SNMP-1 Sestings Use SMAP-1: Contrasty Sestings Status Sestings Revork Sestings Contrasty Name 1: pulle Revork Sestings Contrasty Name 2: Delastice Contrasty Sesting: Revork Sesting	rky

5 Specify SNMPv1 settings.

If you do not need to change SNMPv1 settings, proceed to the next step.

A			
C 8 http://182.068.0.215/m_net			P+BdX 0 0 0
LIPC030wr6019w	(L8P\$838w/5018w)		To Portal Login User: System Manager Log Out
Settings/Registration			Mail to System Manager
Preferences = Display Settings	Settinga/Registration: System Managem Edit SNMP Settings	ent Settings: Network Setting	s > SNMP Settings > Edit SNMP Settings
□ Timer Settings AdjustmentMaintenance □ Utility Mene System Management Settings	Change the following settings. Changes will be effective after the main	n power is turned OFF and O	N GK Gancel
System Management	SNMPv1 Sottings		
::: Biocurity Stellings B Network Sollings ::: Initiatus Setting Information	Use SMMP-1 Community Name 1: MRB Access Parmission 1: Community Name 2: MRB Access Parmission 2: Deckated Community Settings	Public Read Only * Read Only * Onl ReadWrite Read Only	
	SNMPv3 Settings Use SNMPv3 To enable the [User Bellings] and the [Dee Settings]. Private: Management Information Acc		starred De on the (Renetic Li Settings) page in (Security

[Use SNMPv1]

Select the check box to enable SNMPv1. You can specify the rest of the SNMPv1 settings only when this check box is selected.

[Community Name 1]/[Community Name 2]

Enter up to 32 alphanumeric characters for the name of the community.

[MIB Access Permission 1]/[MIB Access Permission 2]

For each community, select [Read/Write] or [Read Only] for the access privileges to MIB objects.

[Read/Write]	Allows both viewing and changing the values of MIB objects.	
[Read Only]	Allows only viewing the values of MIB objects.	

[Dedicated Community Settings]

Dedicated Community is a preset community, intended exclusively for administrators using Canon software, such as imageWARE Enterprise Management Console. Select [Off], [Read/Write] or [Read Only] for access privileges to MIB objects.

[Off]	Do not use the Dedicated Community.
[Read/Write]	Allows the Dedicated Community to both view and change the values of MIB objects.
[Read Only]	Allows the Dedicated Community to only view MIB objects.

Downloaded from ManualsPrinter.com Manuals

Specify SNMPv3 settings.

If you do not need to change SNMPv3 settings, proceed to the next step.

Use SNMPv3	
User Settings 1	
[2] Enable User	
User Name:	inter
MIB Access Permission	Haad.Witte +
Security Settings:	Authentication On/Encryption On -
Authentication Algorithm:	⊛ MD5 ⊖ \$HA1
SetiCharge Pasavord	
Authentication Password:	
Confirm:	
Encryption Algorithm	e DES AES
Set/Change Password	
Encryption Pasaword	
Confirm:	
Encryption Passwold Confirm	
Context Settings	
Context Name 1:	
Context Name 2:	

[Use SNMPv3]

Select the check box to enable SNMPv3. You can specify the rest of the SNMPv3 settings only when this check box is selected.

[Enable User]

Select the check box to enable [User Settings 1]/[User Settings 2]/[User Settings 3]. To disable user settings, clear the corresponding check box.

[User Name]

Enter up to 32 alphanumeric characters for the user name.

[MIB Access Permission]

Select [Read/Write] or [Read Only] for access privileges to MIB objects.

[Read/Write]	Allows both viewing and changing the values of MIB objects.
[Read Only]	Allows only viewing the values of MIB objects.

[Security Settings]

Select [Authentication On/Encryption On], [Authentication On/Encryption Off], or [Authentication Off/Encryption Off] for the desired combination of authentication and encryption settings.

[Authentication Algorithm]

When [Security Settings] has been set to [Authentication On/Encryption On] or [Authentication On/Encryption Off], select [MD5] or [SHA1] as the authentication algorithm, according to your environment.

[Encryption Algorithm]

When [Security Settings] has been set to [Authentication On/Encryption On], select [DES] or [AES] as the encryption algorithm, according to your environment.

[Set/Change Password]

To set or change the password, select the check box and enter between 6 and 16 alphanumeric characters for the password in the [Authentication Password] or [Encryption Password] text box. For confirmation, enter the same password in the [Confirm] text box. Passwords can be set independently for authentication and encryption algorithms.

[Context Name 1]/[Context Name 2]/[Context Name 3]

Enter up to 32 alphanumeric characters for context names. Up to three context names can be registered.

Specify printer management information acquisition settings.

With SNMP, printer management information (such as printing protocols and printer ports) can be monitored and obtained regularly from a computer on the network.

I Security Settings	12 Use SMMEv1		
B Network Settings			
Initialize Setting Information	Community Name 1:	public	
	MIB Access Permission 1:	Read Only a	
	Community Name 2:		
	MIB Access Permission 2:	Read Only m	
	Dedicated Community Settings:	⊖ OH ⊝ Read/Write a Read Only	
	SNMPv3 Settings		
	Use SNMPv3		
	"To enable the [User Settings] and the (Con Settings).	ted Settings), [Lie 55.] must be turned On on the (Nemde Li Settings) page in (Security	
	Printer Management Information Acq		
	X		
		Cepyrgre CANON INC. 2813	

[Acquire Printer Management Information from Host]

Select the check box to enable monitoring of the printer management information of the machine via SNMP. To disable monitoring of the printer management information, clear the check box.

8 Click [OK].

C 8 http://182.068.0.215/m_net	twork,snmp_adit.html		P-16X 0 0 0
LIPE030wr6010w	(1.0P5030w/5010w.)	T.	o Portel Login User: System Manager Log Out
Settings/Registration			Mail to System Manager
Preferences	Settings/Registration: System Managem	ent Settings: Network Settings > SNN	#P Settings > Edit SNINP Settings
Display Settings	Edit SNMP Settings	3	
= Timer Settings Adjustment/Maintenance = Utility Mane System Management Settings	Change the following settings. Changes will be effective after the ma	n power is turned OFP and ON.	OK Cancel
 System Management Security Settings 	SNMPv1 Sottings		
Sucurry Settings Network Settings	Use SNMPv1		
I Initialize Setting Information	Community Name 1:	public	
	MIB Access Permission 1:	Read Only ×	
	Community Name 2:		
	MIB Access Permission 2:	Read Only in	
		0.01	

9 Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

NOTE

Disabling both SNMPv1 and SNMPv3

If both versions of SNMP are disabled, some of the functions of the machine become unavailable, such as obtaining machine information via the printer driver.

Enabling Both SNMPv1 and SNMPv3

If both versions of SNMP are enabled, it is recommended that MIB access permission in SNMPv1 be set to [Read Only]. MIB access permission can be set independently in SNMPv1 and SNMPv3 (and for each user in SNMPv3). Selecting [Read/Write] (full access permission) in SNMPv1 negates the robust security features that characterize SNMPv3 because most of the machine settings can then be controlled with SNMPv1.


LINKS

CEnabling SSL Encrypted Communication for the Remote UI

Configuring SLP Communication with imageWARE LBP6030w

You can use device management software such as imageWARE Enterprise Management Console^{*} to facilitate the collection and management of various information about networked devices. In an environment where such software is installed, information about device settings and errors is collected via a server on the network. If the machine is connected to an imageWARE network, imageWARE searches the network for the machine by using protocols such as Service Location Protocol (SLP). SLP settings can be specified via the Remote UI.

 * For more information about imageWARE, contact your local authorized Canon dealer.



NOTE


To change the SLP port number **Changing Port Numbers**

Start the Remote UI and log on in System Manager Mode. Starting the Remote UI

2 Click [Settings/Registration].

havened.	Device Name: Product Name: Location:	LBP5030w5018w LBP5030w5018w	Login User: System Manager Log
Remote UI: Portal			Mail to System Mana
		Last Updated 01/01 2015 03:34:20 PM	Status Monitor/Cancel
Jevice Basic Information			V
Device Status			Settingu/Registration
Printet: Roady to print.			47
Error Information			
No errora.			
Sepport Link			
Support Link:			

3 Click [Network Settings] ▶ [TCP/IP Settings].



4 Click [Edit] in [Multicast Discovery Settings].

C 8 http://182.068.0.215/m_netv	ork,topip.html		P-26X 0 0 0
	Functions that use SSL		
	Remote UI		
	Multicast Discovery Settings		
			ER.
	Discovery Response:	On	
	Scope Name:	dofault	
	Port Number Settings		
			Edt
	LPD:	515	
	RAW:	9100	
	HTTP:	80	
	SNMP:	161	
	WSD Multicast Discovery:	3702	

5 Select the [Respond to Discovery] check box and enter the required information.

SENSYS LUPEODOWIGHTW	LEPGEDBwS018w1 To Portel Login User: System Manag	_
Settings/Registration	Mail to System	n Mana
references	Settinga/Registration. System Management Settings. Network Settings > TCP/IP Settings > Edit Multicast Discovery	Setting
III Display Settings	Edit Malticant Discovery Settings	
Timer Settings	Change the following settings.	
djustment/Maintenance	Changes will be effective after the main power is turned CFF and ON.	
System Management Settings	OK	Cancel
System Management		
Security Settings	Multicast Discovery Sottings	
B Network Settings	Respond to Dise every	
Initialize Setting Information	Scope Name: default	
	E	
	*	

[Respond to Discovery] Select the check box to set the machine to respond to imageWARE multicast discovery packets and enable management by imageWARE. If you do not want to respond, clear the check box.

[Scope Name]

To include the machine in a specific scope, enter up to 32 alphanumeric characters for the scope name.

6 Click [OK].

7 Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

Security LBP6030w

Confidential information is handled by information devices everywhere, including computers and printers, and any of these devices may become a target for malicious third parties at any time. Attackers may directly gain unauthorized access to your devices, or indirectly take advantage of negligence or improper use. Either way, you may incur unanticipated losses when your confidential information is leaked. To counter these risks, this machine is equipped with a variety of security functions. Set the necessary configuration depending on your network environment.

Establishing the Basics of Information Security



OProtecting the Machine from Unauthorized Access


Implementing Robust Security Features



CEnabling SSL Encrypted Communication for the Remote UI

Protecting the Machine from Unauthorized Access LBP6030w

To prevent unauthorized third parties from accessing and using the machine, you can implement multiple security measures, such as setting system manager passwords, using firewalls, and changing port numbers.



Setting System Manager Passwords LBP6030w


Administrator access rights are required to change machine settings from the Remote UI. After logging in as an administrator, use the following procedure to set the PIN (system manager password). The system manager password is critical to the security of the machine. Make sure that only system managers know the system manager password.

Start the Remote UI and log on in System Manager Mode. Starting the Remote UI

2 Click [Settings/Registration].

freedom,	LBPS030w5919w LBP5030w5919w	Login User: System Manager Log
Remote UI: Portal		Mail to System Mana
	Last Updated 01101 2013 03:34:20 PM	Status Monitos/Cancel
Device Basic Information		
Device Status		Settings/Registration
Printer: Roady to print.		47
Error Information		
No errore.		
Sepport Link		
Support Link:		





4 Enter the PIN.

C 8 http://182.068.0.215/mj.typ	ters,edit.kimi			P-16× 0 0 8
LIPE010wr6010w	/ L8P6838w/6018w /		To Postel Login U	Iser: System Manager Log On
Settings/Registration				Mail to System Manager
Preferences	Settings/Registration: System Vic	nagement Settings: System M	anagement > Edit System Mana	genent
Display Settings	Edit System Management			
Timer Settings AdjustmentMaintenance	Change the following settings.			
© Utility Menu				OK. Cancel
System Management Settings				
System Management	System Manager Information			
II Security Settings	System Manager PIN:	Not set.		
II Network Settings	E Set/Change PIN			
Initialize Setting Information	PIN		(Max 7 digits)	
	Confirm:		(Max 7 digits)	
	System Manager Name:	Administrator		
	Contact Information			


[Set/Change PIN]

To set or change a PIN, select the check box and enter a number of up to 7 digits. Enter the same number in both in the [PIN] and [Confirm] text boxes.

NOTE:

- You cannot register a PIN that consists only of zeros, such as "00" or "0000000."
- To clear a PIN setting, select the [Set/Change PIN] check box and click [OK] with the [PIN] and [Confirm] text boxes empty.

5 Enter the name and contact information of the system manager as necessary, and click [OK].



[System Manager Name] Enter up to 32 alphanumeric characters for the name of the system manager.

[Contact Information]

Enter up to 32 alphanumeric characters for the contact information of the system manager.


[E-Mail Address]

Enter up to 64 alphanumeric characters for the e-mail address of the system manager.

[System Manager Comment] Enter up to 32 alphanumeric characters for a comment about the system manager.

Restricting Communication by Using Firewalls LBP6030w

Without proper security, unauthorized third parties can access computers and other communication devices that are connected to a network. To lower the risk of unauthorized access, you can allow communication with devices having specified IP addresses and reject communication with other devices. Conversely, you can also reject communication with devices having specified IP addresses and allow communication with other devices. You can specify a single IP address or a range of IP addresses.



NOTE


- Up to 16 IP addresses (or ranges of IP addresses) can be specified for both IPv4 and IPv6.
- The communication protocols that can be restricted in this way are TCP, UDP, and ICMP.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

lamang,	Device Name: Product Name: Location:	LBP6030w5919w LBP5030w5919w	Login User: System Manager Log (
👌 Remote UI: Portal			Mail to System Manag
		Last Updated 01/01 2013 03:34:20 PM	Status Monitor/Cancel
Nevice Basic Information			V
Device Status			Settingu/Registration
Printet: Roady to print.			470
Error Information			
No erroru.			
iepport Link			
Support Link:			

Click [Security Settings] ▶ [IP Address Filter].



4 Click [Edit] to specify a filter type.



[IPv4 Address: Outbound Filter]

Restrict data sent from the machine to a computer by specifying an IPv4 address.

[IPv4 Address: Inbound Filter]

Restrict data received by the machine from a computer by specifying an IPv4 address.

[IPv6 Address: Outbound Filter]

Restrict data sent from the machine to a computer by specifying an IPv6 address.

[IPv6 Address: Inbound Filter]

Restrict data received by the machine from a computer by specifying an IPv6 address.

5 Specify the settings for filtering.

As the policy conditions, select a default policy to allow or reject communication between the machine and other devices. Then specify IP addresses for exceptions.

-			
Ce 🛞 🛿 http://182.068.0.215/mj.rec.)	pfilter_v4cend.html		P+86× 0 ℃ 8
LIP6030w/9010w/	L8P6839w/6018w3	To Por	M Login User: System Manager Log Out
Settings/Registration			Mail to System Manager
Preference	Film IRMA Addresses Exist Distributions Change the following sating Obseque will be effective after Set Darkbound Filter Chang Policy: Exception Addresses Exception Addresses Addresses Engineer: To enter multiple T-addresses a		(K) Canad
	X		
			Creyright CANON INC. 2013

1 Select the [Use Filter] check box, and then select a policy with [Default Policy].

[Use Filter]

Select the check box to restrict communication. Clear the check box to communicate without restrictions.

[Default Policy]

As the policy conditions, select whether to allow or reject other devices to communicate with the machine.

[Reject]	Select to allow communication only when the data is sent to or received from devices whose IP addresses are entered in [Exception Addresses]. Communication with other devices is prohibited.
[Allow]	Select to block data that is sent to or received from devices whose IP addresses are entered in [Exception Addresses]. Communication with other devices is allowed.

2 Specify address exceptions.

Enter an IP address (or a range of IP addresses) in the [Address to Register] text box and click [Add].

NOTE:

Entry format for IP addresses

- To enter a single address (IPv4)
 - Enter numbers delimited by "." (periods) (Example: "192.168.0.10").
- To enter a single address (IPv6)

Enter hexadecimal numbers delimited by ":" (colons) (Example: "fe80::10").

- To specify a range of addresses Insert a hyphen ("-") between the addresses (Examples: "192.168.0.10-192.168.0.20" "fe80::10-fe80::20").
- To specify a range of addresses with a prefix Enter an address, followed by a slash ("/") and a number indicating the prefix length (Examples: "192.168.0.32/27" "fe80::1234/64").

When [Reject] is selected for an outbound filter

Outgoing multicast and broadcast packets cannot be filtered.

To delete an IP address that has been set

Select the IP address to delete, and then click [Delete].

		Add
	use a hyphen as follows: x00.000.000.000.000	
IP address	as follows: xoo.coc.coc/xx (prefix length: 0-32))
	192 168 0 10	
(192 168 0 10 192 168 0 20	
	192.166.0.32/27	
(Delete	

3 Click [OK].

6 Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

Changing Port Numbers LBP6030w

Ports serve as endpoints for communicating with other devices. Typically, standard port numbers are used for major protocols, but devices that use these port numbers are vulnerable to attacks because these port numbers are well-known. To enhance security, some network administrators prefer to change the port numbers. When a port number has been changed, the new number must be shared between communicating devices, such as computers and servers. If a port number changes, set it on this machine as well.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

issente.	Device Name: Product Name: Location:	LBP6030wf618w LBP6030wf618w	Login User: System Manager Log (
Remote UI: Portal			Mail to System Manag
		Last Updated 01101 2015 00:34:26 PM	Status Moniton/Cancel
levice Basic Information			
Device Status			SettingaRegistration
Printet: Roady to print.			474
Error Information			
No errora.			
epport Link			
Support Link:			


3 Click [Network Settings] ▶ [TCP/IP Settings].

C Reput 192.266.0.215 km, network Atmil	w/0018w.J		P = E G X 0 10 To Postal Login User: System Manager Log
Settings/Registration		-	Mail to System Mary
Display Settings Timer Settings Adjustment/Maintenance Netw	s Registration: System Wa ook Sottings ook Settings ANP Settings	ragement Settings. Network Settings IPv4 Settings	
System Management Settings System Management System Management Network Settings Intervent Settings Interven		IN-Startings WNR5 Settings UPID Print Settings MeB/CS Setlings RWW Print Bettings WBD Settings SSL Settings	
		Part Number Sellings MTU film Softings SNTP Settings Maticast Discovery Settings	
94	MP Settings		

4 Click [Edit] in [Port Number Settings].

~			
(a) 10 http://182.568.0.215/vs_ket	entrik_att pip.html		
	Discovery Response:	On	
	Scope Name:	default	
	Port Number Sottings		
			E41
	LPID:	515	
	RAW:	9100	
	HTTP:	00	
	SNMP:	161	
	WSD Multicast Discovery:	3/02	
	Multicast Discovery:	427	
	MTU Size Settings		
			641
	MTU Size:	1500	

5 Change the port number, and click [OK].



[LPD]/[RAW]

Change the port used for LPD printing or RAW printing. For details about each protocol, see **Configuring Printing Protocols** and Web Services.

[HTTP]

Change the port used by HTTP. HTTP is used for communications over the network, such as when you access the machine via the Remote UI.

[SNMP]

Change the port used by SNMP. For details about SNMP, see OMOnitoring and Controlling the Machine with SNMP.

[WSD Multicast Discovery]

Change the port used for WSD multicast discovery. For details about WSD, see Configuring Printing Protocols and Web Services.

[Multicast Discovery]

Change the port used for SLP multicast discovery. For details about SLP, see **Configuring SLP Communication with** imageWARE.

6 Restart the machine.

Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

LINKS

Configuring Printer Ports

Enabling SSL Encrypted Communication for the Remote UI LBP6030w

Authorized users may incur unanticipated losses from attacks by malicious third parties, such as sniffing, spoofing, and tampering of data as it flows over a network. To protect your valuable data, you can encrypt Remote UI communication between the machine and a Web browser on the computer by using Secure Sockets Layer (SSL). SSL is a mechanism for encrypting data sent or received over the network. SSL must be enabled when the Remote UI is used to make settings for SNMPv3. To use SSL for the Remote UI, you need to set a key pair and enable the SSL function. Have a key pair ready to use (Configuring Settings for Key Pairs and Digital Certificates).



IMPORTANT

When you use SSL to encrypt communication with the Remote UI, set the time data of the machine. You can use either of the following methods to set the time data.


- Use a network time server to adjust the machine's system clock Configuring SNTP
- Notify the machine of the currently set time on your computer OSynchronizing to the time set on the computer

Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

Click [Settings/Registration].

ineres,	Device Name: Product Name: Location:	LBP5030w5019w LBP5030w5019w	Login Uzer: System Manager Log (
Remote UI: Portal			Mail to System Manag
		Last Updated 01/01 2015 03:34:20 PM	Status Moniton/Cancel
levice Basic Information			1
Device Status			SettinguRegistration
Printet: Roady to print.			47
Error Information			
No errore.			
epport Link			
Support Link:			

Click [Network Settings] ▶ [TCP/IP Settings].



4 Click [Key and Certificate] in [SSL Settings].

Use Multicast Discovery	0n	
Disk white and Discovery	CH	
SSL Settings		
		Key and Certificate.
Key and Certificate Settings	Not set.	
Functions that use SSL		
Remote UI		
Multicast Discovery Settings		
		Edit.
Discovery Response:	On	
Scope Name:	dofault	
Port Number Settings		

5 Select the key to use from the list of keys and certificates, and click [Register Default Key].

LUPGOJOwi6315	w/LEP6030w/5018w		To Po	Login User: System Manager Log
Settings/Registration				Mail to System Mana
Preferences = Display Settings = Timer Settings Adjustment/Maintenance = Utility Mene System Management Settings	SetingsRegistre Key and Costif Register Det Select	cate Settings	trgs: Network Settings > TCP/IP 5 Key Usage	etings > Key and Certificate Settings Certificate
System Management Security Settings Network Settings	0	Sample		
a Initialize Setting Information	×			

NOTE:

Viewing details of a key pair or certificate

You can check the details of the certificate or verify the certificate by clicking the corresponding text link under [Key Name], or the certificate icon. **Verifying Key Pairs and CA Certificates**

6 Enable SSL.

1 Click [Security Settings] ▶ [Remote UI Settings].

Settings:Registration Pelences Settings:Tegetation System Varagement Settings Security Set = Time Settings = Time Settings Security Settings - AdjustmetMicroaces Security Settings	Mail to System Manag
Display Sellings Security Solitings Trove Sellings Trove Sellings	trgs
Uhiliy Mere Spains Karagemet Settings Status Varianemet Settings Status Varianemet Settings Status Varianemet Status Varianemet Status Varianemet Status Varianemet Settings StatusV	nd Filter und Filter

2 Click [Edit].

Settings/Registration			Mail to System Man
Preferences Display Settings Timer Settings	Settings/Registration System Remote UI Settings	i Maragement Settings. Security Settings >	Renote UI Settings
 Uniter Settings Edustment/Maintenance Utility Menu 			Edit
System Management Settings	Remote UI Settings Use SSL:	01	
System Management Security Settings Network Settings Initialize Setting Information	×		
			Copyright CANON INC.

3 Select the [Use SSL] check box and click [OK].

-	
🗲 🛞 😣 http://182.068.0-215/in_securi	P = 2 S X D = - 2 S X D = - 2
LBP6030wr6010w / I	EP6838w/6018w J To Portal Login User: System Manager Log Out
Settings/Registration	Mail to System Manager
Preferences = Dapler Settings = Trace Settings Adjustment Maintenance = Utily Maine System Management Settings = System Management = Settings = System Settings = Network Settings = Network Settings = Network Settings	Settings Tingshadan System Varagereed. Settings Settings > Benade US Settings > Edit Renade US Settings Edit Reseate US Settings Company Se Notwards US Settings Changer of the effective after the main power in Luned CPF and CN. Reseate US Settings (2) (0) CRC Careed Reseate US Settings (2) (0) SSL Vertice to Settings Vertice to Settin
	CepyrgH CANCH MC 2015

[Use SSL]

Select the check box to use SSL in communication with the Remote UI. Clear the check box if you do not want to use SSL.



Restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

NOTE

Starting the Remote UI with SSL enabled

If you start the Remote UI when SSL is enabled, a security alert may be displayed regarding the security certificate. In this case, check that the correct URL is entered in the address field, and then proceed to display the Remote UI. **© Starting the Remote UI**

LINKS

Generating Key Pairs
 Using CA-issued Key Pairs and Digital Certificates
 Monitoring and Controlling the Machine with SNMP

Configuring Settings for Key Pairs and Digital Certificates LBP6030w

In order to encrypt communication with a remote device, an encryption key must be sent and received over an unsecured network beforehand. This problem is solved by public-key cryptography. Public-key cryptography ensures secure communication by protecting valuable information from attacks, such as sniffing, spoofing, and tampering of data as it flows over a network.

Key Pair



A key pair consists of a public key and a secret key, both of which are required for encrypting or decrypting data. Data can be exchanged safely, because encrypted data cannot be decrypted without the other key in a key pair. You can register up to three key pairs (**Cusing CA-issued Key Pairs and Digital Certificates**). Key pairs can also be generated by the machine (**Calificates**).

CA Certificate



Digital certificates including CA certificates are similar to other forms of identification, such as driver's licenses. A digital certificate contains a digital signature, which enables the machine to detect any spoofing or tampering of data. It is extremely difficult for third parties to abuse digital certificates. Digital certificates (including public keys) that are issued by a certificate authority (CA) are called CA certificates. You can register up to three CA certificates including the one that is preinstalled (**Ousing CA-issued Key Pairs and Digital Certificates**).

Key and Certificate Operating Requirements

Certificates for key pairs generated with the machine must conform to X.509v3. If you install a key pair or a CA certificate from a computer, make sure that they meet the following requirements.

Format	 Key pair: PKCS#12*1 CA certificate: X.509v1 or X.509v3, DER (encoded binary)
Files extension	 Key pair: ".p12" or ".pfx" CA certificate: ".cer"
Public key algorithm (and key length)	RSA (512 bits ^{*2} , 1024 bits, 2048 bits, or 4096 bits)
Certificate signature algorithm	SHA1-RSA, SHA256-RSA, SHA384-RSA ^{*3} , SHA512-RSA ^{*3} , MD5-RSA, MD2-RSA
Certificate thumbprint algorithm	SHA1

*1 Requirements for the certificate contained in a key pair shall follow the operating conditions for CA certificates.

*2 Not supported when the operating system of the communication partner device is Windows 8/Server 2012. Depending on the application of update programs, encrypted communication may also not be possible with other versions of Windows.

 *3 SHA384-RSA and SHA512-RSA are available only when the RSA key length is 1024 bits or more.

NOTE


The machine does not support use of a certificate revocation list (CRL).

Generating Key Pairs LBP6030w


The key pair required for encrypted communication via Secure Sockets Layer (SSL) can be generated with the machine. You can use SSL when accessing the machine via the Remote UI. Up to three key pairs can be registered on the machine.

Start the Remote UI and log on in System Manager Mode. Starting the Remote UI


2 Click [Settings/Registration].



3 Click [Security Settings] ▶ [Key and Certificate Settings].



4 Click [Generate Key].




NOTE:

To delete a registered key pair

- On the right side of the key pair that you want to delete, click [Delete] > [OK].
- A key pair cannot be deleted when "SSL" is displayed under [Key Usage], indicating that the key pair is currently in use. In this case, disable SSL or replace the key pair with another. You will then be able to delete it.

5 Specify settings for the key and certificate.



[Key Settings]

[Key Name]

Enter up to 24 alphanumeric characters for naming the key pair. Set a name that will be easy for you to find later in a list.

[Signature Algorithm]

Select the signature algorithm from the drop-down list.

[Key Algorithm]

The algorithm used to generate keys is RSA. Select the key length from the drop-down list. The larger the number for the key length, the slower the communication. However, the security is tighter.

[512-bit] cannot be selected for the key length, if [SHA384] or [SHA512] is selected for [Signature Algorithm].

[Certificate Settings]

[Validity Start Date]

Enter the first date of validity of the certificate in year/month/day format in the range 1 January 2000 to 31 December 2037.

[Validity End Date]

Enter the last date of validity of the certificate in year/month/day format in the range 1 January 2000 to 31 December 2037. A date earlier than the [Validity Start Date] cannot be set.

[Country/Region]

Click the [Select Country/Region] radio button and select the country/region from the drop-down list. You can also click the [Enter Internet Country Code] radio button and enter a country code, such as "US" for the United States.

[State]/[City]

As necessary, enter up to 24 alphanumeric characters for the address.

[Organization]/[Organization Unit]

As necessary, enter up to 24 alphanumeric characters for the name of the organization.

[Common Name]

As necessary, enter up to 48 alphanumeric characters for the common name of the certificate. "Common Name" is often abbreviated as "CN."

6 Click [OK].

- A key pair may take approximately 10 to 15 minutes to generate.
- After a key pair is generated, it is automatically registered to the machine.

LINKS

OUsing CA-issued Key Pairs and Digital Certificates OVerifying Key Pairs and CA Certificates DEnabling SSL Encrypted Communication for the Remote UI

Using CA-issued Key Pairs and Digital Certificates LBP6030w

Key pairs and digital certificates can be obtained from a certification authority (CA) for use with the machine. After obtaining them from a CA, you can install and register key pairs and CA certificate files on the machine by using the Remote UI. Make sure that the key pair and the certificate satisfy the requirements of the machine (**Skey and Certificate Operating Requirements**). You can register up to three key pairs and three CA certificates including the preinstalled ones.




Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI


2 Click [Settings/Registration].

issents,	Device Name: LBP6000wf818w Product Name: LBP6000wf818w Location:	Login User: System Manager Log
Remote UI: Portal		Mail to System Mana
	Last Updated 01:01 2013 03:34:20 PM	Bistus Monitos/Cancel
evice Basic Information		
Device Status		Seitings/Registration
Printet: 🔵 Ready to print.		47
Error Information		
No errore.		
pport Link		
Support Link:		

Click [Security Settings] > Click [Key and Certificate Settings] or [CA Certificate Settings].
 Click [Key and Certificate Settings] to install a key pair, or [CA Certificate Settings] to install a CA certificate.



4 Click [Register Key and Certificate] or [Register CA Certificate].



NOTE:

To delete a registered key pair or CA certificate

- On the right of the key pair or CA certificate you want to delete, click [Delete] > [OK].
- A key pair cannot be deleted when "SSL" is displayed under [Key Usage], indicating that the key pair is currently in use. In this case, disable SSL or replace the key pair with another. You will then be able to delete it.

5 Click [Install].

■ You can only install one file on this machine. If another file is already installed, click [Delete] > [OK] to delete the previously installed file.



6 Click [Browse], specify the file to install, and click [Start Installation].

	w/LEP\$839w/6018w/	To Porte	Login User: System Manager Log (
Settings/Registration			Mail to System Manag
Preferences = Display Settings	SettingsRegistration. System Certificate > Install Key and	n Management Settings. Security Settings > Key and Ce Settilicate	stilicate Settings > Register Key and
Timer Settings	Install Key and Certificate		1
Adjustment/Maintenance © Utility Menu System Management Settings	Specify the file path of the Click [Browse] to select a f	key and certificate to install. lie.	9 Start Installation Cancel
System Management			
Security Settings	Install Key and Certificate		
D Network Settings	File Path:	C1Example/EXAMPLE.p12	Browse
Initialize Setting Information	X		

The key pair or CA certificate from the computer is installed in the machine.

7 Register the key pair or CA certificate.

Registering a key pair

1 Click [Register] on the right of the key pair you want to register.

Settings/Registration		Mail to System Ma
Verbencas Daplay Settings Daplay Settings Update Settings Ubly Monteshare Ubly Monteshare Ubly Monteshare System Management Settings System Management Settings System Management Settings Network Settings	Settings.Registration System Mana Carificate Register Key and Carifficate Installed Rey and Carifficate Install. File Name EXAMPLE P12	openwer Settinge: Security Settings > Koy and Certificate Settings > Register Koy and Certificate Settings > Register Koy and Register
II Initiatize Setting Information	2	
		Copyright CANON IN

2 Enter the name of the key pair and password, and then click [OK].

-			
C 8 http://182.068.0.215/m.j.toc.)	key_reg_set.html?id=L&File=DVAMPL	EP12	P-EdX A D
LIPS030w/9010w/	L8P6030w/6018w3	To Pr	ortal Login User: System Manager Log Out
Settings/Registration			Mail to System Manager
Preferences = Display Settings	Settings/Registration: System Certificate > Enter Private Ke	Management Settings: Security Settings > Key and Password	Certificate Settings > Register Key and
Timer Settings	Enter Private Key Passwor	d (1997)	
Adjustment/Maintenance	Enter the private key passw File Name: EXAMPLE P12	ord for this file.	
System Management Settings			2 OK Cancal
Security Settings	Enter Private Key Passage	4	
D Network Settings	Key Name:	Exemple	
Initialize Setting Information	Password:		
	x		
			Copyright CANON INC. 2013

[Key Name]


Enter a name of up to 24 alphanumeric characters for registering the key pair in the machine. Set a name that will be easy for you to find later in a list.

[Password]

Enter up to 24 alphanumeric characters for the password of the secret key that is set in the file to be registered.

Registering a CA certificate

Click [Register] on the right of the CA certificate you want to register.



LINKS

Generating Key Pairs
 Verifying Key Pairs and CA Certificates
 Enabling SSL Encrypted Communication for the Remote UI

Verifying Key Pairs and CA Certificates LBP6030w

Once key pairs and CA certificates are registered, you can view their detailed information or verify their effective dates and signature.


1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

lamang,	Device Name: Product Name: Location:	LBP5030w5010w LBP5030w5010w	Login User: System Manager Lo
Remote UI: Portal			Mail to System Man
		Last Updated 01/01 2013 00:34	28 PM 🔹 Status Monitos/Cancel 🥢
Device Basic Information			12
Device Status			Settings/Registration
Printer: Ready to print.			47
Error Information			
No errore.			
Sepport Link			
Support Link:			

Click [Security Settings] > Click [Key and Certificate Settings] or [CA Certificate Settings].

• Click [Key and Certificate Settings] to verify a key pair, or [CA Certificate Settings] to verify a CA certificate.



4 Click the icon for the key pair or CA certificate that you want to verify.

🗧 💿 🚱 kitas//132.068.0.215/m.j.c				P-16X 01
LUPGOLOWSD104	(LEP\$030w/6018w)		To Portal L	ogin User: System Manager Log
Settings/Registration				Mail to System Mana
elerences	SettingsRegistration Sy	stern Management Settings: Se	curity Settings > Key and Certilic	ale Sellings
Display Settings	Key and Certificate Se	tings		1
III Timer Settings				Register Key and Certificate.
ustment/Maintenance = Utility Menu				
uten Maragement Settings	Registered Key and	Certificate		
II System Management	Generate Key			
B Security Settings	Key Name	Key Usage	Certificate	
Network Settings	Example			Delete
Initialize Setting Information				
	×.			

Certificate details are displayed.

5 Check the certificate details, and click [Certificate Verification].



The result from verifying the certificate is displayed as shown below.

-		The local sector of the lo
C 8 http://182.068.0.215/mj.sec	sarity, key, prop., verity. html/id=18.xes=1	P+86× 0 ☆ 8
LIPEO10w/6010w	LEPSIDW/6018w1	To Portal Login User: System Manager Log Out
Settings/Registration		Mail to System Manager
Preferences Display Settings Trace Settings AdjustmentMatematice UINIty Mane System Management Settinge System Management	Certificate Verification	This conflicate is valid. Back to Contificate Details
Security Sotings Network Settings Initialize Soting Information	×.	Chaylogic GHVON INC 2013

LINKS

Generating Key Pairs
 Using CA-issued Key Pairs and Digital Certificates

Using the Remote UI LBP6030w

You can use a Web browser to operate the machine remotely, check the documents waiting to be printed, and check the status of the machine. You can also make network and other settings for the machine. The "Remote UI" starts when you enter the IP address of the machine in your Web browser. It is very convenient, because it allows you to operate the machine remotely without leaving your desk or installing a special application.



Tasks you can do in the Remote UI OManaging Documents and Checking the Machine Status OChanging Machine Settings

How to use the Remote UI OStarting the Remote UI ORemote UI Screens

System Requirements

The following environment is required to use the Remote UI. In addition, set your Web browser to enable cookies.

Windows

- Windows XP/Vista/7/8
- Microsoft Internet Explorer 7.0 or later

Mac OS

- Mac OS 10.4 or later
- Safari 3.2.1 or later

Starting the Remote UI LBP6030w

To operate the machine remotely, start the Remote UI by entering the machine's IP address in your Web browser. Before starting, check the IP address that has been assigned to the machine (**Viewing Network Settings**). If you do not know the machine's IP address, ask your network administrator, or start the Remote UI from the Printer Status Window (**Starting from the Printer Status Window**).

Start the Web browser.

2 Enter "http://<IP address of the machine>/" in the address field, and press the [ENTER] key.



If you are using an IPv6 address, enclose the IPv6 address with brackets (example: "http://[fe80:2e9e:fcff:fe4e:dbce]/").
NOTE:

If a host name for the machine is registered with a DNS server

Instead of <IP address of the machine>, you can enter <"host name"."domain name"> (example: "http://my_printer.example.com").

If a security alert is displayed

A security alert may be displayed when communication with the Remote UI is encrypted (**Communication for the Remote UI**). If there are no problems with certificate settings or SSL settings, continue browsing to the Remote UI site.

3 Select [System Manager Mode] or [End-User Mode].

•	Canon	Login LEP6030w6018w / LEP6030w6018w /		
a	System Manager Mode	_		
b	* End-User Mode		Log in	
_			Copyright CANON INC. 2013	
				-

[System Manager Mode]

You can perform all Remote UI operations and make all settings. If a PIN (system manager password) has been set, enter it in [System Manager PIN]. (**OSetting System Manager Passwords**) If a PIN has not been set (factory default setting), you do not need to input anything.

[End-User Mode]

You can check the status of documents or the machine, and you can also check the settings.

4 Click [Log In].

The Portal Page (main page) of the Remote UI appears. SRemote UI Screens

i santang,	Device Name: Product Name: Location:	LBP5030w/6018w LBP5030w/6018w	Login User: System Manager Log
👌 Remote UI: Portal			Mail to System Mana
		Last Updated 01/01 2015 00.34:20 PM	Status Monitor/Cancel
Device Basic Information			
Device Status			SettinguRegistration
Printet: Ready to print.			4
Error Information			
No errore.			
Sepport Link			
Support Link:			

Starting from the Printer Status Window

Select the machine by clicking 🚇 in the system tray.

			Canon LBP0030/8040/0018L		
Customics		•		Customize	
🖂 al (00.00 01/01/2013			🖂 a (00:00

🔰 Click 🚳.

Canon LEP6030/6040/6018L	- C - X
Job Options Help	
Ready to Print	Å
	Troubleshooting Details .

Web browser starts, and the login page of the Remote UI appears.

NOTE:

If a security alert is displayed

A security alert may be displayed when communication with the Remote UI is encrypted (**CEnabling SSL** Encrypted Communication for the Remote UI). If there are no problems with certificate settings or SSL settings, continue browsing to the Remote UI site.

3 Select [System Manager Mode] or [End-User Mode].

•	Callon	Login LEP6030w/6018w / LEP6030w/6018w /		
a (System Manager Mode System Manager FIN:	_		
- DO	* End-User Mode		Log In	
-			Copyright CANON INC. 2013	

[System Manager Mode]

You can perform all Remote UI operations and make all settings. If a PIN (system manager password) has been set, enter it in [System Manager PIN]. (Setting System Manager Passwords). If a PIN has not been set (factory default setting), you do not need to input anything.

[End-User Mode]

You can check print documents, check the status of the machine, and view machine settings.

4 Click [Log In].

The Portal Page (main page) of the Remote UI appears. OREMOTE UI Screens

🔶 💽 🚱 http://182.068.0.215/portel	top Hami	P-10 X 00
factory.	Device Name: LBP5030w5018w Product Name: LBP5030w5018w Location:	Login User: System Manager Log Ou
😪 Remote UI: Portal		Mail to System Manager
	Last Updated 01101 2015 03.34/28 PM	Status Monitos/Cancel
Device Basic Information		
Device Status		SettinguRegistration
Printer: Roady to print.		47
Error Information		
No errore.		
Support Link		
Support Link:		
		Copyright OANON INC. 2013

Remote UI Screens LBP6030w

This section describes the main screens of the Remote UI.

Portal Page (Main Page) [Status Monitor/Cancel] Page

[Settings/Registration] Page

Portal Page (Main Page)

and the second	Device Name: LBP9030w6018w Product Name: LBP9030w6018w Location:	Login User: System
Remote UI: Portal		2 Mail to System Manager
evice Basic Information	Last Updated 0101 2013 03	Status MonitorCoreel
Device Status Printer: @ Ready to print.	4	SettinguRegistration
Error Information No errors.		_
opport Link	5	

[Log Out]

Logs out from the Remote UI and returns to the log on page.

[Mail to System Manager]

Displays a window for creating an e-mail to the system manager. Contact information for the system manager is specified in [System Manager Information] under [System Management].

8 Refresh Icon

Refreshes the current page.

2 Device Basic Information

Displays the current status of the machine and error information. If an error has occurred, a link to the Error Information page is displayed.

Support Link

Displays a link to support information, as specified in [Device Information] under [System Management].

[] [Status Monitor/Cancel]

Displays the [Status Monitor/Cancel] page. You can use this page to check the current printing status, cancel print processing, and view a history of print jobs.

[Settings/Registration]

Displays the [Settings/Registration] page. When you are logged on in System Manager Mode, you can use this page to change machine settings. **Changing Machine Settings**

[Status Monitor/Cancel] Page

Statu / xor/Cano			3			Mail to System Man
I Job Status	Frint: Job Status	cel: Print: Job Status	<u> </u>		Last	Updanka 01/01 2013 01 4
= Job Log					Linker	
= Error Information	Print Job State	15				
Device Features	Job Number	Job Name	Status	Job Operation	Job Type	Time
Device Information	9922	Document 1.rtf	Printing	Cancel	Printer	01/01 2013 08:23:36 PM
= Check Counter						
	- B 5					
						COEVIGIT CANON INC.

[[To Portal]

Returns to the Portal Page (main page).

🗾 Menu

Click an item to display the content in the page on the right. OManaging Documents and Checking the Machine Status

Breadcrumb trail

Indicates the series of pages you opened to display the current page. You can use this to check which page you are currently displaying.

4 Refresh Icon

Refreshes the current page.

[Top Icon

Moves up to the top of the page when it has been scrolled out of view.

[Settings/Registration] Page

Settir 2 Jatration	etereraliset w (LEPSEDEw/SOTEw/		P + E C X 0 12 13
Preferences Display Settings Trace Settings Adjustment/Maintenance Utility Mene System Management Settings	Settings Registration Preferences Display Settings Display Settings Remote UI Language	English	Est.
 System Management Security Settings Network Settings Initialize Setting Information 	24		Copyright CAVON INC. 381

[To Portal]

Returns to the Portal Page (main page).

ව Menu

Click an item to display the content in the page on the right. OChanging Machine Settings

Breadcrumb trail

Indicates the series of pages you opened to display the current page. You can use this to check which page you are currently displaying.

[Top Icon

Moves up to the top of the page when it has been scrolled out of view.

NOTE

About [System Management Settings]

- You can change system settings only when you have logged on in System Manager Mode.
- When you have logged on in End-User Mode, only [System Management] is displayed.

Managing Documents and Checking the Machine Status LBP6030w

Checking the Current Status of Print Documents Checking the History of Printed Documents Checking Error Information Checking the Maximum Print Speed Checking System Manager Information

Viewing the Page Counter Value

NOTE

The name of the application that requested printing may be added to the file name of printed documents.

Checking the Current Status of Print Documents

You can check a list of up to five documents that are currently printing or waiting to be printed.

Log on to the Remote UI (Starting the Remote UI) > [Status Monitor/Cancel] > [Job Status]

Status Monitor/Cancel	L8P6838w/5018w/				To Portel Lo	gin User: System Manager Log Mail to System Man
	Status Monitor/Car	icel: Print: Job Status				551156101153
Job Status Job Log	Print: Job Status				Last	Updated 01/01 2013 08:23 46 PM
Error Information	Print Job Stat	15				
Device Features	Job Number	Job Name	Status	Job Operation	Job Type	Time
Device Information Check Counter	0022	Document 1.rtf	Printing	Cancel	Printer	01/01 2013 08:23:36 PM
	×					
						Copyright CANON INC.

You can click [Cancel] to delete the print job for a document that is currently printing or waiting to be printed.

NOTE

- Click [Job Number] to display detailed information about a document. For example, you can check the user name and the print page count of the document.
- If an error occurs, but printing can continue nevertheless, [Continue/Retry] appears in [Job Operation]. You can click [Continue/Retry] to clear the error and resume printing. However, the printing may not be performed properly if you use the Continue/Retry function to clear the error and resume printing.

Checking the History of Printed Documents

The history displays a list of up to 50 printed documents.

Log on to the Remote UI (Starting the Remote UI) > [Status Monitor/Cancel] > [Job Log]

C C Mtp://182.068.0.215/jhis.plic		_		To Do	and Loople I	P - E G X 🕜 C
Status Monitor/Cancel			100		a togar	Mail to System Man
int	Status Monitor/C	ancel: Prin	t Job Log			
to Joh Status	Print: Job Log				Last Upda	8401012013082741PM
Error Information	Print Job Lo	0				
Device Features	Job Number	Benuk	Start Time	End Time	Job Type	File Name
Device Information	0022	Error	01/01 2013 08:23:36 PM	01/01 2013 08:25:24 PM	Printer	Document 1.rtf
Check Counter	0021	OK	01/01 2013 08:19:21 PM	01/01 2013 08:19:33 PM	Printer	Document 1.rtf
	0020	OK	01/01 2013 07:24:06 PM	01/01 2013 07:24:24 PM	Printer	Network Status Print
	0019	OK	01/01 2013 07:23:45 PM	01/01 2013 07:23:53 PM	Printer	Configuration Page
	0018	OK	01/01 2013 07:22:30 PM	01/01 2013 07:22:42 PM	Report	
	0017	OK	01/01 2013 06:14:44 PM	01/01 2013 06:23:31 PM	Printer	Document 3.rtf
	0016	OK	01/01 2013 06:13:52 PM	01/01 2013 06:23:16 PM	Printer	Document 2.nf
	0015	OK	01/01 2013 06:13:44 PM	01/01 2013 06:23:10 PM	Printer	Document 1.rtf
	0014	OK .	01/01 2013 06:05:49 PM	01/01 2013 06:11:20 PM	Printer	Document 3.rtf

Checking Error Information

When an error occurs, you can display this page by clicking the message displayed under [Error Information] on the Portal Page (main page). **OPortal Page (Main Page)**


Ť.	Log on to the Remote UI (Starting the Remote UI) [Status Monitor/Cancel] [Frror Information]

Status Monitor/Car	cal	Mail to System Man
Vint	Status Monitor/Cancel: Error Information	
I Job Status	Error Information	Last Updated 01/01 2013 08:30:06 PM
Jab Los Error Information	One or more errors have occurred.	
Denke Features	Error information	
Device Information	The cover is open. Pallow the procedure shown on the contr	al panel or described in the user's manual to securely class the cove
		Depyrgnt CANON INC.

Checking the Maximum Print Speed

This page displays the maximum print speed of the machine.





Checking System Manager Information

This page displays information about the machine and the system manager. This information is set in [System Management] on the [Settings/Registration] page (**Changing Machine Settings**).

5



LIP6030w/6013w/	L8P6838w/6018w/		To Portal Login User: System Manager Log
Status Monitor/Cancel			Mail to System Man
Print	Status Monitor/Cancel: Device Inform	ation	
= Job Status = Job Log	Device Information	12	Last Updated 01/01 2013 08:47:08 PM
= Error Information	Device Basic Information		
Device Features	Vanufacture:	CANON INC.	
Device Information	Device Name:	L5P6030w6018w	
- Check Counter	Location:		
	Product Name:	L5P6030w6018w	
	System Manager Information		
	System Manager Name:	Administrator	
	Contact Information:		
	E-Mail Address:		
	Support Link:		
	System Manager Comment:		

Viewing the Page Counter Value

This page displays a total page count of the documents that have been printed.



LINKS

Remote UI Screens

Changing Machine Settings LBP6030w

You can change various machine settings from your computer by using the Remote UI. For example, you can change network and security settings.

NOTE

However, to change settings under [System Management Settings], you must log on in System Manager Mode.



2 Click [Settings/Registration].

laments.	LBPS030wf613w LBP5030wf613w	Login User: System Manager Log O
Remote UI: Portal		Mail to System Manag
	Last Updated 01101 2015 00:34:20 PM	Status Monitos/Cancel
Jevice Basic Information		V
Device Status		Settings/Registration
Printet: Roady to print.		477
Error Information		
No errore.		
Sepport Link		
Support Link:		

3 Click the menu item you want to set, displaying it, and then click [Edit].

LIP6030wr6010w	(LIPEDDw/6010w)	To Postel Login User: System Manager Log (
Settings/Registration		Mail to System Manag
Preferences	Settings/Registration: Preferences: Display Settings	
Display Settings	Display Settings	
Timer Settings		
AdjustmentMaintenance	Display Settings	
 Utility Menu 		Eat.
System Management Settings		
II System Management	Remote UI Language: English	
II Security Settings	x	
II Network Settings	-	
II Initialize Setting Information		
		Copyright CANON INC. 21

For details about the settings menu, see Setting Menu List.

LINKS

©Remote UI Screens

 \mathbf{T}

 \mathbf{T}

Setting Menu List LBP6030w

This section describes the menu items that can be set using the Remote UI. Default settings are marked with a dagger (†).

[Preferences] Menu

- ODisplay Settings
- C Timer Settings

[Adjustment/Maintenance] Menu OUtility Menu

[System Management Settings] Menu

- System Management
- Security Settings
- Network Settings
- Initialize Setting Information

Display Settings

Select the display language used for the Remote UI screens.

Remote UI Language Chinese (Simplified) English † French German Italian Japanese Spanish




Log on to the Remote UI (**Starting the Remote UI**) > [Settings/Registration] > [Display Settings] > [Edit] > Select the display language > [OK]

-		
C 🔁 🛞 kttp://182.068.0.215/p.d	pley,petring.html	P-86× 0 ℃ 8
LIPE030wr6013	a / LEPSEDBw/6018w /	o Portel Login User: System Manager Log Out
Settings/Registration		Meil to System Manager
Preferences	Settings/Registration Preferences: Display Settings > Edit Display Settings	
Display Settings	Edit Display Settings	
Timer Settings		
AdjustmentMaintenance	Change the following settings.	
 Utility Menu 		OK Cancel
System Management Settings	Display Settings	
System Management	Remote UI Language: English	
Security Settings	Hamole of Language: (Crym)	
Network Settings	x .	
Initialize Setting Information		
		Copyright CANON INC. 2913

[Remote UI Language]

Selects the display language used for the Remote UI screens.



Make settings related to time, such as the time zone.

Time Zone UTC-12:00 to UTC 0:00⁺ to UTC+12:00

```
Use Daylight Saving Time
   Off †
   On
      Start
          January to March<sup>†</sup> to December
          1st to Last<sup>†</sup>
          Monday to Sunday<sup>†</sup>
      End
          January to October<sup>+</sup> to December
          1st to Last<sup>†</sup>
          Monday to Sunday<sup>+</sup>
Auto Sleep Time
   Off
   After 1 minute<sup>†</sup>
   After 5 minutes
   After 10 minutes
   After 15 minutes
   After 30 minutes
   After 60 minutes
   After 90 minutes
   After 120 minutes
   After 150 minutes
   After 180 minutes
Auto Shutdown Time
   Off
   After 1 hour
   After 2 hours
   After 3 hours
   After 4 hours<sup>†</sup>
   After 5 hours
   After 6 hours
   After 7 hours
   After 8 hours
```



Log on to the Remote UI (Starting the Remote UI) > [Settings/Registration] > [Timer Settings] > [Edit] > Item settings > [OK]

C 182.068.0.215/p.tim	1 - 1		P-BdX 0 000
LIP6030w/6019w	/ LIP5839w/6018w/	To Portel Login L	Iser: System Manager Log Out
Settings/Registration			Mail to System Manager
Preferences Display Settings Timer Settings AdjustmentMaintenance Utility Menu	Settings Registration Preferences 1 Edit Timer Settings Change the following sattings.	iner Sellings > Edit Timer Sellings	OK Cancel
System Management Settings System Management Socurity Settings	Timer Settinos		
 Network Sating Network Sating Information Initiatize Setting Information 	Use Daylight Saving Time Start End: Auto Stoep Time: Auto Struktown Time:	Mach V and Senday V Cethar V and Senday V Alter Trinsle N Alter Frons N	
			Cepylight CANON INC. 2013

[Time Zone]

Set the time zone of the region where the machine will be used.

NOTE:

Coordinated Universal Time (UTC) is the primary time standard by which the world regulates clocks and time. The correct UTC time zone setting is required for Internet communications.

[Use Daylight Saving Time]

Enable or disable daylight saving time. If daylight saving time is enabled, specify the dates from which and to which daylight saving time is in effect.

[Auto Sleep Time]

The machine enters sleep mode automatically when it remains idle for a certain length of time. Specify the length of time until the machine enters auto sleep. We recommend using the factory default settings to save the most power. **Setting Sleep Mode**

[Auto Shutdown Time]

You can set up the machine to automatically turn itself OFF after it remains idle for a certain length of time. This prevents wasted power consumption caused by forgetting to turn the machine OFF. Specify the length of time until the machine turns itself OFF. **Setting Auto Shutdown**

Utility Menu

You can clean the fixing unit inside the machine.

Cleaning 🔽

Clean the fixing unit if black spots or streaks appear on printouts. Note that you cannot clean the fixing unit when the machine has documents waiting to be printed. To clean the fixing unit, you need plain A4 size paper. Before starting, load A4 size paper in the multi-purpose tray. (**Cleaning Paper in the Multi-Purpose Tray**)

Log on to the Remote UI (Starting the Remote UI) [Settings/Registration] [Utility Menu] [Cleaning] [Execute] [OK]

LIPCOLOWIG11	he (LBPGB) Inv/S010e /	To Portel Login User: System Manager Log On
(Settings/Registration		Mail to System Manage
Preferences = Display Settings = Trares Settings Adjustment Maintenance = Utility Manes System Management = Security Settings = Network Settings = Instruct Settings Interaction	SetingsReposition Adjustment/Variationse Utility Version Cleaning Cleaning Cleaning Cleaning Terming Cleaning Terming Cleaning Terming Cleaning Terming Cleaning	Exocuto
		Copyright CANON INC. 281

- The paper is fed slowly into the machine, and cleaning starts. The cleaning is done when the paper is completely ejected.
 - Cleaning cannot be cancelled once it starts. Wait until it finishes (approx. 140 seconds).

System Management

You can specify that a PIN (system manager password) is required when logging in to the Remote UI in System Manager Mode, and you can register information about the system manager, such as name and contact information. You can also register a name to identify this machine, and register its location.





Log on to the Remote UI in System Manager Mode (Starting the Remote UI) > [Settings/Registration] > [System Management] > [Edit] > Item settings > [OK]

C 10 182 188.0 215 (m. system				P-86X 000
LIPEODWG010w (To Board 1 cole the	er: System Manager Log Out
(A) Settings/Registration				Mail to System Manager
Preferences = Display Settings	SetingsRegistration, System Manag Edit System Management	ernent Settings. System Manag	ement > Edit System Manag	
= Timer Settings Adjustment/Maintenance = Utility Mene	Change the following sottings.			OK Cancel
System Management Settings	System Manager Information			
B Sycken Management = Secury Sentrys = Network Settings = Initiation Setting Information	System Managar PN: SatChango PN PR Confine System Managar Name: Context Information: E-Mail Actives: System Managar Comment.	Not set.	(Hac 7 digits) (Hac 7 digits)	
6	Device Information Device Name: Location: Sapport Link:	LBP0030w46010w		
				Copyright CANON INC. 2813

[System Manager Information]

Specify the PIN and other system manager information. **©Setting System Manager Passwords**

[Device Information]

[Device Name]

Enter up to 32 alphanumeric characters for the name of the machine.

[Location]

Enter up to 32 alphanumeric characters for the location of the machine.

[Support Link]

Enter a link to support information about the machine. The link can be up to 128 alphanumeric characters long. The link is displayed on the Portal Page (main page) of the Remote UI.

Security Settings

Enable or disable encrypted communication via SSL and IP address packet filtering.

Remote UI Settings

Select whether to use SSL encrypted communication. SEL Encrypted Communication for the Remote UI

Use SSL	
Off +	
On	

Key and Certificate Settings

Register key pairs, or generate them on the machine. You can check and verify registered key pairs. **OConfiguring Settings for** Key Pairs and Digital Certificates

CA Certificate Settings

Register a CA certificate. One CA certificate is preinstalled. You can check and verify registered CA certificates. Settings for Key Pairs and Digital Certificates

IP Address Filter

Specify whether to allow or reject packets sent to or received from devices with specified IP addresses.


IPv4 Address: Outbound Filter

Do not allow the machine to send data to a computer with a specified IPv4 address. **Prestricting Communication by Using** Firewalls

Use Filter Off† On
Default Policy Reject Allow†

IPv4 Address: Inbound Filter

Reject data received by the machine from a computer with a specified IPv4 address. **©Restricting Communication by Using** Firewalls



IPv6 Address: Outbound Filter

Do not allow the machine to send data to a computer with a specified IPv6 address. **©Restricting Communication by Using** Firewalls



IPv6 Address: Inbound Filter

Reject data received by the machine from a computer with a specified IPv4 address. **©Restricting Communication by Using** Firewalls



Network Settings

Make settings related to network functions.

TCP/IP Settings

Specify settings for using the machine in a TCP/IP network, such as IP address settings.

IPv4 Settings

Specify settings for using the machine in an IPv4 network. Setting IPv4 Address Configuring DNS

IP Address Settings	
Auto Acquire	
Select Protocol	
Off	
DHCP ⁺	
BOOTP	
RARP	
Auto IP	
On t	
Off	
IP Address	
Subnet Mask	
Gateway Address	
DNS Settings	
Primary DNS Server Address	
Secondary DNS Server Address	

Host Name Domain Name DNS Dynamic Update Off† On DNS Dynamic Update Interval: 0 to 24⁺ to 48 (hours) **mDNS Settings** Use mDNS Off On t mDNS Name **DHCP Option Settings** Acquire Host Name Off On t DNS Dynamic Update Off[†] On

IPv6 Settings

Specify settings for using the machine in an IPv6 network. Setting IPv6 Addresses Oconfiguring DNS

IP Address Settings
Use IPv6
Off ⁺
On
Stateless Address
Off
On ⁺
Use Manual Address
Offt
On
IP Address
Prefix Length: 0 to 64 ⁺ to 128
Default Router Address
Use DHCPv6
Off+
On
DNC Cottings
DNS Settings
Primary DNS Server Address
Secondary DNS Server Address
Use Same Host Name/Domain Name as IPv4
Off
On†
Host Name
Domain Name
DNS Dynamic Update
Off+
On
Register Manual Address
Off ⁺
On
Register Stateful Address
Off ⁺
On
Register Stateless Address
Off †
On
DNS Dynamic Update Interval: 0 to 24 ⁺ to 48 (hours)
mDNS Settings
Use mDNS
Off
On†
Use Same mDNS Name as IPv4
Off
On†
mDNS Name

WINS Settings

Specify settings for Windows Internet Name Service (WINS), which provides a NetBIOS name for IP address resolutions in a mixed network environment of NetBIOS and TCP/IP. **Configuring WINS**

WINS Resolution Off⁺ On WINS Server Address Scope ID

LPD Print Settings

Enable or disable LPD, a printing protocol that can be used on any hardware platform or operating system. Configuring Printing Protocols and Web Services

Use LPD Printing Off On t

NetBIOS Settings

Set a NetBIOS name and a workgroup name, which must be set to register this machine with a WINS server. **Configuring NetBIOS**

NetBIOS Name Workgroup Name

RAW Print Settings

Enable or disable RAW, a Windows specific printing protocol. OConfiguring Printing Protocols and Web Services

Use RAW Printing Off On[†]

WSD Settings

Enable or disable automatic browsing and acquiring information for the machine by using the WSD protocol that is available on Windows Vista/7/8/Server 2008/Server 2012. Configuring Printing Protocols and Web Services

Use WSD Printing Off On†
Use WSD Browsing Off On†
Use Multicast Discovery Off On †

SSL Settings

Specify the key pair to use when conducting SSL encrypted communication with the Remote UI. **Descripted Communication for the Remote UI**

Multicast Discovery Settings

Specify whether the machine should respond to discovery packets when multicast discovery is performed on the network using Service Location Protocol (SLP). Configuring SLP Communication with imageWARE

Respond to Discovery Off On† Scope Name

Port Number Settings

Change port numbers for protocols according to your network environment. **OChanging Port Numbers**

```
LPD

1 to 515<sup>+</sup> to 65535

RAW

1 to 9100<sup>+</sup> to 65535

HTTP

1 to 80<sup>+</sup> to 65535

SNMP

1 to 161<sup>+</sup> to 65535

WSD Multicast Discovery

1 to 3702<sup>+</sup> to 65535

Multicast Discovery

1 to 427<sup>+</sup> to 65535
```

MTU Size Settings

Select the maximum size of packets the machine sends or receives. OChanging the Maximum Transmission Unit

SNTP Settings

Specify whether to acquire the time from a time server on the network. **Oconfiguring SNTP**

Use SNTP Off†	
On	
NTP Server Name	
Polling Interval: 1 to 24 ⁺ to 48 (hours)	

SNMP Settings

Specify the settings for monitoring and controlling the machine from a computer running SNMP-compatible software. **Omnitoring** and Controlling the Machine with SNMP

SNMPv1 Settings
Use SNMPv1
Off
On t
Community Name 1
MIB Access Permission 1
Read/Write [†]
Read Only
Community Name 2
MIB Access Permission 2
Read/Write [†]
Read Only
Dedicated Community Settings
Off
Read/Write [†]
Read Only
SNMPv3 Settings
Use SNMPv3
Off
On†
User Settings 1/User Settings 2/User Settings 3
Context Settings
Printer Management Information Acquisition Settings
Acquire Printer Management Information from Host Off ⁺

On

Dedicated Port Settings 🔁

Enable or disable the dedicated port. The dedicated port is used when using the Printer Status Window to make machine settings and acquire information about the machine.

Use Dedicated Port Off On⁺

Log on to the Remote UI in System Manager Mode (**Starting the Remote UI**) > [Settings/Registration] > [Network Settings] > [Dedicated Port Settings] > [Edit] > Select whether to use > [OK] > Restart the machine

A		
C 8 http://182.068.0.215/m_net		P+B6X 0 🗘 🖯
LIP6030wr6010w	(LIIPGIDIWG018w)	To Portal Login User: System Manager Log Out
Settings/Registration		Mail to System Manager
Preferences = Display Settings	Settings/Registration System Management Settings Ne Settings	etwork Settings > Dedicated Port Settings > Edit Dedicated Port
Timer Settings	Edit Dedicated Port Settings	
AdjustmentMaintenance Utility Menu	Change the following settings. Changes will be effective after the main power is turne	ed OFF and ON.
System Management Settings System Management		OK Cancal
II Security Settings	Dedicated Port Settings	
Network Settings	I Use Dedicated Port	
 Initialize Setting Information 		
		Depyrgint GAWGW INC. 2013

[Use Dedicated Port]

Select the check box to use the dedicated port. Clear the check box if you do not want to use it.

IMPORTANT:

If you clear the check box, the Printer Status Window cannot acquire machine information.

Waiting Time for Connection at Startup

Specify a wait time for connecting to a network. Select the setting depending on your network environment. Setting a Wait Time for Connecting to a Network

Waiting Time 0[†] to 300 (seconds)

Wireless LAN Settings 🔽

You can check wireless LAN settings and status information. Wireless LAN settings cannot be changed from the Remote UI. Make wireless LAN settings from the computer using the MF/LBP Network Setup Tool. (©Connecting to a Wireless LAN)

Log on to the Remote UI in System Manager Mode (Starting the Remote UI) > [Settings/Registration] > [Network Settings] > [Wireless LAN Settings] > Check settings and information

-			
C 🔁 🔄 😡 http://182.068.0.215/rm_netw	ork_wirelesslam.html		P-16X 0 0 0
LBP6030w/9019w /	LEP6038w6018w7		To Portel Login User: System Manager Log Out
Settings/Registration			Mail to System Manager
Preferences	Settings/Registration: System Varage	ment Settings: Network Settings	> Wireless LAN Settings
Display Settings Timer Settings	Wireless LAN Settings	1	
AdustmentMaintenance	Wireless LAN Information		
 Utility Menu 	WAC Addmina:	2440A-64-28-AE-73	
System Management Settings	Wireless LAN Status:	Good	
System Management	Latent Error Information:	No errora.	
II Security Settings	Channel:	11	
Network Settings Initialize Setting Information	SSID Sottings		
- management and	534D Settings:	0024A50EBD68-1	
	Security Settings		
	Security:	WPA/WPA2-P5K	
	WPA/WPA2-PSK Settings		
	Encryption for WPA/WPA2:	Auto	
	WPAWPA2-PSK:		
	×		
	-		
			Copyright CANCIN INC. 2013

[MAC Address]

Displays the MAC address of the wireless LAN.

[Wireless LAN Status]

Displays the connection status (signal strength) of the wireless LAN.

[Latest Error Information]

Displays information about the latest failure to make a wireless LAN connection.

[Channel]

Displays the wireless LAN channel that is currently in use.

[SSID Settings]

Displays the SSID of the connected wireless LAN router.

[Security Settings]

Displays the type of encryption that is currently being applied.

Initialize Setting Information

Initializes settings and returns the machine to the factory default state.

Initialize Menu

Returns the settings in the [Preferences] Menu to the factory default settings. OInitializing Preferences Settings

Initialize System Management Settings

Returns the settings in the [System Management Settings] Menu to the factory default settings. OInitializing System Management Settings

Initialize Key and Certificate

Returns key and certificate settings to the factory default settings. [2] Initializing Key and Certificate Settings

Troubleshooting

When a problem occurs, check this chapter to find out solutions before contacting Canon.

Paper Jams

If the paper jams, see **OClearing Paper Jams** to remove the jammed paper.



A Message Appears

If the Printer Status Window displays an error message, see ⁽⁾ When an Error Message Appears.



Common Problems

If you suspect that the machine is malfunctioning, see the following sections before contacting Canon.



Common Problems Installation/Settings Problems Printing Problems

Printing Results are Not Satisfactory

If printing results are not satisfactory, see **OWhen You Cannot Print Properly**.



When a Problem Cannot Be Solved

If a problem persists, see the following to find out where to contact. OWhen a Problem Cannot Be Solved



Clearing Paper Jams

If paper jams, <Paper Jam inside Printer> is displayed in the Printer Status Window. Use the following procedure to remove the jammed paper. Before starting, carefully read the safety instructions in **OImportant Safety Instructions**.



IMPORTANT

When removing the jammed paper, do not turn OFF the machine

Turning OFF the machine deletes the data that is being printed.

If paper tears

Remove all the paper fragments to prevent them from becoming jammed.

If paper jams repeatedly

- Tap the paper stack on a flat surface to even the edges of the paper before loading it into the machine.
- Oheck that the paper is appropriate for the machine. OPaper
- Oheck that no jammed paper fragments remain in the machine.

Do not forcibly remove jammed paper from the machine

Forcibly removing the paper may damage parts in the machine. If you are not able to remove the paper, contact your local authorized Canon dealer or the Canon help line. **OWhen a Problem Cannot Be Solved**

NOTE

If you click [Troubleshooting Details], you can display the same troubleshooting methods that are described in this manual.




How to Clear Paper Jams


If there is paper loaded in the multi-purpose tray, remove it first. If the jammed paper cannot be removed easily, do not try to pull it out forcibly. Proceed to the next step.

1 Gently pull out the paper.

Pull the paper straight out.



- 2 Check whether paper is jammed inside the machine.
 - **1** Open the top cover.




2 Remove the toner cartridge.




3 Gently pull out the paper.

Hold both edges of the paper, pull the leading edge of the paper down, and then pull it out.



4 Replace the toner cartridge.

Align with the toner cartridge guide (6), and push firmly all the way in.



- **5** Close the top cover.
- The paper jam message disappears, and the machine is ready to print.

When an Error Message Appears

Bidirectional communication is not enabled.

Checking Bidirectional Communication

Enable bidirectional communication, and restart the computer.

Cannot Communicate with Printer

An error message appears in the Printer Status Window when there is a problem with print processing, when the machine cannot communicate, or when some other problem prevents normal operation. See the following list for more information about error messages.

In a terminal connection environment, the machine is redirected and a setting problem prevents

If the machine has been redirected in a terminal connection environment, such as a remote desktop application or XenAPP (MetaFrame), there may be a problem with firewall or other settings that prevents communication with the machine. Check the communication settings of the server and client. For details, contact your network administrator.

Cannot Communicate with Server

communication.

Your computer is not connected to the print server.

Make the proper connection between your computer and the print server.

The print server is not running.

Start the print server.

The machine is not shared.

Make the proper printer sharing settings.
 Printer Driver Installation Guide

You lack user rights to connect to the print server.

Ask the administrator of the print server to change your user rights.

[Network discovery] is not enabled. (Windows Vista/7/8/Server 2008/Server 2012)

Enable [Network discovery].
 Carbon Enabling [Network discovery]

Check Paper

The paper size that was set in the printer driver is different from the paper size of the last print job.

When you try printing with the machine after changing the paper size setting, this message is displayed to prompt you to check the paper size. Check the size of the paper that is loaded in the multi-purpose tray.

When the paper size specified in the printer driver matches, or when you want to print using the currently loaded paper

Without loading new paper, press the 🛓 (Paper) key, or click 📄 in the Printer Status Window.

When the paper size specified in the printer driver does not match Load paper of the specified size, and press the ↓ (Paper) key on the machine. ↓ Loading Paper in the Multi-Purpose Tray



The job may not be printed normally.

can be clicked to continue printing. If you continue printing and the results are not satisfactory, print the job again.

Check Printer

The toner cartridge is not set.

Set the toner cartridge correctly.
 OHow to Replace Toner Cartridges

There is paper from a paper jam left inside the machine.

Thoroughly check for fragments of paper that may be left inside the machine. If you find any, remove them. If the paper is difficult to remove, do not try to forcibly pull it out of the machine. Follow the instructions in the manual to remove paper.

Clearing Paper Jams

Communication Error

The machine is not connected with a USB cable.

Connect the machine to your computer using a USB cable.
 Printer Driver Installation Guide

The machine is not turned ON.

The (Power) indicator does not light if the machine is not turned ON. Turn it ON. If the machine does not respond when you press the power switch, check to make sure that the power cord is connected correctly and then try again to turn the power ON.

©Turning the Power ON

Incompatible Printer

A printer other than this machine is connected.

Make the proper connection between your computer and the machine.
 Connecting to a Wireless LAN

NOTE

If you are not sure on how to make a USB connection, see Printer Driver Installation Guide.

Incorrect Port

 $\mathbf{\Sigma}$

 \mathbf{T}

 \mathbf{T}

The machine is connected to an unsupported port.

Check the port.
Checking the Printer Port

NOTE

If the port you need is not available

- If you are using a network connection, configure the port. OCONFIGURING Printer Ports
- If you are using a USB connection, reinstall the printer driver. Printer Driver Installation Guide

Insufficient Printer Memory

The document being printed contains a page with a very large amount of data.

This machine cannot print the data. Click [14] to cancel the print job.

Network Communication Error

The machine is not connected via the network.

Make the proper network connection between your computer and the machine.
 Connecting to a Wireless LAN

The machine is not turned ON.

The () (Power) indicator does not light if the machine is not turned ON. Turn it ON. If the machine does not respond when you press the power switch, check to make sure that the power cord is connected correctly and then try again to turn the power ON.
 Turning the Power ON

Communication is restricted by a firewall.

- Ask the system manager of the machine about the problem.
 Restricting Communication by Using Firewalls
- If the machine cannot be accessed because of incorrect settings, use the (n) (Wi-Fi) key to initialize the system management settings.

OInitializing by Using the Wi-Fi Key

Out of Paper or Paper Could Not be Fed

There is no paper in the multi-purpose tray. Or the paper could not be fed.

Set the paper correctly, and then press the
 (Paper) key on the machine.
 (Paper) her in the Multi-Purpose Tray

Paper Jam inside Printer

There is a paper jam inside the machine.

Do not try to forcibly pull jammed paper out of the machine. Follow the instructions in the manual to remove paper.

Service Error

An error has occurred inside the machine.

- Turn OFF the machine, wait for at least 10 seconds, and turn it back ON. If the message does not reappear, you can continue using the machine.
- If the same message reappears after you turn the power back ON, turn the power OFF, unplug the power plug from the AC power outlet and contact your local authorized Canon dealer. Make a note of the error code that is displayed, and have it ready when you contact your local authorized Canon dealer.



Top Cover Open

 $\mathbf{\Sigma}$

The top cover is not completely shut.

Shut the top cover firmly.



NOTE

If the top cover will not close completely, check to make sure that the toner cartridge has been pushed all the way in.

Common Problems

If you encounter problems when using the machine, check the items in this section before contacting us. If the problems persist, contact your local authorized Canon dealer or the Canon help line.

Check the Following

- → Is the machine turned ON? / Is the power cord connected?
 - The () (Power) indicator does not light if the machine is not turned ON. If the machine does not respond when you press the power switch, check to make sure that the power cord is connected correctly and then try again to turn the power ON.
 Turning the Power ON
- → Is the machine connected via wireless LAN (LBP6030w only) or a USB cable?
 - Check whether the machine is connected correctly. In the case of wireless LAN, check whether the ((n) (Wi-Fi) indicator is lit. If it is not lit, the machine is not connected via wireless LAN.
 When the machine cannot connect to the wireless LAN
- Does the Printer Status Window display an error message?
 - If a problem occurs, a message is displayed in the window.
 Printer Status Window
 When an Error Message Appears

If a problem persists even after checking

Click the link that corresponds to the problem.

Installation/Settings Problems
 Printing Problems

Installation/Settings Problems

Together with this section, see **Common Problems**.

Problems with the Wireless LAN Connection (LBP6030w)
 Problems with the USB Connection
 Problems via the Print Server

Problems with the Wireless LAN Connection (LBP6030w)

Remote UI is not displayed.

The (ψ) (Wi-Fi) indicator lights if a connection has been established. Check whether it is lit, and whether IP addresses are correct. Then try to start the Remote UI again.
 Front Side

Viewing Network Settings

- Are you using a proxy server? If you are using a proxy server, add the machine's IP address to the [Exceptions] list (addresses that do not use the proxy server) in the Web browser's proxy settings dialog.
- Is communication on your computer restricted by a firewall? If the Remote UI cannot be displayed because of incorrect settings, use the (n) (Wi-Fi) key to initialize the system management settings.
 Restricting Communication by Using Firewalls

Initializing by Using the Wi-Fi Key

A connection to a network cannot be established.

Check whether the machine is properly installed and ready to connect to the network.
 When the machine cannot connect to the wireless LAN

You are unsure of the IP address that was set.

OViewing Network Settings

When the machine cannot connect to the wireless LAN



Check the status of your computer

- Have the settings of the computer and the wireless router been completed?
- Are the cables of the wireless router (including the power cord and LAN cable) correctly plugged in?
- Is the wireless router turned ON?

If the problem persists even after checking the above:

- Turn OFF all of the devices, and then turn them ON again.
- Wait for a while, and try again to connect to the network.



Check whether the machine is turned ON

- \bullet The (Power) indicator does not light if the machine is not turned ON.
- If the machine is turned ON, turn it OFF, and then turn it back ON.





Check the installation site of the machine and the wireless router

- Is the machine too far from the wireless router?
- Are there any obstacles such as walls between the machine and the wireless router?
- Are there any appliances such as microwave ovens or digital cordless phones that emit radio waves near the machine?





Reset the wireless LAN settings Connecting to a Wireless LAN

NOTE

When you need to manually set up the connection

If the wireless router is set up as described below, enter the required information manually.

- The stealth function is enabled.
- ANY connection refusal* is enabled.
- The WEP key number to use is set to a number from 2 to 4.
- The automatically generated WEP key (hexadecimal) is selected.
- * A function in which the wireless router refuses the connection if the SSID of the device to be connected is set to "ANY" or is blank.

When you need to change the settings of the wireless router

If the wireless router is set up as described below, change the settings of the router.

- MAC address filtering is enabled.
- When only IEEE 802.11n is used for the wireless communication, WEP is selected or the WPA/WPA2 encryption method is set to TKIP.

Problems with the USB Connection

Communication is not possible.

- Exchange the USB cable. If the USB cable is a long one, exchange it for a shorter one.
- If you are using a USB hub, connect the machine directly to your computer using a USB cable.

Problems via the Print Server

You cannot find the print server to connect to.

- Are the print server and computer connected correctly?
- Is the print server running?
- Do you have user rights to connect to the print server? If you are not sure, consult the print server's administrator.
- Is [Network discovery] enabled? (Windows Vista/7/8/Server 2008/Server 2012)
 Enabling [Network discovery]

You cannot connect to a shared printer.

- On the network, does the machine appear among the printers of the print server? If it is not displayed, contact the network or server administrator.
 - ODisplaying Shared Printers in the Print Server

Printing Problems

Together with this section, see **Common Problems**. For problems related to connection with the computer, see **DInstallation/Settings Problems**.

Printing results are not satisfactory, or the paper is curled or wrinkled.

OWhen You Cannot Print Properly

You cannot print.

- Can you print a Windows test page? If you can print a Windows test page, there is no problem with the machine or the printer driver. Check the print settings of your application.
 Printing a Test Page in Windows
 - If you cannot print a test page, check the following according to your environment.
 - Wireless LAN connection
 - Check the connection status (signal strength) of the wireless LAN.
 Viewing Network Settings

NOTE:

If the connection is poor, try the following.

- Change the channel of your wireless LAN router. If you have more than one router, set the channels to be at least five channels apart.
- . If you can change the radio output power of your wireless LAN router, raise the output power.
- If your computer is connected to the wireless LAN, are the computer and this machine using the same wireless LAN router SSID? If they are different, reset the wireless LAN connection settings of this machine.

Viewing Network Settings Checking the SSID to Which Your Computer Is Connected

Connecting to a Wireless LAN

NOTE:

When you reset wireless LAN connection settings

- When making settings with the MF/LBP Network Setup Tool, select [Easy Setup] > [My wireless LAN access point does not have a WPS button or I cannot find the button].
- As the wireless LAN router, select the one with the SSID to which the computer is connected.
- Have you selected the correct port? If there is no port to use, create a port.

Checking the Printer Port Configuring Printer Ports

- Is communication on your computer restricted by a firewall? If the machine cannot be accessed because of incorrect settings, use the (m) (Wi-Fi) key to initialize the system management settings.
 Restricting Communication by Using Firewalls
 Initializing by Using the Wi-Fi Key
- Disable security software and other resident software.
- Reinstall the printer driver. Printer Driver Installation Guide
- Can you print from other computers on the network? If you also cannot print from other computers, contact your local authorized Canon dealer or the Canon help line.

USB connection

- Have you selected the correct port? If there is no port to use or you are not sure, reinstall the printer driver. When you reinstall the printer driver, the correct port is created automatically.
 Checking the Printer Port
 Printer Driver Installation Guide
- Is bidirectional communication enabled? Enable bidirectional communication, and restart the computer.
 Checking Bidirectional Communication
- Disable security software and other resident software.
- Connect to another USB port on the computer.
- Delete the USB class driver, and then reinstall the printer driver. Printer Driver Installation Guide
- Can you print from a USB connection to another computer? If you also cannot print from other computers, contact

Via print server

- Can you print from the print server? If you can print from the print server, check the connection between your computer and the print server.
 Problems via the Print Server
- Disable security software and other resident software.
- Reinstall the printer driver.
 Printer Driver Installation Guide
- Can you print from other computers via the print server? If you also cannot print from other computers, contact your local authorized Canon dealer or the Canon help line.

It takes a long time before printing starts.


Did you print on narrow paper? After you print to narrow width paper, the machine may wait until the temperature inside the machine has fallen before resuming printing. This is done to maintain printing quality. As a result, it may take some time before the next job is printed. Wait until the machine is ready to print. Printing will resume when the temperature inside the machine has fallen.

A blank sheet is output (nothing is printed).

Did you pull the sealing tape out when loading the toner cartridge? If you did not pull it out, remove the toner cartridge, pull the sealing tape out, and reload the toner cartridge.
 How to Replace Toner Cartridges

When You Cannot Print Properly

If printing results are not satisfactory, or paper creases or curls, try the following solutions. If the problems persist, contact your local authorized Canon dealer or the Canon help line.



Printing Results Are Not Satisfactory

Grime inside the machine may affect printing results. First try cleaning the machine. OCleaning the Machine

Smudge Marks Appear on the Bottom Edge of Printouts



Did you print data without margins, all the way to the edge of the page?

This symptom occurs if a margin is set to none in the printer driver. The range that can be printed on this machine is the range inside a 5 mm margin around the edge of the paper or a 10 mm margin around the edge of envelopes. Make sure to have margins around the document to print.

[Finishing] tab > [Advanced Settings] > [Expand Print Region and Print] > [Off]

Streaks Appear on Printouts



→ Are you using appropriate paper?

Check the usable paper types, and replace with appropriate paper.
 Paper

In the printer driver, set [Output Adjustment Mode] to [On].

[Quality] tab > [Advanced Settings] > [Output Adjustment Mode] > [On]

NOTE:

Printing speed may be slower if you set the mode to [On].

In the printer driver, change the setting of [Special Print Adjustment A]. The improvement effect is weakest for [Mode 1] and strongest for [Mode 4]. Try the adjustment starting with [Mode 1].

[Finishing] tab > [Advanced Settings] > [Special Print Adjustment A] > Select mode

NOTE:

When you select a stronger improvement effect, the overall print density becomes lighter. Also, edges may become less sharp and details may be rougher.

In the Printer Status Window, enable [Reduce Toner Spots Around Text].

ODisplaying the Printer Status Window

[Options] > [Device Settings] > [Assisting Print Settings] > Select the [Reduce Toner Spots Around Text] check box

IMPORTANT:

When you select this check box, print quality may be lower for some types of paper (especially thin paper) and some printing environments (especially environments with high humidity). In that case, clear the check box.

Turn over the paper (front to back) so that the print side is changed, and then reload the paper.

IMPORTANT

Rarely, the symptoms may worsen depending on the type of paper you are using. In that case, get the print side back to original.


→ Toner may adhere when you replace the toner cartridge or when you leave the machine without printing for a

long period.

In the printer driver, change the setting of [Special Print Adjustment B]. The remedial effect is weakest for [Mode 1] and strongest for [Mode 3]. Try the adjustment starting with [Mode 1].

[Finishing] tab > [Advanced Settings] > [Special Print Adjustment B] > Select mode NOTE:

When you select a stronger improvement effect, printing speed becomes slower.






Are you using appropriate paper?

- Check the usable paper types, and replace with appropriate paper.
 Paper
- In the Printer Status Window, enable [Reduce Toner Spots Around Text].
 Displaying the Printer Status Window

[Options] > [Device Settings] > [Assisting Print Settings] > Select the [Reduce Toner Spots Around Text] check box

IMPORTANT:

When you select this check box, print quality may be lower for some types of paper (especially thin paper) and some printing environments (especially environments with high humidity). In that case, clear the check box.





Are you using appropriate paper?

Check the usable paper types, and replace with appropriate paper.
 Paper

Is it time to replace the toner cartridge?

Materials inside the toner cartridge may have deteriorated. Replace the toner cartridge.
 How to Replace Toner Cartridges

Printouts Are Faded



 $\mathbf{\Sigma}$

 \mathbf{T}



➔ Is toner running low?

e Remove the toner cartridge, shake it 5 or 6 times to evenly distribute the toner inside the cartridge, and then

reload it into the machine. Ousing Up All of the Toner

Are you using appropriate paper?

Check the usable paper types, and replace with appropriate paper.
 Paper

➔ Have you specified the correct paper type?

- Specify the type of paper again, according to the type of paper that you are using.
 - Basic Print Operations

A Portion of the Page Is Not Printed/Printing Position is Wrong



Did you print data without margins, all the way to the edge of the page?

This symptom occurs if a margin is set to none in the printer driver. The range that can be printed on this machine is the range inside a 5 mm argin around the edge of the paper or a 10 mm margin around the edge of envelopes. Make sure to have margins around the document to print.

 \mathbf{T}

 \mathbf{T}

[Finishing] tab > [Advanced Settings] > [Expand Print Region and Print] > [Off]

White Streaks Appear/Printing is Uneven



Is toner running low?

Remove the toner cartridge, shake it 5 or 6 times to evenly distribute the toner inside the cartridge, and then reload it into the machine.
 Using Up All of the Toner

Is it time to replace the toner cartridge?

Materials inside the toner cartridge may have deteriorated. Replace the toner cartridge.
 OHow to Replace Toner Cartridges

White Spots Appear



- Are you using paper that has absorbed moisture?
 - Replace with appropriate paper.
 Paper

- → Are you using appropriate paper?
 - Check the usable paper types, and replace with appropriate paper.
 Paper

➔ Is it time to replace the toner cartridge?

- Materials inside the toner cartridge may have deteriorated. Replace the toner cartridge.
 Chow to Replace Toner Cartridges
- Are you printing a document with strong contrasts between light and dark, and does the white appear around text or edges in an image?
 - In the printer driver, set [Special Print Mode] to [Special Settings 2].

[Finishing] tab > [Advanced Settings] > [Special Print Mode] > [Special Settings 2]

NOTE:

Compared to the [Off] setting, the [Special Settings 2] setting selects lighter print density.

Black Spots Appear

 \mathbf{T}

 \mathbf{T}

 \mathbf{T}



Have you cleaned the fixing unit?

Clean the fixing unit.
 CFixing Unit

Reverse Side of Paper is Smudged



Have you loaded paper that is smaller than the size of the print data?

 ${\scriptstyle \bullet}$ Check to make sure that the paper size matches the size of the print data.

Printouts Are Grayish



Is the machine installed in a location where it is exposed to direct sunlight?
 Move the machine to a location where it is not exposed to direct sunlight.
 Relocating the Machine



➔ Are you trying to read a small barcode or one with thick lines?

Enlarge the barcode.

• In the printer driver, set [Special Print Mode] to [Special Settings 1].

[Finishing] tab > [Advanced Settings] > [Special Print Mode] > [Special Settings 1] NOTE:

When you specify [Special Settings 1], printouts may be faded.

 \mathbf{T}

Paper Creases or Curls

Paper Creases



Is the paper loaded correctly?

Paper may crease when it is not loaded below the load limit guides, or when it is loaded obliquely. **Coading Paper in the Multi-Purpose Tray**

→ Are you using paper that has absorbed moisture?

- Replace with appropriate paper.
- OPaper
- If you are using A4, Letter size, or Legal size paper, change the setting of [Wrinkle Adjustment] in the printer driver. The improvement effect is weaker for [Mode 1] and stronger for [Mode 2]. Try the adjustment starting with [Mode 1].

[Finishing] tab > [Advanced Settings] > [Wrinkle Adjustment] > Select mode

NOTE:

Printing speed becomes slower if you select stronger improvement.


→ Are you using appropriate paper?

- Check the usable paper types, and replace with appropriate paper.
 Paper
- In the printer driver, set [Output Adjustment Mode] to [On].

[Quality] tab > [Advanced Settings] > [Output Adjustment Mode] > [On]

NOTE:

Printing speed may be slower if you set the mode to [On].



NOTE:

Printing speed may be slower when you select this check box.

If you are using A4, Letter size, or Legal size paper, change the setting of [Wrinkle Adjustment] in the printer driver. The improvement effect is weaker for [Mode 1] and stronger for [Mode 2]. Try the adjustment starting with [Mode 1].

[Finishing] tab > [Advanced Settings] > [Wrinkle Adjustment] > Select mode

NOTE:

Printing speed becomes slower if you select stronger improvement.

Are you using appropriate paper?

Check the usable paper types, and replace with appropriate paper.

Paper

Paper Is Fed Incorrectly

Paper Is Not Fed/Two or More Sheets Are Fed Together



→ Is the paper loaded correctly?

- Fan the paper stack thoroughly so that the sheets are not stuck together.
- Check whether the paper is loaded correctly.
 Choading Paper in the Multi-Purpose Tray
- Check whether the number of sheets of paper loaded is appropriate and whether the appropriate paper is used.
 Paper
- Check whether mixed sizes and types of paper are loaded together.

When a Problem Cannot Be Solved

If a problem cannot be resolved, contact your local authorized Canon dealer or the Canon help line.

IMPORTANT

Do not disassemble or repair the machine yourself

If you disassemble or repair the machine yourself, it may not be covered by warranty.

■When Contacting Canon

When contacting us, have the following information ready.

- Product name (LBP6030w / LBP6030B / LBP6030)
- Dealer where you purchased the machine
- Details about your problem (such as what you did, what happened as a result, and any messages that were displayed)
- Serial number (10 alphanumeric characters long, found on the label on the back side of the machine)



Serial No. X00000000	Canor	1	
	Serial No.	XXXXXX00000	

Maintenance

This chapter describes upkeep of the machine, including how to clean the machine and print setting lists.

Basic Maintenance OCleaning the Machine



- The machine becomes dirty OExterior
- Smudge marks appear on printouts SFixing Unit

Replacing Toner Cartridges OReplacing Toner Cartridges



- If you want to use all of the toner OUsing Up All of the Toner
- How to replace toner cartridges OHOW to Replace Toner Cartridges

Printing Setting Lists



If you want to print a list of machine settings **Oprinting Setting Lists**

Checking the Total Pages Printed by the Machine

If you want to check the total number of pages printed by the machine OViewing the Page Counter Value

Initializing Settings LBP6030w

If you want to restore settings to the factory defaults **[] Initializing Settings**

Relocating the Machine




If you want to relocating the machine for maintenance or an office move **Pelocating the Machine**

Cleaning the Machine

Clean the machine regularly to prevent deterioration in printing quality and to ensure safe and trouble-free operation. Carefully read the safety instructions before you start cleaning. **OMaintenance and Inspections**

Where to Clean



Exterior

Regularly wipe the exterior of the machine to keep it in good condition. Wipe the ventilation slots regularly to keep it free of dust.

1 Turn OFF the machine, and unplug the power plug from the AC power outlet.

. When you turn OFF the machine, data that is waiting to be printed is deleted.

2 Wipe the exterior of the machine and the ventilation slots.

- Use a soft, well-wrung-out cloth dampened with water or a mild detergent diluted with water.
- For the location of the ventilation slots, see OBack Side.



- **3** Wait for the exterior of the machine to dry completely.
- 4 Plug the power cord back into the AC power outlet.

Fixing Unit

Dirt may adhere to the fixing unit inside the machine and cause smudges and black streaks to appear on printouts. If this occurs, proceed as follows to clean the fixing unit. Note that you cannot clean the fixing when the machine has documents waiting to be printed. To clean the fixing unit, you need normal A4 size paper. Before starting, load A4 size paper in the multi-purpose tray. **C**Loading Paper in the Multi-Purpose Tray



2 Select [Options] [Utility] [Cleaning].

-	lptions Help	-		
	Preferences (Users)	- 1		
_	Preferences (Administrators)	- t		
	Counter Information			
	Wireless LAN Status	L		
10	Utility	-	Cleaning	^
2	Device Settings		Configuration Page Print	
	Management Settings	•	Network Status Print	*
	Remote UE	T	Troubleshooting Det	als.
	Refresh			

3 Click [OK].



The paper is fed slowly into the machine, and cleaning starts. The cleaning is done when the paper is completely ejected.

Cleaning cannot be cancelled once it starts. Wait until it finishes (approx. 140 seconds).


NOTE

Cleaning from the Remote UI

You can also clean the fixing unit from the [Utility Menu] page of the Remote UI. OCleaning

Replacing Toner Cartridges

No warning message appears, even when toner begins to run low. Use the printout symptoms described below as a guide to when to replace the toner cartridge. **OHOW to Replace Toner Cartridges**



NOTE

When, of the above symptoms, one of "White streaks appear," "Faded," and "Uneven density" appears, you may be able to continue printing for a while longer by taking the steps in **Ousing Up All of the Toner**.

TIPS

You can specify that a message like the one shown below be displayed when print quality cannot be guaranteed because the toner cartridge has reached its lifetime or for some other reason. This allows you to avoid the waste of poor-quality printouts, because you are notified in advance when the time comes to replace the toner cartridge.

Canon LBP6030/6040/6018L						
	-	- • •				
Options Help						
(3 69 🚳						
Replacing this toner car	nt gualdy because the tones cartidge is reaching the gualdy because the tones cartidge is recommended wal for more relarization on how to replace a tones to more information on how to replace a tones transition or to	cattidge. +				
Pilet Job Information						
Cannot guarantee print qu lifetime, etc. Replacing this toner cartr See the instruction manu-	idge with a new toner ca	rtridge is recommend	ed.			
		_				
1 Sele	ect the machine	by clicking 🚑	in the syster	n tray.		
				-		
		Canon LBP00				
		Canon EBroo	30/6040/6013L			
			30/6040/9013L			
	Customize		Customize			
	Custornize		Customies	70.00		
				00:00		
	Custornize		Customies	C0:00 01/01/2013		
	Custornize		Customies	C0000 01/01/2013		
2 Sele	Cuttomize		Cutomiz.	01/01/2015	v Settings	1.
	Cutomize. 		Cutomiz	01/01/2015	y Settings].
E Canor	Cuterria.		Cutomiz.	01/01/2015	y Settings].
분) Canor Job Op	Cutamize.		Cutomiz	01/01/2015	y Settings].
E Canor	Cutomia. 2010 0000000000000000000000000000000000		Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutarria.		Cutomiz	01/01/2015	y Settings].
분실 Canor Job Op	Cuterrize.		Cutomiz	01/01/2015	y Settings].
분실 Canor Job Op	Cuterria. © all (*) 9070 01.00.2013 Cott [Options] > [] Prifernes (Men) Prifernes (Men) Cuter Infermation		Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cuterrize.	Device Setting	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutatrize.	Device Setting	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutatrize.	Device Setting	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutarria.	Device Setting	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutatrize.	Device Setting	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cutarria.	Settings to Disable Wi-Fi Key Siege Settings. Autro Shortdoom Settings.	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cuterrise.	Settings to Disable Wi-Fi Key Siege Settings. Autro Shortdoom Settings.	Cutomiz	01/01/2015	y Settings].
분) Canor Job Op	Cuterrize.	Settings to Disable Wi-Fi Key Siege Settings. Autro Shortdoom Settings.	Cutomiz	01/01/2015	y Settings].



IMPORTANT

- You can continue printing when this message is displayed, but the print quality may deteriorate.
- Even if this message is not displayed, use the symptoms listed at the top of this page as a guide to replacing toner cartridges. Replace the toner cartridge when a symptom appears.

LINKS


Consumables


Using Up All of the Toner

Printout symptoms like the following appear when toner begins to run low.



When symptoms like these appear, take the following steps. They will allow you to use up all of the toner in the toner cartridge. You will be able to continue printing for a while longer, until the toner runs out completely. If the symptoms do not improve after you take the following steps, replace the toner cartridge (**Chow to Replace Toner Cartridges**). Before starting, read the safety instructions in **Chaintenance and Inspections** and **Consumables**.






2 Remove the toner cartridge.




3 Shake the toner cartridge 5 or 6 times as shown below to evenly distribute the toner inside the cartridge.



4 Replace the toner cartridge.

Align with the toner cartridge guide (
(), and push firmly all the way in.






How to Replace Toner Cartridges


Before replacing a toner cartridge, read the precautions in **OMaintenance and Inspections** and **OConsumables**.



2 Remove the toner cartridge.



3 Remove the new toner cartridge from the protective bag.




4 Shake the toner cartridge 5 or 6 times as shown below to evenly distribute the toner inside the cartridge, and then place it on a flat surface.



5 Pull the sealing tape straight out.


• The full length of the sealing tape is approximately 50 cm.



IMPORTANT:

When pulling out the sealing tape


- If any sealing tape remains inside the toner cartridge, print quality may deteriorate.
- Do not pull the sealing tape at an angle. If the sealing tape breaks, you may not be able to pull it out completely.



• If the sealing tape becomes stuck when pulling it out, keep pulling until it is completely removed.

6 Replace the toner cartridge.

Align with the toner cartridge guide (6), and push firmly all the way in.



7 Close the top cover.

Printing Setting Lists

You can print setting lists from the Printer Status Window. This is convenient when you want to print a list of network settings or a list of power saving and other configuration settings for the machine. Setting lists are formatted to print on A4 size paper. Before starting, load A4 size paper in the multi-purpose tray. **C**Loading Paper in the Multi-Purpose Tray



2 Select [Options] > [Utility] > [Configuration Page Print] or [Network Status Print].

0 0	lptions Help			
	Preferences (Users) Preferences (Administrators)	ł		
1	Counter Information Wireless LAN Status			
10	Utility	- 1 C	Cleaning.	^
2	Device Settings	-	Configuration Page Print	
	Management Settings	-	Network Status Print	
	Remote UE	Ĩ	Troubleshooting De	tals.
	Refresh			

[Configuration Page Print]


Prints a list of the settings under [Options] > [Device Settings] together with machine version information.

[Network Status Print] (LBP6030w)


Prints a list of the network settings of the machine.



Output example: [Configuration Page Print]



Output example: [Network Status Print]



NOTE

You can also use the machine's \downarrow (Paper) key to print and view a list of the machine's IPv4 settings, MAC address, wireless LAN settings, and version information. **Viewing Network Settings**

Viewing the Page Counter Value

You can check the total number of pages that the machine has printed by viewing the page counter in the Printer Status Window.

1 Select the machine by clicking **W** in the system tray.



2 Select [Options] ▶ [Counter Information].

b 🖸	ptions Help			
1	Preferences (Users)			
_	Preferences (Administrators)			
1	Counter Information			
1	Windless LAN Status			
1	Utility	•		
2	Device Settings	•		
٩.	Management Settings	· · ·		*
	Remote UE		Trou	bleshooting Details .
	Refresh			

The total number of printed pages is displayed.

Counter Information	
Counter Total Printed Pages:	5
	ОК Нер

Initializing Settings LBP6030w

You can restore the machine's settings to the factory default settings.


Initializing Preferences Settings
 Initializing System Management Settings
 Initializing Key and Certificate Settings

Initializing Preferences Settings LBP6030w


You can initialize the settings of the Remote UI [Preferences] menu (**Setting Menu List**) to return them to the factory default settings.

Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].



3 Click [Initialize Setting Information] ▶ [Initialize Menu].



4 Select the settings to initialize, and then click [Initialize].



[Menu to Initialize]

Select the settings to initialize from the drop-down list. Select [Initialize All] to initialize both [Display Settings] and [Timer Settings].



Initializing System Management Settings LBP6030w

You can initialize the settings in the Remote UI [System Management Settings] menu (**Setting Menu List**) to return them to the factory default settings.

NOTE


To initialize [Key and Certificate Settings] and [CA Certificate Settings] in [Security Settings], see **Cinitializing Key and Certificate Settings**.

1 Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].

🗧 💽 🔞 http://182.068.0.215/portel,	top Hamil	P-10 x 000
factory.	Device Name: LIPP0030w/913w Product Name: LBP0030w/913w Location:	Login User: System Manager Log Out
😪 Remote UI: Portal		Mail to System Manager
	Last Updated 01101 2013 03:34:20 PM	Status Monitor/Cancel
Device Basic Information		
Device Status		Settings/Registration
Printer: Roady to print.		(*)
Error Information		
No erroru.		
Support Link		
Support Link:		
		Copyright CANCIN INC. 2013

3 Click [Initialize Setting Information] > [Initialize System Management Settings].



4 Select the settings to initialize, and then click [Initialize].



[Setting Information to Initialize]

Select the settings to initialize from the drop-down list. Select [Initialize All] to initialize all of the settings in [System Manager Information], [Device Information], [Security Settings], and [Network Settings] at once.




6 If you initialized the network settings, restart the machine.

• Turn OFF the machine, wait for at least 10 seconds, and turn it back ON.

Initializing by Using the Wi-Fi Key

You can use the machine's ((1) (Wi-Fi) key to initialize the machine's system management settings. If you turn OFF the machine, and then turn ON the machine while pressing the ((1) (Wi-Fi) key, all of the settings in the [System Management Settings] menu (Setting Menu List) of the Remote UI are initialized at once. However, the [System Manager Name], [Device Name], and [Location] settings of [System Management] are not initialized.



Initializing Key and Certificate Settings LBP6030w

You can restore the settings of key pairs (Key and certificate settings) and CA certificates to the factory default settings. Note that any key pairs that you have registered in the machine and any CA certificates (except the preinstalled CA certificates) will be deleted by the initialization.

NOTE


If you perform this initialization, SSL encrypted communication requiring a key pair will not be possible. To use SSL encrypted communication, set another key pair and enable the function again.

Start the Remote UI and log on in System Manager Mode. OStarting the Remote UI

2 Click [Settings/Registration].


lamang.	LIPP000w5919w LBP5030w5919w	Login User: System Manager Log 0
Remote UI: Portal		Mail to System Manage
	Last Updated 01/01 2013 03:34:20 PM	Status Monitos/Cancel
Jevice Basic Information		
Device Status		SettinguRegistration
Printet: Roady to print.		477
Error Information		
No errore.		
Sepport Link		
Support Link:		

3 [Initialize Setting Information] > [Initialize Key and Certificate].



4 Click [Initialize].








Configuring Settings for Key Pairs and Digital Certificates

Relocating the Machine


The machine is heavy. To avoid injury, be sure to follow the procedure below when moving the machine. Also be sure to read the safety instructions before you begin. **OImportant Safety Instructions**



3 If you will be transporting the machine across a long distance, remove the toner cartridge. O How to Replace Toner Cartridges

4 Close the multi-purpose tray and output tray, and carry the machine to its new location.

To carry the machine, grasp it on both sides with the front side facing you.



5 Carefully place the machine at its new location.

For the procedure to follow after moving the machine, see the "Getting Started." OManuals Included with the Machine

Appendix

This chapter contains technical specifications of this machine, instructions on how to use the e-Manual, disclaimers, copyright information, and other information that you may need. Refer to it as required.

Feature Highlights

Give the features that are described in this section a try. The features are grouped under four headings: "Going Green and Saving Money," "Improving Efficiency," and "So Much More."

Going Green and Saving Money

Easy on the environment, easy on your wallet

There are lots of ways to cut back on paper, toner, power, and expenses.





When there are many pages in a document, the printout can be inconveniently bulky – hard to carry around and store, and also hard to read. But there is a solution. Print multiple pages onto one sheet! This allows you to save paper and make your documents slimmer and easier to handle.



For more information about this function, see **Printing Multiple Pages Onto One Sheet**.



You can save power by setting the machine to enter sleep mode automatically whenever it has not been used for a while. You don't need to turn OFF the power each time, but you can still have the machine minimize its power consumption. The auto shutdown function can boost the savings, by automatically turning OFF the machine if it remains idle for a longer time. These convenient functions work in the background to save power and money every day.



To save power by putting the machine into sleep mode: **OSetting Sleep Mode**

To configure the machine to be automatically turned OFF: **Setting Auto Shutdown**



To economize on toner, you can use draft mode for drafts and test printouts. Or you can switch between modes according to purpose, using normal mode for beautiful photos and draft mode for company documents that do not require presentation quality.



For more information about this function, see **Saving Toner**.

Improving Efficiency

01



The Printer Status Window and Remote UI^{*} allow you to manage the machine remotely from the computer at your desk. You can monitor the state of the machine from your computer, and also check error information. Whenever a printing error occurs, the Printer Status Window appears automatically to notify you with easy to understand messages and animations. Save time and trouble by eliminating trips between your desk and the machine. The Remote UI makes it simple to configure the machine, including the many network setting items.

Remote Management with Printer Status Window and Remote UI

 * The Remote UI is available on the LBP6030w only.

Canon LBP6030/6040/60	18L		G 😽
Job Options Help			
🔲 🗱 🕪 😫			
	Paper Jam in: Renove the janued pap Click (Troubleshooting De		,
	Print Job Information		Troubleshooting Details .
	Document Name:	Document 1.rf	
	User Name:	User01	
	Printed Pages:	0	
			2

For more information about the Printer Status Window, see **Printer Status Window**.

For more information about the Remote UI, see **OUsing the Remote UI**.



Everyone in the office uses the printer. If you register the most popular settings as the default settings, you can use them right away. You can also register frequently used combinations of print settings as "profiles." Then you can call up your favorite settings in a single operation, by selecting a profile instead of selecting each setting every time you print.



To change default print settings: **Changing Default Settings**

To register combinations of frequently used print settings as "profiles": **ORegistering Combinations of Frequently Used Print Settings**



Save Time with Shortcuts


When you have a number of documents to print, it would be convenient to print them all with one operation. Canon PageComposer allows you to combine multiple documents and print them all at once. It is an easy way to save time and work more efficiently.

🚰 Canon PageComposer - C		40/6018L - User01	
File Edit Moveto Help		12 IL	
Document Name	Pages	Layout Informati. Comments	
Document 1.tf	1	1 on 1	
Document 2.rtf	1	1 on 1	
Document 3.tf	1	1 on 1	
For Help, press F1.			

For more information about this function, see **OCombining and Printing Multiple Documents**.

C

So Much More



01

Keep Your Printouts Private

For personal information and sensitive documents that you want to keep private, you can print watermarks such as "CONFIDENTIAL" or "TOP SECRET." In addition to these standard watermarks, you can also design your own watermarks.



For more information about this function, see **OPrinting Watermarks**.




No cables, easy installation, simple maintenance. If you've got a WPS wireless LAN router, bypass the settings process altogether and be ready to go before you know it. Enjoy the kind of clutter-free and easy to use document system that you can only get from wireless. Compatible with IEEE 802.11b/g/n for stress-free wireless, and also supports WEP and WPA/WPA2-PSK (TKIP/AES-CCMP) for tighter security.



For more information about this function, see **OConnecting to a Wireless LAN**.



Blow up a regular one-sheet printout and make an exceptionally large poster. A large poster will be printed out on nine sheets. Put them together in a 3x3 grid, and voila!



For more information about this function, see **OPrinting Posters**.



Automatically Collate Meeting Handouts

When you print multiple copies of a multi-page document, you can use the collate function to print one copy after another with all of the pages in the correct order. This is convenient when preparing handouts for meetings or presentations.



For more information about this function, see **O**Collating Printouts by Page.

Specifications

Due to continuing product enhancements, the specifications of this machine are subject to change without notice.

OMachine Specifications Wireless LAN Specifications OPaper

Machine Specifications

Hardware SpecificationsSoftware Specifications

Hardware Specifications

_		
Туре	Desktop page printer	
Printing System	Semiconductor laser + dry-type electrophotographic system	
Toner Fixing System	On-demand fixing system	
Print Speed*1 (Plain paper (60 to 89 g/m ²), A4 continuous printing)	18 pages/minute	
Warm-Up Time*2 (from power ON until machine enters standby)	10 seconds or less	
Recovery Time*3 (recovery from sleep mode to standby)	1 second or less	
First Print Time ^{*3} (A4 printing)	Approx. 7.8 seconds	
Acceptable Paper Stock	© Paper	
Paper Capacity (Multi-purpose tray)	Approx. 150 sheets	
Paper Output	Face down	
Output Capacity*4 (Output tray)	Approx. 100 sheets	
Noise (measured in accordance with ISO 7779, declared noise emission in accordance with ISO 9296)	 LwAd (declared A-weighted sound power level (1 B = 10 dB)) During standby: Inaudible*5 During printing: 6.53 B or less LpAm (declared A-weighted sound pressure level (bystander position)) During standby: Inaudible*5 During printing: 49.3 dB 	
Environmental Conditions (machine only)	Operating Environment Temperature: 10 to 30 °C Humidity: 20 to 80% RH (no condensation) 	
Host Interface	LBP6030w USB interface: Hi-Speed USB/USB Network interface: IEEE 802.11b/g/n LBP6030B / LBP6030 USB interface: Hi-Speed USB/USB	
	LBP6030w	
	•	

User Interface	LED indicators: 3 • Operation keys: 2 LBP6030B / LBP6030 • LED indicators: 2 • Operation keys: 1
Power	220 to 240 V (± 10 %), 50/60 Hz (± 2 Hz)
Power Consumption*6 (20 °C)	 Maximum: 870 W or less During operation: Approx. 330 W During standby: 1.8 W or less (USB connection) 2.8 W or less (Wireless LAN connection) (LBP6030w only) During sleep mode: 8 W or less (USB connection) 6 W or less (Wireless LAN connection) (LBP6030w only) When the power switch is turned OFF: 0.5 W or less
Consumables	© Consumables
Weight	Machine and accessories • Machine (excluding toner cartridge): Approx. 5.0 kg • Toner cartridge: Approx. 0.5 kg Consumables • Toner cartridge (Canon Cartridge 725): Approx. 0.5 kg

*1 Print speed may be slower depending on the settings for output adjustment mode, paper size and type, paper orientation, and number of copies printed.

 st_2 May vary depending on conditions of use (installation environment, etc.).

 *3 May vary depending on the output environment.

 $^{\ast 4}$ May vary depending on the installation environment and type of paper used.

*5 Indicates that the sound pressure level of each bystander position is below the ISO 7779 absolute criteria for the background noise level.

*6 Even if the machine is turned OFF, a slight amount of power is still consumed while the power plug is plugged into the AC power outlet. To stop power consumption completely, unplug the power plug from the AC power outlet.

Software Specifications

Printing Software	UFR II
Printable Area	OPrintable Range

Wireless LAN Specifications LBP6030w

Standards	IEEE 802.11b/g/n
Transmission Scheme	DS-SS system, OFDM system
Frequency Range	2,412 to 2,472 MHz
Data Transmission Rate	IEEE 802.11b 1/2/5.5/11 Mbps IEEE 802.11g 6/9/12/18/24/36/48/54 Mbps IEEE 802.11n • SGI Invalidated 20 MHz: 6.5/13/19.5/26/39/52/58.5/65 Mbps • SGI Validated 20 MHz: 7.2/14.4/21.7/28.9/43.3/57.8/72.2 Mbps • SGI Invalidated 40 MHz: 13.5/27/40.5/81/108/121.5/135 Mbps • SGI Validated 40 MHz: 13.5/27/40.5/81/108/121.5/135 Mbps • SGI Validated 40 MHz: 13.5/27/40.5/81/108/121.5/135 Mbps
Communication Mode	Infrastructure mode
Security	WEP, WPA-PSK (TKIP/AES-CCMP), WPA2-PSK (TKIP/AES-CCMP)
Connection Method	WPS (Wi-Fi Protected Setup), Manual setup

Paper

■Supported Paper Sizes

Paper sizes that can be loaded in the multi-purpose tray are listed below.

A4 (210.0 mm x 297.0 mm) **B5** (182.0 mm x 257.0 mm) A5 (148.5 mm x 210.0 mm) Legal (215.9 mm x 355.6 mm) Letter (215.9 mm x 279.4 mm) **Executive** (184.2 mm x 266.7 mm) Oficio (216.0 mm x 317.0 mm) Brazil Oficio (216.0 mm x 355.0 mm) Mexico Oficio (216.0 mm x 341.0 mm) Foolscap (216.0 mm x 330.0 mm) **16K** (195.0 mm x 270.0 mm) Envelope Monarch (98.4 mm x 190.5 mm) Envelope No. 10 (COM10) (104.7 mm x 241.3 mm) Envelope DL (110.0 mm x 220.0 mm) Envelope C5 (162.0 mm x 229.0 mm) Custom paper size (Width 76.2 to 216.0 mm x Length 188.0 to 356.0 mm)

Paper Tray Capacity by Paper Type

Chlorine-free paper can be used with this machine.

Paper Type		Capacity (Multi-Purpose Tray)	
Plain paper ^{*1}	60 to 80 g/m ²	Approx. 150 sheets	
	81 to 89 g/m ²	Approx. 120 sheets	
Hoover popor	90 to 105 g/m²	Approx. 100 sheets	
Heavy paper	106 to 163 g/m²	Approx. 60 sheets	
Transparency*2 *3		Approx. 100 sheets	
Labels *3		Approx. 50 sheets	
Envelope		Approx. 10 sheets	

*1 Recycled paper can be used.

*2 Use laser printer transparencies.


*3 Use A4 or Letter size only.

■ Machine Settings for Paper Types

CLoading Paper

Printable Range

The printable range is indicated in gray. Envelopes require a 10 mm margin on the top, bottom, left, and right.




Consumables

The following is a guide to the estimated replacement time for the consumables used in this machine. Purchase consumables at your local authorized Canon dealer. Observe safety and health precautions when storing and handling consumables (**Consumables**).

NOTE

Depending on the installation environment, printing paper size, or document type, you may need to replace consumables before the end of the estimated lifetime.

Toner Cartridges



Supplied Toner Cartridges

The average yield $\!\!\!^*$ of the toner cartridge that comes with the machine is 700 sheets.

* The average yield is based on "ISO/IEC 19752" (the global standard related to "Method for the determination of toner cartridge yield for monochromatic electrophotographic printers and multi-function devices that contain printer components" issued by ISO [International Organization for Standardization]) when printing A4 size paper with the default print density setting.

Replacement Toner Cartridges

For optimum print quality, using Canon genuine toner cartridges is recommended.

Canon Genuine Toner Cartridge	Average yield of toner cartridge*	
Canon Cartridge 725	1,600 sheets	

NOTE

When replacing toner cartridges OHow to Replace Toner Cartridges

LINKS

CReplacing Toner Cartridges

Manuals Included with the Machine

The manuals listed below are included with the machine. Refer to them as necessary.

Getting Started		Read this manual first. It contains easy to understand explanations of everything you need to do to set up the machine, from removing the packing materials to configuring the settings. It also explains basic maintenance.
	PDF Getting Started	This manual has descriptions in the following languages. Bulgarian, Croatian, Czech, Estonian, Greek, Hungarian, Latvian, Lithuanian, Persian, Portuguese, Romanian, Slovakian, Slovenian, Ukrainian
e-Manual (This Manual)	emanual	This manual describes all the functions of the machine. It is designed for viewing in a Web browser. You can browse information by category or enter a keyword to search for pages on a specific topic. OUsing the e-Manual
Printer Driver Installation Guide	PrinterDriver	This manual explains how to install the printer drivers included on the User Software CD-ROM/DVD-ROM.

Using the e-Manual

The e-Manual is a manual that can be viewed on your computer. It describes all of the functions of the machine. You can search for information about what you want to do, or enter a keyword to quickly find the page you are looking for. You can use the e-Manual by installing it on your computer, or start the e-Manual directly from the CD-ROM/DVD-ROM. **©Installing the e-Manual**

How to Find the Topic You Are Looking For

You can find the page you are looking for using the following three methods.

Search the contents

You can find the page you are looking for by selecting a topic from the [Contents] tab on the left side of the screen, or by selecting a chapter icon from the icons next to the topics.

C Top Page

C Topic Page

Search by keyword

You can search by entering keywords, such as "envelope" or "toner cartridge." Pages containing the keywords are displayed. You can also enter phrases such as "load paper." The search will find topics containing all of the words in the phrase (AND search).

Search Tab

Search the site map

Click [Site Map] on the top part of the screen to display a list of all the e-Manual topics. From there you can find the topic you are looking for.

Site Map

NOTE

System Requirements

To use the e-Manual, one of the following Web browsers is required. The content of the e-Manual may not display correctly if a browser not listed below is used.

Windows: Internet Explorer 8.0/9.0/10.0/11.0, Firefox 24.x ESR/26.0

Mac OS: Safari 7.0, Firefox 24.x ESR/26.0

Installing the e-Manual

Install the e-Manual on your computer by using the CD-ROM/DVD-ROM that comes with the machine.

1 Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.

2 Click [Custom Installation].

Canon	UFRII LT CD-ROM/DVD-ROM Setup
	Easy Installation
	Installs the standard programs and the menuals. Custom Installation Installs the programs and menuals that you select.
111-	Start Software Programs
11	Manuals Displays manuals.
All a start	
100	Ext

NOTE:

- If the above screen does not appear ODISPLAYING the [CD-ROM/DVD-ROM Setup] Screen
- If [AutoPlay] is displayed, click [Run MInst.exe].

Clear the [Printer Driver] check box, and click [Install].

ustom Installation				
te selected programs shown below fou can configure the network setting	rill be installed. Click [install], a s for your device before installi	and then follow the i ng the printer driver	instructions displayed on the screen	
Printer Driver This program is required t	or printing using your device.			Readme B0 MB
American American	your device. If you install the n	nanuals on your co	mputer, you can display them	11 ME
	C : Free Disk Space	54151 MB	Space Required to Install	11 M
Back			Install Can	cel

4 Read the License Agreement and click [Yes] to agree.

License Agreement
Please read the following license agreement completely and carefully before installing the software programs.
(September 1995). Consistent with 48 C.F.R. 12.312 and 48 C.F.R. 227.7302-1 through 227.7202-4 (June 1995), all U.S. Government End Users shall acquire the Software with only those rights set forth herein. Manufacture is Canon Inc.730-2, Shirmonamics JChome, Oldha-J., Kiopi 146-3931, Japan.
10. SEVERABILITY In the event that any section hereof is declared or found to be llegal by any court or tribunal of competent jurisdiction, such section shall be null and void with respect to the jurisdiction of that court or tribunal and all the remaining provisions hereof shall remain in full force and effect.
11. ACKNOWLEDGENENT BY CLOWNS THE BUTTON INDUCTING YOUR ACCEPTANCE AS STATED BELOW OR USING THE SOFTWARE, YOU ACKNOWLEDGE THAT YOU AND READ THS ADREEMENT, UNDERSTOOD IT, AND ADREE TO BE DOUND BY ITS TERMS AND COMDITIONS. YOU ALSO ADREE THAT THIS ADREEMENT IS THE CONSELFE AND EXCLUSIVE STATEMENT OF ADREEMENT BETWEEN YOU AND CANON CONCERNING THE SUBJECT NATTHER ORDER STATE AND EXCLUSIVE STATEMENT OF ADREEMENT BETWEEN YOU AND CANON WITTEN, AND ANY OTHER COMMUNICATIONS BETWEEN YOU AND CANON RELATING TO THE SUBJECT MATTER HEREOF, MID ANDROMENT TO THIS ADREEMENT BALL BETWEEN WOL AND CANON RELATING TO THE SUBJECT MATTER HEREOF. NO ADMENDING THE ADMENDATIONS BETWEEN WOL AND CANON RELATING TO THE SUBJECT MATTER HEREOF. OR CONCUMPTIONE OF CONCUMPTIONE OF CONCUMPTIONE OF CONCUMPTIONE OF CONCUMPTIONES.
Should you have any questions concerning this Agreement, or if you dealers to contact Canon for any reason, please write to Canon's sales subsidiary or distributorification, serving the country where you obtained the Products.
To accept the terms of this agreement, click [Vas]. To decline the terms of this agreement, click [Vas]. To use this program, the terms of this agreement must be accepted.
Back Yes No

Click [Install].

- 5
- If you want to change the installation destination, click [Browse] and select your desired location.

Manual Installer		×
Select the folder where the manual will be installed.		
Destination Folder (Browne
	Install	Cancel

The installation begins.



7 Click [Next] ▶ [Exit].



■Viewing the e-Manual

Double-click the shortcut icon of the e-Manual on the desktop.



If a security warning message appears

Click [Allow blocked content].

Internet Explorer restricted this webpage from running scripts or ActiveX controls. Allow blocked content ×

Viewing the e-Manual Directly from the CD-ROM/DVD-ROM

- **1** Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.
 - If the [CD-ROM/DVD-ROM Setup] screen does not appear ODisplaying the [CD-ROM/DVD-ROM Setup]
 Screen
 - If [AutoPlay] is displayed, click [Run MInst.exe].

2 Click [Manuals].

3 Click [e-Manual].

Uninstalling the e-Manual

You can remove the e-Manual from the computer to restore the computer to the same state it was in before the e-Manual was installed.

1 Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.

2 Click [Start Software Programs].

Canon	UFRII LT CD-ROM/DVD-ROM Setup
	Easy Installation
	Installs the standard programs and the manuals. Custom Installation Installs the programs and manuals that you select.
111	Starts programs due vous and the second starts of the second starts of the second starts of the second starts of the second starts and s
11	Manuats Displays manuals
A. The	
2. CAT 100	Ext

NOTE:

- If the above screen does not appear ODISPLAYING the [CD-ROM/DVD-ROM Setup] Screen
- If [AutoPlay] is displayed, click [Run MInst.exe].

3 Click [Start] for [Manual Uninstaller].

Start Software Programs	
Starts programs from the GD/D//D. Click [Start] to the right of the program you want to start.	
IFILEP Network Setup Tool Configures printer settings in order to connect to the network.	Readme Start
Manual Uninstaller The manuals installed by this setup will be uninstalled.	Start
Back	Gancel

4 Click [Next].

Uninstall Manual The nanuals installed		
The manuals installed	by this setup will be u	ininstalled.
P111.04.04	And an 2 19	

The uninstall begins.

5	Click [Exit].	
	💝 Manual Installer 🔤	
	Uninstal Manuals Uninstalation of the manuals is complete.	
	Exit	J

Downloaded from ManualsPrinter.com Manuals






Screen Layout of the e-Manual

The e-Manual is divided into different screens, and the content of each screen varies.

Top Page

This page appears when the e-Manual is started.



👩 Canon

Click to return to the top page from any other page.

[Contents] tab/[Search] tab

Click to toggle the display between the [Contents] tab and [Search] tab.

Contents

Displays the titles of chapters (). Place the mouse pointer over one of the titles to display the topics in that chapter on the right. Click a topic to display its page.



📵 [Тор]

Click to return to the top page from any other page.

[Site Map]

Click to display the titles of all e-Manual topics.

🚹 [Help]

Click to display information on how to view the e-Manual, how to perform a search, and other information.

(9 [Print]

Click to print the currently displayed topic page.

🚯 Feature Highlights

This page provides a variety of practical examples of ways to use the machine. Click 1/2/3 to toggle the display of practical examples by category, or click the sliding display for more information about each category. The sliding display can be stopped by moving the pointer onto it. **C**Feature Highlights

[Quick Help]/[Troubleshooting]/[Maintenance]

Click to view how to solve problems or maintain the machine.

[For Mac OS Users]

Click to view precautions when using Mac OS.

() [Notice]

Click to view important information you should know when using the machine.

[Office Locations]

Click to display contact information for any inquiries about the machine.

Feature Highlights

This page provides a variety of practical examples of ways to use the machine.

There are lots of ways to cut back on paper, tonk preserved 01 Image: A start of the paper of the p		Easy on the environment, easy on your wallet	
Sleep Mode Successful to enter sleep mode automatically whenever it has not been used for a while. You don't need to turn OFF the power sent time, but you can still have the machine inimize its power consumption. The auto shutdown function can boost the savings, by automatically turing OFF the machine if it remains life for a longer time. These convenient functions work			
You can save power by setting the machine to enter sleep mode automatically whenever it has not been used for a while. You don't need to turn OFF the power each time, but you can still have the machine minimize its power consumption. The auto shutdown function can boost the savings, by automatically turning OFF the machine it remains ide for a longer time. These convenient functions work	01	Print Multiple Pages on a Single Sheet	
whenever it has not been used for a while, You don't need to turn OFF the power each time, but you can still have the machine minimize its power consumption. The auto shutdown function can boost the savings, by automatically turning OFF the machine if it remains idle for a longer time. These convenient functions work	02	Sleep Mode	
		ou can save power by setting the machine to enter sleep mode automatically	

0 🔾 🔿

Click to expand the window to show the information. Click again to collapse the window.

60

Click to display the corresponding topic page.

Topic Page

Topic pages contain information about how to configure and use the machine.

Canon	Top Site Map Help Print 📥	
Contents Search Using the Remote UI Contents Using the Remote UI Contents Using the Remote UI Exarting the Remote UI Exarting the Remote UI Remote UI Screens Nanosging Occuments and Checking the Machine Status Contents Status Contents Status Contents Status Contents Status Contents Status Contents Status Contents Status	Top > Using the Remote UI > Changing Machine Settings > Setting Menu List Setting Menu List Setting Menu List This section describes the menu items that can be set using the Remote UI. Default settings are marked with a dagger ('). Infeferences] Menu Original Settings Timer Settings	-() -()
	[Adjustment/Maintenance] Menu OUtility Menu [System Management Settings] Menu O System Management O Security Settings O Network Settings O Initialize Setting Information	
e	Display Settings Select the display language used for the Remote UI screens. Remote UI =	- k
(Print SI)	Notice Office Locations	

Chapter icons and topic titles are displayed in this tab.

🕒 🔍 🗩

The [Contents] tab can be widened and narrowed.

[Expand All]/[Collapse All]

Click [Expand All] to display all of the subsections of all topics. Click [Collapse All] to close all of the subsections of all the topics.

6 Chapter icons

Click a chapter icon to navigate to the top of the corresponding chapter.

Copics

Displays the topics of the selected chapter. If "+" is displayed on a topic, clicking it displays the subsections of that topic. Click "-" to close an expanded topic.

[Print all]

All pages of the selected chapter are opened in a separate window. You can print them as necessary.

(9) Navigation

This shows which chapter topic you are currently viewing.

(h 🖪

Click to return to the page top.

() < / >

Click to display the previous or next topic.

00


Click to jump to the corresponding page. To return to the previous page, click the "Back" button on your Web browser.

🚷 🔼

Click to display hidden detailed descriptions. Click again to close the detailed descriptions.

Search Tab

This tab contains a text box to perform a search and find the page you are looking for.



[Enter keyword(s) here]

Enter one or more keywords and click **Q** to display the search results in a results list. You can enter a phrase to find pages that contain all of the words in the phrase. To find the exact phrase, enclose it in double quotation marks.

[Search options]

Click to specify search conditions such as the scope of the search and case sensitivity.

G Search scope selector

You can use this to select the individual chapters to search. This allows you to search more efficiently, when you can predict the chapters containing the topic that you are looking for.

6 Search options selector

Select the check box to make your search case-sensitive.

[Search with these conditions]


Cand cospecify the conditions. After setting them, press this to perform the search and display the results in the [Result] list.

🗿 Result list

This displays pages that contain the specified keywords. From the results, locate the page you are looking for and click the topic title of the page. If the results cannot be displayed on one page, click || or a page number to display the results on the corresponding page.

Site Map

This page displays the titles of all topics in the e-Manual.



6 Chapter icons

Click to jump to the table of contents of the selected chapter.

() Topic titles

Displays titles and topics. Click a title to jump to the corresponding topic page.

6

Click to return to the page top.

📵 🔺 / 🔻

Click to go to the previous or next chapter.

Viewing the e-Manual

Marks

Cautions regarding safety, restrictions and cautions regarding the handling of the machine, useful tips, and other information are indicated using the marks below.

	Indicates a warning concerning operations that may lead to death or injury to persons if not performed correctly. To use the machine safely, always pay attention to these warnings.
	Indicates a caution concerning operations that may lead to injury to persons if not performed correctly. To use the machine safely, always pay attention to these cautions.
\bigcirc	Indicates an operation that must not be performed. Read these items carefully, and make sure not to perform the described operations.
IMPORTANT	Indicates operational requirements and restrictions. Be sure to read these items carefully to operate the machine correctly and avoid damage to the machine or property.
NOTE	Indicates a clarification of an operation, or contains additional explanations for a procedure.
TIPS	Indicates useful functions or tips for using the machine.

Keys

Keys on the machine and buttons on the computer display are indicated with the following notations:

Туре	Example notation in the e-Manual
Machine key	🛔 (Paper) key
Buttons and other text interfaces on the computer display	[Preferences]

Computer screens

Unless otherwise noted, displays used in the e-Manual are those for the LBP6030w. Depending on the operating system you are using, the appearance of the displays in this manual may differ slightly from the displays that you see. Also, the appearance of printer drivers and software may differ depending on their version.

Illustrations

- Unless otherwise noted, illustrations used in the e-Manual are those for the LBP6030w.
- Depending on the country or region, the shape of power cord plugs and AC power outlets may differ from those shown in the illustrations of the e-Manual.

Other

This section describes basic Windows operations and includes disclaimers, copyright information, and other information.

Basic Windows Operations

- Displaying [Computer] or [My Computer]
- Displaying the Printer Folder
- CEnabling [Network discovery]
- ODisplaying Shared Printers in the Print Server
- Displaying the [CD-ROM/DVD-ROM Setup] Screen
- Printing a Test Page in Windows
- Checking the Bit Architecture
- Checking the Printer Port
- Checking Bidirectional Communication
- Checking the SSID to Which Your Computer Is Connected

Displaying [Computer] or [My Computer]

Windows XP/Server 2003 [Start] > select [My Computer].

Windows Vista/7/Server 2008 [Start] > select [Computer].

Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [File Explorer] > [Computer] or [This PC].

Displaying the Printer Folder

Windows XP Professional/Server 2003 [Start] > select [Printers and Faxes].

Windows XP Home Edition [Start] > select [Control Panel] > [Printers and Other Hardware] > [Printers and Faxes].

Windows Vista [Start] > select [Control Panel] > [Printer].

Windows 7/Server 2008 R2 [Start] > select [Devices and Printers].

Windows 8/Server 2012 Right-click the lower-left corner of the screen > select [Control Panel] > [View devices and printers].

Windows Server 2008 [Start] > select [Control Panel] > double-click [Printers].

Enabling [Network discovery]

If you are using Windows Vista/7/8/Server 2008/Server 2012, enable [Network discovery] to view the computers on your network.

Windows Vista

[Start] > select [Control Panel] > [View network status and tasks] > under [Network discovery], select [Turn on network discovery].

Windows 7/Server 2008 R2

[Start] > select [Control Panel] > [View network status and tasks] > [Change advanced sharing settings] > under [Network discovery], select [Turn on network discovery].

Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [Control Panel] > [View network status and tasks] > [Change advanced sharing settings] > under [Network discovery], select [Turn on network discovery].

Windows Server 2008

[Start] > select [Control Panel] > double-click [Network and Sharing Center] > under [Network discovery], select [Turn on network discovery].

1 Open [Windows Explorer] or [File Explorer].

Windows XP/Vista/7/Server 2003/Server 2008

[Start] > select [All Programs] or [Programs] > [Accessories] > [Windows Explorer].

Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [File Explorer].



Select a print server from [Network] or [My Network Places].

To check a computer on the network, you may need to enable [Network discovery] (SEnabling [Network discovery]) or search for the computer on the network.

💮 🕞 - 📴 + Libraries	*	× 49	Search Libraries				р Р
Organiza - New libro	ny			22	•	8	0
🛛 🜟 Favoritas	Libraries Open a library to see your files and	l arrange them by folder,	date, and other pro	perties.			
D Contraction	Documents	A.	Music				
> 🛤 Computer	Library		Library				
a Ser Maturet D ∰ PRINTSERVER	Pictures Library		Wideos Library				
4 items							

The shared printers are displayed.

				. *
🕒 🖉 🗮 🕨 Network	PRINTSERVER +	 Search PRINTSER 	VER	م
Organiza 🔹 Network a	nd Sharing Center View remote printers		81 F	0
🛛 🖈 Favoritas	Canon LEP6030 6040 6018L	SharedDocs Share		
D 📷 Libraries	·••.			
D M Computer				
4 📬 Network				
PRINTSERVER.				
2 items				

Displaying the [CD-ROM/DVD-ROM Setup] Screen

If your computer does not display the [CD-ROM/DVD-ROM Setup] screen after you insert the CD-ROM/DVD-ROM, follow the procedure below. This following example uses "D:" as the name of the CD-ROM/DVD-ROM drive. The CD-ROM/DVD-ROM drive name may be different on your computer.

Windows XP/Server 2003

[Start] > select [Run] > enter "D:\MInst.exe" > click [OK].

Windows Vista/7/Server 2008

[Start] • enter "D:\MInst.exe" in [Search programs and files] or [Start Search] • press the [ENTER] key on the keyboard.


Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [Run] > enter "D:\MInst.exe" > click [OK].

Printing a Test Page in Windows

You can check whether the printer driver is operational by printing a test page in Windows.

- Load A4 size paper in the multi-purpose tray. OLoading Paper in the Multi-Purpose Tray
- Display the printer folder. ODisplaying the Printer Folder
- **3** Right-click the icon of the machine and click [Printer properties] or [Properties].



4 In the [General] tab, click [Print Test Page].

Canon LBP6	030/0040/00	18L Propertie	;							
General hall	ng Pots	Advanced C	sior Manageme	nt Security	Device 3	Settings	Profile			
-	Canon I	BP6030/6040/	6038L							
Locations										
Comment										
Model	Canon L	896030/6040/	018L							
Features Color: No			Paper avail	able						
Double-si Staple: No	dect No		A4			*				
Speed: 18 Maximum	resolution	600 dpi				~				
		Prefs	NEDCEL.	Print	Test Pag					
							ОК	Cano	Apply	Help

Windows prints the test page.

Checking the Bit Architecture

If you are not sure whether your computer is running 32-bit or 64-bit Windows, follow the procedure below to check.

Display [Control Panel].

Windows Vista/7/Server 2008 [Start] > select [Control Panel].

Windows 8/Server 2012 Right-click the lower-left corner of the screen > select [Control Panel].

2 Display [System].

Windows Vista/7/8/Server 2008 R2/Server 2012 Click [System and Security] or [System and Maintenance] > [System].

Windows Server 2008 Double-click [System].


3 Check the bit architecture.

32-bit operating systems

[32-bit Operating System] is displayed.


64-bit operating systems [64-bit Operating System] is displayed.

Downloaded from ManualsPrinter.com Manuals




Checking the Printer Port

- **1** Display the printer folder. ODisplaying the Printer Folder
- 2 Right-click the icon of the machine and click [Printer properties] or [Properties].



3 In the [Ports] tab, check that the port is selected correctly.




NOTE

If you are using a network connection and have changed the machine's IP address (LBP6030w)


If the [Description] of the selected port is [Canon MFNP Port], and the machine and the computer are on the same subnet, then the connection will be maintained. You do not need to add a new port. If it is [Standard TCP/IP Port], you need to add a new port. **Configuring Printer Ports**

Checking Bidirectional Communication

- **1** Display the printer folder. ODisplaying the Printer Folder
- 2 Right-click the icon of the machine and click [Printer properties] or [Properties].



3 In the [Ports] tab, check that the [Enable bidirectional support] check box is selected.



Checking the SSID to Which Your Computer Is Connected

If your computer is connected to a wireless LAN network, click and , click and in the system tray to display the SSID of the connected wireless LAN router.



For Mac OS Users

Your machine may have not come with a driver for Mac OS depending on when you purchased the machine. The drivers are uploaded to the Canon website when they become needed. Check the operating system of your computer and download the appropriate driver from the Canon website. For the driver installation procedure and how to operate the driver, see the "Printer Driver Guide for Macintosh."

In the e-Manual and Printer Driver Installation Guide, methods to operate in the Windows environment are explained as examples. To view how to use the driver and utility for Mac OS, see the following guide or help.

Object	Reference	
Installing the driver	Printer Driver Guide for Macintosh	
How to use the driver functions	Driver Help	

Displaying the Driver Guide

Double-click the following HTML file in the [SFP] folder on the supplied CD-ROM/DVD-ROM.

Printer Driver Guide for Macintosh

[SFP] - [Documents] - [XXXXXX]* - [GUIDE] - [index.html]

* For [XXXXXX], select your desired language.

Displaying the Driver Help

Click [🕐] on the driver.

Notice

Third Party Services and Software

Third Party Software (PDF)

You need Adobe Reader/Adobe Acrobat Reader to view files in the PDF format. If Adobe Reader/Adobe Acrobat Reader is not installed on your system, download the reader from the Adobe System's web site and install it.

Product Name

Safety regulations require the product's name to be registered. In some regions where this product is sold, the following name(s) in parentheses () may be registered instead.

LBP6030w / LBP6030B / LBP6030 (F166400)

EMC requirements of EC Directive

This equipment conforms with the essential EMC requirements of EC Directive. We declare that this product conforms with the EMC requirements of EC Directive at nominal mains input 230 V, 50 Hz although the rated input of the product is 220 to 240 V, 50/60 Hz. Use of shielded cable is necessary to comply with the technical EMC requirements of EC Directive.

Laser Safety

This product is certified as a Class 1 laser product under IEC60825-1:2007 and EN60825-1:2007. This means that the product does not produce hazardous laser radiation.

Since radiation emitted inside the product is completely confined within protective housings and external covers, the laser beam cannot escape from the machine during any phase of user operation. Do not remove protective housings or external covers, except as directed by the equipment's manuals.

The label shown below is attached to the laser scanner unit inside the machine.



CLASS 1 LASER PRODUCT LASER KLASSE 1 APPAREIL À LASER DE CLASSE 1 APPARECCHIO LASER DI CLASSE 1 PRODUCTO LÁSER DE CLASE 1 APARELHO A LASER DE CLASSE 1 LUOKAN 1 LASER-TUOTE LASERPRODUKT KLASS 1

A CAUTION

Use of controls, adjustments, or performance of procedures other than those specified in this manual may result in hazardous radiation exposure.

International ENERGY STAR Program



As an ENERGY STAR® Partner, Canon Inc. has determined that this product meets the ENERGY STAR Program for energy efficiency.

The International ENERGY STAR Office Equipment Program is an international program that promotes energy saving through the use of computers and other office equipment.

The program backs the development and dissemination of products with functions that effectively reduce energy consumption. It is an open system in which business proprietors can participate voluntarily.

The targeted products are office equipment, such as computers, displays, printers, facsimiles, and copiers. The standards and logos are uniform among participating nations.

WEEE Directive



Only for European Union and EEA (Norway, Iceland and Liechtenstein)

This symbol indicates that this product is not to be disposed of with your household waste, according to the WEEE Directive (2012/19/EU) and national legislation. This product should be handed over to a designated collection point, e.g., on an authorized one-for-one basis when you buy a new similar product or to an authorized collection site for recycling waste electrical and electronic equipment (EEE). Improper handling of this type of waste could have a possible negative impact on the environment and human health due to potentially hazardous substances that are generally associated with EEE. At the same time, your cooperation in the correct disposal of this product will contribute to the effective usage of natural resources. For more information about where you can drop off your waste equipment for recycling, please contact your local city office, waste authority, approved WEEE scheme or your household waste disposal service. For more information regarding return and recycling of WEEE products, please visit www.canon-europe.com/weee.

■IPv6 Ready Logo



The protocol stack included in this machine has obtained the IPv6 Ready Logo Phase-1 established by the IPv6 Forum.

Product Information required by COMMISSION REGULATION (EU) No 801/2013 amending Regulation (EC) No 1275/2008

Power consumption of the product in networked standby if wired network ports are connected and all wireless network ports are activated (if they are available at the same time).

Model Name	Power consumption of the product in networked standby
LBP6030w	1.6 W

NOTE

The above value(s) are the actual values for single machine, chosen arbitrarily, and may therefore vary from the value of the machine in use. Optional network ports are not connected and/or activated in the measurement.

Legal Limitations on the Usage of Your Product and the Use of Images

Using your product to scan, print or otherwise reproduce certain documents, and the use of such images as scanned, printed or otherwise reproduced by your product, may be prohibited by law and may result in criminal and/or civil liability. A non-exhaustive list of these documents is set forth below. This list is intended to be a guide only. If you are uncertain about the legality of using your product to scan, print or otherwise reproduce any particular document, and/or of the use of the images scanned, printed or otherwise reproduced, you should consult in advance with your legal advisor for guidance.

- Paper Money
- Travelers Checks
- Money Orders
- Food Stamps
- Certificates of Deposit
- Passports

- Postage Stamps (canceled or uncanceled)
- Immigration Papers
- Identifying Badges or Insignias
- Internal Revenue Stamps (canceled or uncanceled)
- Selective Service or Draft Papers
- Bonds or Other Certificates of Indebtedness
- Checks or Drafts Issued by Governmental Agencies
- Stock Certificates
- Motor Vehicle Licenses and Certificates of Title
- Copyrighted Works/Works of Art without Permission of Copyright Owner

■Wireless LAN Regulatory Information LBP6030w

Regulatory information

Users in the European Union and other European countries

LBP6030w includes Wireless LAN Module (Model name: AW-NM383).

This device complies with the essential requirements of the R&TTE Directive 1999/5/EC.

R&TTE Declaration of Conformity (Wireless LAN Module)

CE

Česky [Czech]	Společnost CANON INC. tímto prohlašuje, že zařízení AW-NM383 je v souladu se základními požadavky a dalšími příslušnými ustanoveními směrnice 1999/5/ES.
Dansk [Danish]	Undertegnede CANON INC. erklærer herved, at AW-NM383 overholder de væsentlige krav og øvrige relevante krav i direktiv 1999/5/EF.
Deutsch [German]	Hiermit erklärt CANON INC., dass sich das Gerät AW-NM383 in Übereinstimmung mit den grundlegenden Anforderungen und den übrigen einschlägigen Bestimmungen der Richtlinie 1999/5/EG befindet.
Eesti [Estonian]	Käesolevaga kinnitab CANON INC. seadme AW-NM383 vastavust direktiivi 1999/5/EÜ olulistele nõuetele ja muudele asjakohastele sätetele.
English	Hereby, CANON INC., declares that AW-NM383 is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.
Español [Spanish]	Por medio de la presente CANON INC. declara que el AW-NM383 cumple con los requisitos esenciales y cualesquiera otras disposiciones aplicables o exigibles de la Directiva 1999/5/CE.
Ελληνική [Greek]	Με την παρούσα, η CANON INC., δηλώνει ότι το μοντέλο AW-NM383 συμμορφώνεται προς τις ουσιώδεις απαιτήσεις και τις λοιπές σχετικές διατάξεις της Οδηγίας 1999/5/ΕΚ.
Français [French]	Par la présente, CANON INC. déclare que l'appareil AW-NM383 est conforme aux exigences essentielles et aux autres dispositions pertinentes de la directive 1999/5/CE.
Italiano [Italian]	Con la presente CANON INC. dichiara che AW-NM383 è conforme ai requisiti essenziali ed alle altre disposizioni pertinenti stabilite dalla direttiva 1999/5/CE.
Latviski [Latvian]	Ar šo CANON INC. deklarē, ka AW-NM383 atbilst Direktīvas 1999/5/EK būtiskajām prasībām un citiem ar to saistītajiem noteikumiem.
Lietuvių [Lithuanian]	Šiuo bendrovė "CANON INC." deklaruoja, kad AW-NM383 atitinka pagrindinius Direktyvoje 1999/5/EB išdėstytus reikalavimus ir kitas josnuostatas.
Nederlands [Dutch]	Hierbij verklaart CANON INC. dat AW-NM383 in overeenstemming is met de essentiële eisen en de andere relevante bepalingen van richtlijn 1999/5/EG.
Malti [Maltese]	Hawnhekk, CANON INC., jiddikjara li I-AW-NM383 jikkonforma mal-ħtiġijiet essenzjali u ma' dispożizzjonijiet relevanti oħra tad-Direttiva 1999/5/KE.
Magyar [Hungarian]	Alulírott CANON INC. nyilatkozom, hogy a AW-NM383 megfelel a vonatkozó alapvető követelményeknek és az 1999/5/EC irányelv egyéb előírásainak.
Polski [Polish]	Niniejszym CANON INC. oświadcza, że model AW-NM383 jest zgodny z zasadniczymi wymogami oraz pozostałym stosownymi postanowieniami Dyrektywy 1999/5/EC.
Português [Portuguese]	Por este documento, a CANON INC. declara que o AW-NM383 está em conformidade com os requisitos essenciai e outras disposições relevantes da Diretiva 1999/5/CE.
Slovenščina [Slovenian]	Družba CANON INC. izjavlja, da je tiskalnik AW-NM383 skladni z bistvenimi zahtevami in ostalimi relevantnimi določili direktive 1999/5/ES.
Slovensky [Slovak]	CANON INC. týmto vyhlasuje, že AW-NM383 spĺňa základné požiadavky a všetky príslušné ustanovenia Smernice 1999/5/ES.

Suomi [Finnish]	CANON INC. vakuuttaa täten, että AW-NM383 -laite on direktiivin 1999/5/ EY oleellisten vaatimusten ja sitä koskevien direktiivin muiden ehtojen mukainen.
Svenska [Swedish]	Härmed intygar CANON INC. att denna AW-NM383 står i överensstämmelse med de väsentliga egenskapskrav och övriga relevanta bestämmelser som framgår av direktiv 1999/5/EG.
Română [Romanian]	Prin prezenta, CANON INC., declară faptul că aparatul AW-NM383 este în conformitate cu cerințele esențiale și cu alte prevederi relevante incluse în Directiva 1999/5/CE.
Български език [Bulgarian]	С настоящето CANON INC. декларира, че AW-NM383 отговаря на съществените изисквания и другите приложими изисквания на Директива 1999/5/ЕС.
Íslenska [Icelandic]	Hér með lýsir CANON INC. því yfir að AW-NM383 sé í samræmi við grunnkröfur og aðrar kröfur, sem gerðar eru í tilskipun 1999/5/EC.
Norsk [Norwegian]	CANON INC. erklærer herved at utstyret AW-NM383 er i samsvar med de grunnleggende krav og øvrige relevante krav i direktiv 1999/5/EF.
Gaeilge [Irish]	Dearbhaíonn CANON INC. leis seo go gcloíonn AW-NM383 le ceanglais riachtanacha agus le forálacha ábhartha eile na Treorach 1999/5/CE.

Česky [Czech]	* Toto zařízení může být provozováno na území AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Dansk [Danish]	* Dette produkt må anvendes i AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Deutsch [German]	* Dieses Gerät darf in folgenden Ländern betrieben werden AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Eesti [Estonian]	* Seda seadet võib kasutada AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
English	* This equipment may be operated in AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Español [Spanish]	* Este equipo puede ser utilizado en AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Français [French]	* Cet équipement peut être utilisable en AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Italiano [Italian]	* Questo dispositivo può essere utilizzato in AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Latviski [Latvian]	* Šo aprīkojumu drīkst lietot AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Lietuvių [Lithuanian]	* Šį įrenginį galima eksploatuoti AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Nederlands [Dutch]	* Deze apparatuur kan worden gebruikt in de volgende landen AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Suomi [Finnish]	* Laitetta voidaan käyttää seuraavassa maassa AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Malti [Maltese]	* Dan I-apparat jista' jintuza f' AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Magyar [Hungarian]	* Ez a készülék AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL NO, PL, PT, RO, SE, SI, SK üzemeltethető.
Polski [Polish]	* To urządzenie może być eksploatowane w AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Português [Portuguese]	* Este equipamento pode ser utilizado em AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Slovenščina [Slovenian]	* To opremo je dovoljeno uporabljati v AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Slovensky [Slovak]	 * Toto zariadenie môže byť používané na území AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK. * Upozornenie k používaniu tohto výrobku.Francúzsko: Tento výrobok sa nesmie používať vonku.
Ελληνική [Greek]	* Το παρόν προϊόν μπορεί να χρησιμοποιηθεί στην ΑΤ, ΒΕ, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Svenska [Swedish]	* Den här utrustningen kanske fungerar i AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Română [Romanian]	* Acest echipament poate fi operat in AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.

Български език [Bulgarian]	* Това оборудване може да се използва в АТ, ВЕ, ВG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Íslenska [Icelandic]	 * Viðgerð á þessu tæki má annast á AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Norsk [Norwegian]	* Dette produktet må anvendes i AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.
Gaeilge [Irish]	* Féadfar an trealamh seo a fheidhmiú in AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LT, LU, LV, MT, NL, NO, PL, PT, RO, SE, SI, SK.

Regulatory information for users in Jordan

LBP6030w includes approved Wireless LAN Module (Model name: AW-NM383).

Contains Wireless LAN Module approved by TRC/SS/2014/38

Regulatory information for users in UAE

LBP6030w includes approved Wireless LAN Module (Model name: AW-NM383).

TRA REGISTERED No: ER0126617/14 DEALER No: DA0060877/11

Disclaimers

- The information in this document is subject to change without notice.
- CANON INC. MAKES NO WARRANTY OF ANY KIND WITH REGARD TO THIS MATERIAL, EITHER EXPRESS OR IMPLIED, EXCEPT AS PROVIDED HEREIN, INCLUDING WITHOUT LIMITATION, THEREOF, WARRANTIES AS TO MARKETABILITY, MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OF USE OR NON-INFRINGEMENT. CANON INC. SHALL NOT BE LIABLE FOR ANY DIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES OF ANY NATURE, OR LOSSES OR EXPENSES RESULTING FROM THE USE OF THIS MATERIAL.

Copyright

Copyright CANON INC. 2014

No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual, or otherwise, without the prior written permission of Canon Inc.

Trademarks

- Apple, AppleTalk, EtherTalk, LocalTalk, Mac, Mac OS, Safari, and Bonjour are trademarks of Apple Inc., registered in the U.S. and other countries.
- Microsoft, Windows, Windows Vista, Windows Server and Internet Explorer are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- All other product and brand names are registered trademarks, trademarks or service marks of their respective owners.

Office Locations

CANON INC.

30-2, Shimomaruko 3-chome, Ohta-ku, Tokyo 146-8501, Japan

CANON MARKETING JAPAN INC.

16-6, Konan 2-chome, Minato-ku, Tokyo 108-8011, Japan

CANON U.S.A., INC.

One Canon Park, Melville, NY 11747, U.S.A.

CANON EUROPA N.V.

Bovenkerkerweg 59, 1185 XB Amstelveen, The Netherlands

CANON CHINA CO. LTD.

15F Jinbao Building No.89, Jinbao Street, Dongcheng District, Beijing 100005, PRC

CANON SINGAPORE PTE LTD

1 HarbourFront Avenue, #04-01 Keppel Bay Tower, Singapore 098632

CANON AUSTRALIA PTY LTD

1 Thomas Holt Drive, North Ryde, Sydney NSW 2113, Australia

CANON GLOBAL WORLDWIDE SITES

http://www.canon.com/



LBP6030w / LBP6030B / LBP6030 Printer Driver Installation Guide

Introduction 3	
System Requirements 4	
Installing 5	
Installing from the Supplied CD-ROM/DVD-ROM 6	
Installing after Downloading from the Canon Website 13	
Installing to Use WSD 17	
Setting Up a Print Server 22	
Configuring Settings on the Print Server Computer 23	
Installing Drivers via the Print Server (Client Settings) 26	
Updating and Uninstalling 27	
Updating 28	
Uninstalling 30	
Troubleshooting 33	
Deleting the USB Class Driver36	
Appendix 38	
Connecting the Printer to a Computer 39	
Connecting via Wireless LAN 40	
Connecting via USB 42	
MF/LBP Network Setup Tool 43	
Using the Installation Guide 45	
Screen Configuration of the Installation Guide 46	
Viewing the Installation Guide 49	
Other 50	
Basic Windows Operations 51	
Notice 53	

Introduction

This Installation Guide mainly explains how to install a printer driver and how to set up a print server.

NOTE

System requirements for installation of printer drivers **OSystem Requirements**

Installing

This section explains how to install a printer driver and how to set up the printer so that it is ready to print. OInstalling



Setting Up a Print Server

This section explains how to set up a print server on the network, and how to install printer drivers on client computers via the print server. Setting Up a Print Server



Updating and Uninstalling

This section explains how to update and uninstall printer drivers. **OUpdating and Uninstalling**





Troubleshooting

This section explains how to resolve problems that may occur during printer driver installation. OTroubleshooting



Appendix

This section explains how to connect the printer to a computer, and how to start the MF/LBP Network Setup Tool manually. It also explains how to use the Installation Guide and provides other useful information. **OAppendix**



System Requirements

The following system environment is required to install printer drivers.

OS	 Windows XP Windows Vista Windows 7 Windows 8 Windows 8.1 Windows Server 2003 Windows Server 2008 Windows Server 2008 R2 (64-bit version only) Windows Server 2012 (64-bit version only) Windows Server 2012 R2 (64-bit version only)
Computer	A computer running one of the above operating systems

NOTE


For information about support for the latest operating systems and service packs, visit the Canon website (http://www.canon.com/).

Installing

This section explains how to install a printer driver on your computer and how to set up the printer so that it is ready to print. The printer driver is software that you need to use the printer. Read this section and install the printer driver correctly.

■Installing from the Supplied CD-ROM/DVD-ROM

Install the printer driver from the User Software CD-ROM/DVD-ROM that is supplied with the printer. Perform the setup procedure, from connecting the printer and your computer to installation of the printer driver. **OINSTALLING from the Supplied CD-ROM/DVD-ROM**



■Installing after Downloading from the Canon Website

The latest printer driver versions are available for downloading from the Canon website. Download a printer driver if, for example, the drivers on the CD-ROM/DVD-ROM do not support the operating system of your computer. **Distalling after Downloading from the Canon Website**



NOTE

Adding a WSD Network Printer

If you are using Windows Vista/7/8/Server 2008/Server 2012, you can use WSD (Web Services on Devices) to add a network printer. **OInstalling to Use WSD**

Installing from the Supplied CD-ROM/DVD-ROM

The order of operations in an Easy Installation is "Configure network settings" > "Install the printer driver" > "Install the e-Manual." If you are connecting the printer and a computer via wireless LAN, read **OThings to Check before Starting** before starting.



- The printer may not be recognized if you install the printer driver with the printer turned ON. Always turn OFF the power before installing.
- 2 Log on to the computer with an administrator account.
- **3** Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.
- **4** Click [Easy Installation].

Canon	UFRII LT CD-ROM/DVD-ROM Setup
	Easy Installation
	Custom Installation
111.	Start Software Programs
1	Stats programs required for configuring sattings, etc. Manuals Displays manuals
A.	
. 1 (S)	Ext

NOTE:

- If you do not want to install the e-Manual on your computer, click [Custom Installation].
- If the above screen does not appear Displaying the [CD-ROM/DVD-ROM Setup] Screen
- If [AutoPlay] is displayed, click [Run MInst.exe].

asy Installation In Miloratog programs will be installed. Click (Install, and then follow the instructions displayed on the screen. You can configure the network settings for your device on subsequent screens if it is a network model.	
Printer Driver This program is required for printing using your device.	Readme 80 MB
A Marcual These are the manuals for your device. If you install the manuals on your computer, you can display them with using this COLDVO.	rout 11 MB
C : Free Disk Space 54452 MB Space Required to Inst	tali 91 M
Back Index	Cancel

NOTE:

If you clicked [Custom Installation] in step 4 Clear the [e-Manual] check box, and click [Install].



6 Read the License Agreement and click [Yes] to agree.

License Agreement
Please read the following license agreement completely and carefully before installing the software programs.
(September 1995). Consistent with 48 C.F.R. 12.212 and 48 C.F.R. 227.7202-1 through 227.7202-4 (June 1995), all U.S. Government End Users shall acquire the Software with only those rights set forth herein. Manufacturer is Canon Inc.70-2, Shirnomanuko 3-chome, Otta-ku, Tokyo 146-8591, Japan. 10. SEVERABLITY In the event that are section hereof is declared or found to be illegal by air court or tribunal of competent jurisdiction, such the event that are section hereof is declared or found to be illegal by air court or tribunal of competent jurisdiction, such
section shall be null and void with respect to the jurisdiction of that court or tribunal and all the remaining provisions hereof shall remain in hill force and effect.
11. ACKNOWLEDGEMENT BY CLICKWO THE BUTTON HID/CATING YOUR ACCEPTANCE AS STATED BELOW OR USING THE SOFTWARE, YOU ACKNOWLEDGE THAT YOU AWE READ THIS AGREEMENT, UNDERSTOOD IT, AND AGREE TO BE BOUND BY ITS TERMS AND COMMITIONS. YOU AL SO AGREE THAT THIS AGREEMENT IS THE COMPLETE AND EXCLUSIVE STATEMENT OF ADREEMENT BETWEEN YOU AND CANON COMCEMINGS THE SUBJECT ANTERHISTOR AND SUBSTRIESS ALL PROVIDENT SOFTWARE, YOU ARD CANON WINTER, AND ANY OTHER COMMUNICATIONS BETWEEN YOU AND CANON RELATING TO THE SUBJECT MATTER HERGE, MIN DAY WINTER, AND ANY OTHER COMMUNICATIONS BETWEEN YOU AND CANON RELATING TO THE SUBJECT MATTER HERGE, AND AMENDMENT TO THIS AGREEMENT STATE COMPLEXIES WOLL PROVIDE A OULY AUTHOROUSD BETWEEN WEEK OF CANON.
Should you have any questions concerning this Agreement, or if you desire to contact Canon for any reason, please write to Canon's sales subsidiary or distributoritiesles, serving the country where you obtained the Products.
To accept the terms of this agreement, click [Yes]. To decline the terms of this agreement, click [Yes] To use this program, that ferms of this agreement must be accepted.
Back Yes No

7 Configure the network settings.

Canon MF/LBP Network Setup Tool	- C 🔀
Select the type of connection between the printer and your computer.	
	O Wind LAN Connection
	Wireless LAN Connection
	C 158 Carmection
Useful Tips Ohange Settings	Next >

Wireless LAN Connection

1 Select [Wireless LAN Connection], and click [Next].

2 Follow the on-screen instructions to configure the network settings.

NOTE:

If there is something you do not understand

Click [Useful Tips] at the bottom left of the screen to display troubleshooting tips.



USB Connection

- **1** Select [USB Connection], and click [Next].
- 2 Click [Next].

8 Install the printer driver.

Wireless LAN Connection

1 Select [Standard], select the [Reactivate Printers in the Sleep Mode and Search] check box, and click [Next].

If you are using the printer in an IPv6 environment, click [Detailed Settings] ▶ select [Standard TCP/IP Port] ▶ click [OK].



NOTE: About [Detailed Settings] You can select the port type.

Detailed Settings	
Select a pot.	
Post Type MFNP Port Standard TCP/IP Port	
	OK Cancel

[MFNP Port] (only for IPv4 environment)

This is a port that enables automatic detection of the printer's IP address. Even if the IP address of the printer is changed, the connection between the printer and computer will be maintained, provided that they belong to the same subnet. Therefore, you do not need to add a new port every time the IP address is changed. If you are using the printer in an IPv4 environment, choose this setting.

[Standard TCP/IP Port]

This is a standard Windows port. Whenever the IP address of the printer is changed, a new port must be added.

2 Select check box for the printer that you want to install from the [Printer List].

If you want to use the printer in an IPv6 environment, click the [IPv6 Devices] tab.

ect Printers to Insi ielect the printers (ick [Next].	
Pv4Devices			Manual Search by IP Address
Device Name	Product Name	IP Address	MAC Address
	102	192.168.0.215	240A6420AE73

NOTE:

If the [Select Process] screen is displayed


If a printer driver is already installed, the [Select Process] screen is displayed before the [Select Printers to Install] screen. For your printer, the selection made here makes no difference for the setup process. Simply click [Next].

91	UFRILT Printer Driver - Ver. 21.10
5	lect Process ielect the items to install and the process to install the printer
V	UFRIILT Printer Driver
	Process to Install Printer Driver
	Add New Printers and Update Existing Printer Drivers
	O Add New Printers
	<back next=""> Cancel</back>

If the [IPv6 Devices] tab is not displayed Return to the previous screen, and click [Detailed Settings] > select [Standard TCP/IP Port].

If the printer that you want does not appear in [Printer List] Problems with the Wireless LAN Connection

3 Select the [Set Printer Information] check box, and click [Next].



4 Set the printer information as necessary, and click [Next].

UFRI LT Printer Driver - Ver. 21.10 Printer Information	
Set the port to be used for the selecte Also, you can specify a name for the p	sd printer.
Selected Printer: Use Driver: Port:	Cenon UPP Cenon UPRII LT Driver Ver. 21.10 CHMMP240A6428AE73 * Add Port
Printer Name: Set as Default Use as Shared Printer	Canon LIP
Shared Name:	Onivers to Add Current Printers 1 Number of Printers to Sets 1
	<baok next=""> Cancel</baok>

[Printer Name]

Change the printer name as necessary.

[Set as Default]

Select the check box if you want to use your printer as your default printer.

[Use as Shared Printer]

Select the check box if you want to share the printer (using the computer where you are performing the installation as a print server). **Osetting Up a Print Server during Printer Driver Installation**

5 Check the printer information in [Printer List for Driver Installation], and click [Start].

The setup program will install the drivers wit * Installation cannot be canceled once sta		
Printer List for Driver Installation:		
= Add = Pinter: Canon LB ⁺ (Set Driver : Canon LB Port : CRMPR#_2+0A6425AE73	is default)	

where Installation of the printer driver starts.



1 Select [USB Connection], and click [Next].



2 Click [Yes].



3 When the following screen appears, connect the computer and the printer with a USB cable (OConnecting via USB), and turn ON the printer.

USB Connection	
	Follow the steps below to install the printer driver:
	Statusi
1	 Connect the USB cable to the computer. Connect the USB cable to the printer. If the printer power is off, turn on the
2 🤙 🚔	printer. The printer will be recognized automatically and installation of printer drivers will start.
2.00	If the printer is not automatically recognized
2	even with the USB cable connected, disconnect the cable from the printer after turning off the printer, and then connect the cable egain.
do la	

Installation of the printer driver starts.

NOTE:

If installation does not start **OProblems with the USB Connection**

9 Install the e-Manual.

If you selected [Custom Installation], proceed to step 10.

1 Click [Install].

If you want to change the install destination, click [Browse] and select it.

💭 Manual Installer			
Select the folder where the manual will be installed.			
Destination Folder:			
C1(Program Piles			frovan
	install)	Cancel
	1993)	uance

Installation of the e-Manual starts.

2 Click [Exit].

💝 Manual Installer		X
Instal Manuals Installation of the manuals is complete.		
	Evit	
	CM	

10 Read the information in the following screen carefully, select [Accept] or [Do Not Accept], and click [Next].

ior the development and marketing of products that better need outside needs. Canon requests that the informat when, neisted to your Genon product, be sent via the Internet to Genon (or, in the case that you are using a Canon reduct in Clinia, to the begath approved neered: Company).	
 Information related to Canon laser printer/fax <i>Anktar's</i> ID number, installation date and time, toner use information, number of sheets printed, and <i>mathemace</i>: Information	^
If your Canon product is shared for use, callective information recorded in the shared product will be sent. In this survey, we will not send any other information, including your personal information. For this reason, from the information that is sent to us, we are unable to identify specific outcomes. We are therefore unable to respond to requests to disouse any sent information.	
After you install the survey program, the above information will be sent to Canon (in case of using your Canon product in Orans, to the legally approved reason in corpany) through the Internet every month for ten years. The Internet correction for shall be boxen by you.	
to accept the terms above, select [Accept], and then click [Next] to start installation of this program.	
Accept Send information without confirmation once installation is complete Do Not Accept	
Next >	

If you select [Accept], the Product Extended Survey Program is installed.

The Product Extended Survey Program is a program to send basic information related to installation and usage of the printer to Canon every month for 10 years. It does not send any other information, including your personal information. You can uninstall the Product Extended Survey Program at any time. Our product Extended Survey Program

11 Click [Next].

Install
Gäck (Newl) to evit setup.
Applied This program is required for printing using your device.
Palanual These are the manuals for your device. If you install the manuals on your computer, you can display them without using this CoCO.
Red

12 Select the [Restart Computer Now (Recommended)] check box, and click [Restart].



Checking the Results of the Installation

If the printer driver has been installed correctly, an icon for the installed printer will be displayed in the printer folder (**Displaying the Printer Folder**).

()) = 10 * Hardware and Sound + Devices and Printers + 49	Search Devices and Printers
Add a device Add a printer	
> Devices (4)	
 Printers and Faxes (3) 	
Cnon LBP Document Witer	
7 Barris	

If the e-Manual has been installed correctly, a shortcut icon for the e-Manual will be displayed on the desktop.

 $^{\ast}\,$ However, the icon is not displayed if you selected [Custom Installation].




NOTE

If the icon is not displayed

Uninstall the printer driver (**OUninstalling Printer Drivers**) and repeat the setup from the beginning.

Installing after Downloading from the Canon Website

Install the printer driver after downloading the latest version from the Canon website.




8 Read the License Agreement and click [Yes] to agree.

icense Agreement		1
Please read the following license agreement compl carefully. Click [Yes] to agree to the license agree		l
BY CLICKING THE BUTTON INDICATING YOUR INSTALLING THE SOFTWARE, YOU ACKNOWLE AGREENTERT, UNDERSTOOD IT, AND AGREE TO CONDITIONS, YOU ALSO AGREE THAT THIS A DOCUMENT STATEMENT OF AGREENTERT BIT SUBJECT MATTER HEREOF AND SUBJECTES.	DGE THAT YOU HAVE READ THIS BE BOUND BY ITS TERMS AND GREEMENT IS THE COMPLETE AND HEN YOU AND CANON CONCERNING THE	,
AGRIEHENTS, VERBAL OR WRITTEN, AND ANY YOU AND CANON RELATING TO THE SUBJECT THIS AGRIEHENT SHALL BE EFFECTIVE UNLES REPRESENTATIVE OF CANON.	MATTER HEREOF. NO AMENDMENT TO	
YOU AND CANON RELATING TO THE SUBJECT THIS AGREEMENT SHALL BE EFFECTIVE UNLES	MATTER HEREOF. NO AMENDMENT TO IS SIGNED BY A DULY AUTHORISED	
YOU AND CANON RELATING TO THE SUBJECT THIS AGREEHENT SHALL BE EFFECTIVE UNLES REPRESENTATIVE OF CANON. Should you have any questions concerning this Agr for any reason, please write to Canon's sales subsi	MATTER HEREOF. NO AMENDMENT TO IS SIGNED BY A DULY AUTHORISED	

Install the printer driver.

```
■ Wireless LAN Connection
```

- Select [Standard], select the [Reactivate Printers in the Sleep Mode and Search] check box, and click [Next].
 - If you are using the printer in an IPv6 environment, click [Detailed Settings] > select [Standard TCP/IP Port] > click [OK].



NOTE:

About [Detailed Settings] You can select the port type.

Detailed Settings		
Select a pot.		
Post Type MFNP Port		
Standard TCP/IP Port		
	OK	Cancel

[MFNP Port] (only for IPv4 environment)

This is a port that enables automatic detection of the printer's IP address. Even if the IP address of the printer is changed, the connection between the printer and computer will be maintained, provided that they belong to the same subnet. Therefore, you do not need to add a new port every time the IP address is changed. If you are using the printer in an IPv4 environment, choose this setting.

[Standard TCP/IP Port]

This is a standard Windows port. Whenever the IP address of the printer is changed, a new port must be added.

2 Select check box for the printer that you want to install from the [Printer List].


If you want to use the printer in an IPv6 environment, click the [IPv6 Devices] tab.

elect Printers to Inst			
Select the printers I	to add, and then o	iki [Next].	
IPv4Devices			Manuel Search by 3P Address
Printer List:			
Device Name	Product Name	IP Address	MAC Address
11 LTP	LIP	192.168.0.215	240A6420AE73

NOTE:

If the [Select Process] screen is displayed

If a printer driver is already installed, the [Select Process] screen is displayed before the [Select Printers to Install] screen. For your printer, the selection made here makes no difference for the setup process. Simply click [Next].



If the [IPv6 Devices] tab is not displayed Return to the previous screen, and click [Detailed Settings] > select [Standard TCP/IP Port].

If the printer that you want does not appear in [Printer List] Problems with the Wireless LAN Connection

3 Select the [Set Printer Information] check box, and click [Next].

4Devices			Manual Search by IP Address
hinter List:			
Device Name	Product Name	IP Address	MAC Address
e			Cear Al Search Apain

4 Set the printer information as necessary, and click [Next].

💱 UFRI LT Printer Driver - V	ur. 21.10
Printer Information Set the port to be used for it Also, you can specify a name	
Selected Printer:	Canon LBP
Use Driver:	Canon UFRIILT Driver Ver. 21.10
Ports	CNMPNP_240A6428AE73
	Add Port
Printer Name:	Canon UP
Set as Default	
Use as Shared Printer	
Shared Name:	
	Drivers to Add
	Current Printer
	Number of Printers to Sets
	<back next=""> Cancel</back>

[Printer Name]

Change the printer name as necessary.


[Set as Default]

Select the check box if you want to use your printer as your default printer.

[Use as Shared Printer]

Select the check box if you want to share the printer (using the computer where you are performing the installation as a print server). **Osetting Up a Print Server during Printer Driver Installation**

5 Check the printer information in [Printer List for Driver Installation], and click [Start].



Installation of the printer driver starts.

USB Connection


1 Select [USB Connection], and click [Next].



2 Click [Yes].

Warning		22
4	Installation cannot be stopped once started. Do you want to continue?	
	Yes No	

3 When the following screen appears, connect the computer and the printer with a USB cable (©Connecting via USB), and turn ON the printer.



Installation of the printer driver starts.


NOTE: If installation does not start **OProblems with the USB Connection**

10 Select the [Restart My Computer Now] check box, and click [Restart].



Checking the Results of the Installation

If the printer driver has been installed correctly, an icon for the installed printer will be displayed in the printer folder (**Displaying the Printer Folder**).



NOTE

If the icon is not displayed

Uninstall the printer driver (**Ouninstalling Printer Drivers**) and repeat the installation from the beginning.

Installing to Use WSD

If you are using Windows Vista/7/8/Server 2008/Server 2012, you can print by using the WSD (Web Services on Devices) protocol. If you want to use WSD, first install the printer driver and then add a network printer.


Installing a Printer Driver Adding a Network Printer

Installing a Printer Driver

- Log on to the computer with an administrator account.
- 2 Open the printer folder. ODisplaying the Printer Folder
- **3** Click [Add a printer] or [Add Printer].

~~~~		
GG + Rardware and Sound + Devices and Printers	• + Search Devices as	of Printers 🔎
Add a device Add a printer		8 · 0
> Devices (4)		
Printers and Faxes (2)     Fax     Fax     Procent     SP5     Document     Writer		
6 karrs		

# 4 Click [Add a local printer].





Check that [LPT1] is selected under [Use an existing port], and click [Next].

Choose a printer port		
A printer port is a type of con	mection that allows your computer to	exchange information with a printer
Use an existing port:	LPT1: (Printer Port)	
Create a new port:		
Type of port	Local Port	

**6** Click [Have Disk].

0	🖶 Add Printer		
		te list. CErck Windows Update to see more models. Installation CD, click Have Disk.	
	Manufacturer	Printers           Brother DCP-115C           Brother DCP-12C           B	•
		Next Can	cel

# 7 Click [Browse].

Install Fro	m Disk	
J	Inset the manufacturer's installation disk, and then make sure that the correct drive is selected below.	OK Cancel
	Copy menufacturer's files from:	• Browse

8 Specify the folder where the printer driver is stored, select the Inf file, and click [Open].

Locate File					
Look in:	👗 Driver		- 0	🌶 🗈 🗖	
Recent Places	S] INF				
Desktop					
Libraries					
Computer					
Network					
PREWORK	File name:	Included JNF		- (	Open
	Files of type:	Satup Information (*.inf)		Ŧ	Cancel

Specify the folder where the printer driver is stored as follows.

```
32-bit operating system
Specify [UFRII] ▶ [uk_eng] ▶ [32BIT] ▶ [Driver] folders of the CD-ROM/DVD-ROM or downloaded file.
```

```
64-bit operating system
Specify [UFRII] ▶ [uk_eng] ▶ [x64] ▶ [Driver] folders of the CD-ROM/DVD-ROM or downloaded file.
```


### NOTE:

If you do not know whether to specify the 32-bit version or the 64-bit version OChecking the Bit Architecture

# **9** Click [OK].

Install Fro	m Disk	
4	Inset the nanufacture's installation disk, and then make sure that the correct drive is selected below.	OK Cancel
	Copy menufacture's files from: D:\UFRIN\328IT\Driver •	Browse

**10** Select your printer, and click [Next].



**11** Change the printer name as necessary, and click [Next].

Type a printer	name	
Printername	Canon L60	
This printer will be	installed with the Canon LBP driv	er.
This printer will be	installed with the Canon LBP driv	er.
This printer will be	installed with the Canon LBP driv	er.
This printer will be	installed with the Canon LEP driv	g.
This printer will be	installed with the Canon LBP driv	er.
This printer will be	installed with the Canon LEP driv	er.


The installation starts.

# 12 Select [Do not share this printer], and click [Next].

If you want to share the printer, make sharing settings for the printer added with OAdding a Network Printer. (OCOnfiguring Settings on the Print Server Computer)

		- 21
0	Hinter	
	Printer Sharing	
	If you want to share this printer, you must provide a share name. You can use the suggested name or type a new one. The share name will be visible to other network users.	
	O not share this printer	
	Share this printer so that others on your network can find and use it	
	Share name:	
	Location	
	Comment:	
		_
	Next Carr	and in the second

# 13 Click [Finish].



 $\Rightarrow$  An icon for the installed printer is displayed in the printer folder.

COC + Hardware and Sound + Devices and Printers	* 47	Search Devices and Printers	م
Add a device Add a printer		20 ·	• 0
> Devices (4)			
<ul> <li>Printers and Faxes (3)</li> </ul>			
Chron LBPI BPI Decement Witter			
7 kens			

# Adding a Network Printer

# **1** Open the network folder.

# Windows Vista/Server 2008

[Start] > select [Network].

Windows 7/Server 2008 R2 [Start] > [Computer] > select [Network].


### Windows 8/Server 2012

Right-click the lower-left corner of the screen > [File Explorer] > select [Network].

# 2 Right-click the newly added printer icon, and click [Install].

Carlos - Network			+ Search Network		۳	
00.0				12r	-	-
Organize • Install	Network and Sharing Center > Computer (9) > Other Devices (3) > Printers (1) Caren LBP	Add a printer Ac Install View device webpe Create shortcut Properties	dd a wireless device	2.		
Canon LBP	Categories P Network location: 1					


Installation for using WSD is complete when an icon for the printer is added to the printer folder.



# NOTE

### **Deleting Unneeded Printer Icons**

When you have finished installing the network printer, the icon added in step 13 of **CInstalling a Printer Driver** is no longer needed. To delete the icon, right-click it and select [Remove device] or [Delete] - click [Yes].



# **Setting Up a Print Server**

You can lessen the burden on computers that request printing services by setting up a print server. You can also use the print server to install printer drivers on other computers, so that users of those computers do not need to install the printer driver from the CD-ROM/DVD-ROM.


## Configuring Settings on the Print Server Computer

Configure printer sharing settings on the computer that you want to use as the print server. **Configuring Settings on the Print Server Computer** 



# ■Installing Drivers via the Print Server (Client Settings)

You can use the print server to install printer drivers on other computers (clients) on the same network. This allows all of the computers to share the same printer. **OInstalling Drivers via the Print Server (Client Settings)** 




# **Configuring Settings on the Print Server Computer**


Configure printer sharing settings on the computer that you want to use as the print server. The following procedure assumes that you have already installed the printer driver on the computer that you plan to use as the print server. If you have not installed the printer driver already, see **Osetting Up a Print Server during Printer Driver Installation**.

# IMPORTANT

- It may not be possible to install printer drivers over the network if the client computers and the print server use different versions of the operating system (32-bit or 64-bit).
- Consult your network administrator if you want to set up a print server in a domain environment.
- Log on to the computer with an administrator account.
- Open the printer folder. ODisplaying the Printer Folder
- 3 Right-click the icon of the printer you are setting up and click [Printer properties] or [Properties].



4 Click the [Sharing] tab, select [Share this printer], and enter the share name.



NOTE: If [Change sharing options] is displayed Click [Change sharing options].



5 Install additional drivers as necessary. 🔄

- During the procedure explained in OInstalling Drivers via the Print Server (Client Settings), this step is necessary if you want to use the print server to install printer drivers on computers that use different processor versions (32-bit or 64-bit) of the operating system.
  - **1** Click [Additional Drivers].
  - **2** Select the additional drivers, and click [OK].



Select additional drivers as follows, according to the operating system of the print server.

Print Server	Additional Drivers
32-bit OS	Select [x64].
64-bit OS	<ul> <li>Windows XP/Server 2003         Select [Windows 2000, Windows XP and Windows Server 2003] under [Version].</li> <li>Windows Vista/7/8/Server 2008/         Server 2012         Select [x86] under [Processor].</li> </ul>

#### NOTE:

If you do not know whether to specify the 32-bit version or the 64-bit version for Windows Vista/7/8/Server 2008/Server 2012, see **Checking the Bit Architecture**.

### **3** Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.

If you want to use printer drivers downloaded from the Canon website, download the additional drivers (printer drivers for processor versions that are different from that of the print server).

#### NOTE:

When the [CD-ROM/DVD-ROM Setup] screen is displayed, click [Exit].

#### 4 Click [Browse].

Install pri	nt drivers (x64 processor)	
\$	Please provide a printer driver.	OK Cancel
	Type the path where the file is located, and then click $O\bar{K}$	
	Copy files from:	Browse

5 Specify the folder where the additional drivers are stored, select the Inf file, and click [Open].

no Locate File					- 20-
Look in:	🕌 Driver		•	G 🖠 🖻	<b>-</b>
Recent Places	2	NF			
Desktop					
Libraries					
Computer					
Network					
	File name:	The second part of the			Open
	Files of type:	"inf;"in_		Ŧ	Cancel

Specify the folder where the additional drivers are stored as follows.

```
When the print server uses a 32-bit OS

Specify [UFRII] ▶ [uk_eng] ▶ [x64] ▶ [Driver] folders of the CD-ROM/DVD-ROM or downloaded file.

When the print server uses a 64-bit OS

Specify [UFRII] ▶ [uk_eng] ▶ [32BIT] ▶ [Driver] folders of the CD-ROM/DVD-ROM or downloaded file.
```

- 6 Click [OK].
  - Installation of the additional driver starts. Wait until you are returned to the [Sharing] tab.



### Setting Up a Print Server during Printer Driver Installation

If you are using a printer connected by wireless LAN, you can set up a print server at the time when you install the printer driver. To set the computer onto which you are installing the print driver as a print server, select [Use as Shared Printer] in the [Printer Information] screen, which is displayed when you install the printer driver.

### IMPORTANT

If you are using a printer connected by USB, you cannot set up a print server at the time when you install the printer driver. Set up the print server after installing the printer driver, by using the procedure described above.

### NOTE

For the complete installation procedure, see **OInstalling**.

### [Printer Information] screen

Printer Information	
Set the port to be used for Also, you can specify a nan	the selected printer.
Selected Printer:	Canon LBP
Use Driver:	Canon UFRIILT Driver Ver. 21.10
Ports	CMMPNP_240A6428AE73 *
	Add Port
Printer Name:	Canon LIP
Set as Default	
Use as Shared Printer	
Shared Name:	Canon LBP
	Drivers to Add
	Current Printer: 1 Number of Printers to Set: 1

### [Use as Shared Printer]

When this is selected, the computer onto which you are installing the printer driver is designated as a print server.

### [Shared Name]

Enter the name of the shared printer.

### [Drivers to Add]


Click to install additional drivers. During the procedure explained in **Dinstalling Drivers via the Print Server (Client Settings)**, additional drivers are necessary if you want to use the print server to install printer drivers on computers that use different processor versions (32-bit or 64-bit) of the operating system.

### LINKS


Installing Drivers via the Print Server (Client Settings)

# Installing Drivers via the Print Server (Client Settings)

You can use the print server to install printer drivers for a shared printer on other computers (clients) on the same network. Because the printer drivers are installed via the print server, users of the other computers do not need to use the printer's CD-ROM/DVD-ROM.



If the print server is not discovered **OProblems via the Print Server** 



Follow the instructions on the screen to install the printer drivers.

#### **IMPORTANT:**

4

It may not be possible to install printer drivers via the print server if the client computers and the print server use different processor versions (32-bit or 64-bit) of the operating system. In this case, install additional drivers on the print server. Oconfiguring Settings on the Print Server Computer

# **Updating and Uninstalling**

This section explains how to update and uninstall printer drivers. It also explains how to uninstall the Product Extended Survey Program.

# Updating

You can update installed printer drivers to the latest versions. OUpdating



## Uninstalling

When you no longer need installed printer drivers or the Product Extended Survey Program, you can uninstall (delete) them. Olinistalling



# Updating

computer. 1 Log on to the computer with an administrator account. 2 Download the printer driver from the Canon website (http://www.canon.com/). For more information about how to download the printer driver, see the driver download page for your printer. 3 Unzip the downloaded file. 4 Open the folder where the printer driver is stored. 32-bit operating system [UFRII] > [uk_eng] > [32BIT] folders 64-bit operating system [UFRII] > [uk_eng] > [x64] folders NOTE: If you do not know whether to specify the 32-bit version or the 64-bit version for Windows Vista/7/8/Server 2008/Server 2012, see **Checking the Bit Architecture**. 5 Double-click "Setup.exe." 😋 🔾 🗢 📕 🖛 UFRI 🕨 🌆 ► 32817 ► * <del>6</del>9


Proceed as follows to download the latest printer driver from the Canon website and update the printer driver installed on your



6 Read the License Agreement and click [Yes] to agree.







8 Select [Update Existing Printer Drivers], and click [Next].



**9** Check the printer information in [Printer List for Driver Installation], and click [Start].

he setup program will install the drivers with the	following settings.	
* Installation cannot be canceled once started.		
rinter List for Driver Installation:		
= Update = Printer: Canon LBP		
Driver : Canon LBP Port : CNMPNP_240A6428AE73		
lick (Start) to install.		

Updating of the printer driver starts.

# **10** Select [Restart My Computer Now], and click [Restart].



# Uninstalling


When you no longer need installed printer drivers or the Product Extended Survey Program, you can uninstall them to delete them from your computer.

### OUninstalling Printer Drivers

OUninstalling the Product Extended Survey Program

# Uninstalling Printer Drivers

- Log on to the computer with an administrator account.
- 2 Display [Programs and Features] or [Add or Remove Programs]. ODisplaying [Programs and Features] or [Add or Remove Programs]
- 3 Select the printer driver that you want to uninstall, and click [Uninstall/Change] or [Change/Remove].



The uninstaller starts.

#### NOTE:

If you cannot find the printer driver that you want to uninstall

Start the uninstaller from the User Software CD-ROM/DVD-ROM or from the printer driver file that you downloaded.

### **1** Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.

To start the uninstaller from a printer driver file that you downloaded, carry out the following step.

**2** Open the folder where the uninstaller is stored.

### 32-bit operating system

[UFRII] > [uk_eng] > [32BIT] > [misc] folders of the CD-ROM/DVD-ROM or downloaded file

#### 64-bit operating system

[UFRII] > [uk_eng] > [x64] > [misc] folders of the CD-ROM/DVD-ROM or downloaded file

#### NOTE:

If you do not know whether to specify the 32-bit version or the 64-bit version for Windows Vista/7/8/Server 2008/Server 2012, see **Checking the Bit Architecture**.

### **3** Double-click "UNINSTAL.exe."

Organiza • Burn t	o disc Erase this disc						
🔆 Favorites	18.5 KB		. 40	20.00			
📜 Libraries	UNSDRVJN Configura 4.06 KB	<b>E</b> tion settings	Q	SetupUIK.dll 6.1.0.0 Canon Printer Driv	er Installer		
💻 Computer	Uninstini Configure 3.66 KB	tion settings	-	UNINSTAL.axe Canon Printer Driv CANON INC.	er Uninstaller		
🗣 Network	GLO.D Canon Pri	dil nter Driver Unirotaller				·	

4 Select the printer that you want to uninstall, and click [Delete].

ntei Naine	Driver Name	Version
Canon LB P	Canon LBP	21.10

#### **IMPORTANT:**

If you click [Cleanup], then all files, directory information and other data related to all printers are deleted, not only for the selected printer but for all printers in the list. Normally you should use [Delete] to uninstall printer drivers. Click [Cleanup] when no printer is displayed in the list.

# 5 Click [Yes].

Warning		22
<u>^</u>	Are you sure you want to delete the printer 'Canon LBP '?	
	Yes No	

#### The uninstall starts.

When the following screen appears, click [Yes] or [Yes To All].




# 6 Click [Exit].

inter Name	Driver Name	Version
	Clearup Select All	Delete

### Uninstalling the Product Extended Survey Program

- 1 Log on to the computer with an administrator account.
- 2 Display [Programs and Features] or [Add or Remove Programs]. ODisplaying [Programs and Features] or [Add or Remove Programs]
- 3 Select [Canon Laser Printer/Scanner/Fax Extended Survey Program], and click [Uninstall] or [Remove].



# **4** Click [ОК].



# Troubleshooting

If you encounter problems during installation of the printer driver, see the following sections before contacting Canon.

Problems with the Wireless LAN Connection
 Problems with the USB Connection
 Problems via the Print Server

## Problems with the Wireless LAN Connection


## The printer that you want does not appear in [Printer List].

Click [Search Again] to search for the printer on the network.



Check whether the printer is ready to connect to the network.
 Cannot Connect to the Wireless LAN

### **Cannot Connect to the Wireless LAN**



50 m or less



#### Reset the wireless LAN settings.

Configuring Wireless LAN Network Settings

## NOTE

### When you need to manually set up the connection

If the wireless router is set up as described below, enter the required information manually.

- The stealth function is enabled.
- ANY connection refusal* is enabled.
- The WEP key number to use is set to a number from 2 to 4.
- The automatically generated WEP key (hexadecimal) is selected.
- * A function in which the wireless router refuses the connection if the SSID of the device to be connected is set to "ANY" or is blank.

#### When you need to change the settings of the wireless router

If the wireless router is set up as described below, change the settings of the router.

- MAC address filtering is enabled.
- When only IEEE 802.11n is used for the wireless communication, WEP is selected or the WPA/WPA2 encryption method is set to TKIP.

## Problems with the USB Connection

#### Installation does not start.

- Is the printer turned ON?
- Are the printer and the computer connected correctly via a USB cable?
   Connecting via USB
- Was the printer turned ON before you installed the printer driver? If so, turn OFF the printer and unplug the USB cable, and then reinstall the printer driver.
   Installing

#### **IMPORTANT:**

Always turn ON the printer when the following screen is displayed.



First delete the USB class driver, and then reinstall the printer driver.
 Deleting the USB Class Driver
 Installing

## Problems via the Print Server

#### You cannot find the print server to connect to.

- Are the print server and computer connected correctly?
- Is the print server running?
- Do you have user rights to connect to the print server? If you are not sure, consult the print server's administrator.
- Is [Network discovery] enabled? (Windows Vista/7/8/Server 2008/Server 2012)

©Enabling [Network discovery]


## **Deleting the USB Class Driver**

Delete the USB class driver when it is not possible to install the printer driver correctly when using a USB connection. Note that even if you delete the USB class driver, it will be installed again automatically when you connect the printer and your computer with a USB cable.

- Connect the printer and your computer with a USB cable ( Connecting via USB ), and turn ON the printer.
- 2 Log on to the computer with an administrator account.
- **3** Display [Device Manager]. Displaying [Device Manager]
- **4** Double-click [Universal Serial Bus controllers].

🚔 Device Manager	
File Action View Help	
♦ ♦ 00 8 00 40	
🤋 🐢 Computer	*
Disk drives	
Display adapters	
DVD/CD-ROM drives	
B Annual Interface Devices	
D California IDE ATA/ATAPI controllers	
b - W IEEE 1394 Bus host controllers	
Keyboards	
b - A Mice and other pointing devices	2
Monitors	-
b 👻 Network adapters	
D - D Other devices	
Portable Devices	
Processors	
5 - 4 Sound, video and game controllers	
5 JIII System devices	
b - W Universal Serial Bus controllers	*

5 Right-click [USB Printing Support], and click [Uninstall].



#### **IMPORTANT:**

**Be careful to delete [USB Printing Support] only, and never delete any other devices or device drivers** Windows may not operate properly if you delete other devices or device drivers.

#### NOTE:

#### If [USB Printing Support] is not displayed

[USB Printing Support] is not displayed if the USB class driver is not installed properly. In this case, close [Device Manager] without doing anything further.

## 6 Click [OK].

Confirm	Device Uninstall
Ŧ	USB Pinting Support
Warning	You are about to uninstall this device from your system.
	OK Cancel

- **7** Close [Device Manager].
- 8 Unplug the USB cable, and restart your computer.

## LINKS

Connecting via USB

## **Appendix**

The Appendix provides information you should know, such as how to connect the printer to your computer, how to use the Installation Guide, disclaimers, and copyright information. It also explains how to start the MF/LBP Network Setup Tool manually. Refer to it as necessary.

## **Connecting the Printer to a Computer**

There are two ways to connect the printer to a computer: "via wireless LAN," and "via USB." Select the connection method that best suits your communication environment and devices.

## Connecting via Wireless LAN





Connect the printer to a router via wireless communications. **©Connecting via** Wireless LAN

## Connecting via USB



Connect the printer to a computer via a USB cable. **©Connecting via USB** 

## NOTE

The supported connection methods differ depending on the printer you are using. Refer to the "e-Manual" supplied with your printer for information about the supported connection methods.

## **Connecting via Wireless LAN**

Connect the printer to a computer via a wireless LAN router. The printer and the router are connected wirelessly (via radio waves), so you do not need a LAN cable. To make wireless LAN settings, use the MF/LBP Network Setup Tool from your computer.

# Things to Check before Starting Configuring Wireless LAN Network Settings

## Things to Check before Starting



- Have the computer and the router been connected properly? For more information, see the instruction manuals for the devices you are using, or contact the manufacturer.
- Have the network settings been completed on the computer? If the network has not been set up properly, you will not be able to use the printer on the wireless LAN network, even if you perform the rest of the procedure below.

#### IMPORTANT

#### **Risk of Information Leak**

If the printer is connected to an unsecured network, your personal information might be leaked to a third party because radio waves used in wireless communication can go anywhere nearby, even beyond walls. Use wireless LAN connection at your own discretion and at your own risk.

#### **Wireless LAN Security Standards**

Refer to the "e-Manual" supplied with your printer for information about the security standards supported by the printer.

## NOTE

- The printer does not come with a wireless LAN router. Have one ready as necessary.
- The wireless router must conform to the IEEE 802.11b/g/n standards and be able to communicate in the 2.4 GHz band. For more information, see the instruction manual provided with the router, or contact the manufacturer.
- If you are using the printer in your office, consult your network administrator.


### Configuring Wireless LAN Network Settings

Log on to the computer with an administrator account.

- **Start the MF/LBP Network Setup Tool.** 
  - There are two ways to start the MF/LBP Network Setup Tool: "Start it from the CD-ROM/DVD-ROM," and "Start it from a downloaded file."
     Starting from the CD-ROM/DVD-ROM

Starting from a Downloaded File


**Follow the on-screen instructions to configure the wireless LAN settings.** 




## NOTE:

## If there is something you do not understand

Click [Useful Tips] at the bottom left of the screen to display troubleshooting tips.



## **Connecting via USB**



## NOTE

- If your printer does not come with a USB cable, you will need to provide your own cable separately.
- Make sure that the USB cable you use has the following mark.



• If a Plug and Play automatic setup screen like the one shown below is displayed when you connect the USB cable, click [Close] or [Cancel] to close it.


🐌 Driver Software Installation		
Device driver software wa	as not successfully installed	
USB Printing Support CanonLBP	Ready to use	
What can I do if my device did no	t install properly?	
		Close

## LINKS

Deleting the USB Class Driver

## **MF/LBP Network Setup Tool**

The MF/LBP Network Setup Tool is a utility that allows you to configure initial network settings by following instructions on the screen. The Tool starts automatically when you install a printer driver from the User Software CD-ROM/DVD-ROM. If you want to start it alone manually, you can start it from the User Software CD-ROM/DVD-ROM or start it directly from a file downloaded from the Canon website.



Starting from the CD-ROM/DVD-ROM Starting from a Downloaded File

## NOTE

- The system environment required to use the MF/LBP Network Setup Tool is the same as the system environment required for the printer driver. **System Requirements**
- See Oconfiguring Wireless LAN Network Settings for information about how to configure initial network settings by using the MF/LBP Network Setup Tool.

### Starting from the CD-ROM/DVD-ROM

- Log on to the computer with an administrator account.
- 2 Insert the User Software CD-ROM/DVD-ROM into the drive on the computer.
- **3** Click [Start Software Programs].



NOTE:


- If the above screen does not appear ODisplaying the [CD-ROM/DVD-ROM Setup] Screen
- If [AutoPlay] is displayed, click [Run MInst.exe].

4 Click [Start] of [MF/LBP Network Setup Tool].


Start Software Programs	
Starts programs from the CD/DVD. Click [Start] to the right of the program you want to start.	
MFA.SP Network Setup Tool Configures printer settings in order to connect to the network.	Readme
The manual Uninstalled by this setup will be uninstalled.	
	Start
Back	Cancel

## Starting from a Downloaded File

The MF/LBP Network Setup Tool is included among the files that you download to install a printer driver. Start by downloading the printer driver file, which contains the printer driver and associated files, from the Canon website (http://www.canon.com/).



## 2 Double-click "CNAN1STK.exe" in the [Network_Setting_Tool] folder.



## **Using the Installation Guide**

The Installation Guide is a manual that can be viewed on your computer. It provides information about the installation of printer drivers. You can find pages quickly by searching for what you want to do or by entering keywords.

#### How to Find the Topic You Are Looking For

You can find the page you are looking for using the following three methods.

#### Search the contents

You can find the page you are looking for by selecting a topic from the [Contents] tab on the left side of the screen, or by selecting a chapter icon from the icons next to the topics.

## OTop Page

C Topic Page

#### Search by keyword

You can search by entering keywords, such as "USB" or "environment." Pages containing the keywords are displayed. You can also enter phrases such as "update driver." The search will find topics containing all of the words in the phrase (AND search).

#### Search Tab

#### Search the site map

Click [Site Map] on the top part of the screen to display a list of all the Installation Guide topics. From there you can find the topic you are looking for.

Site Map

## NOTE

#### System requirements

To use the Installation Guide, one of the following Web browsers is required. The content of the Installation Guide may not display correctly if a browser not listed below is used.

Internet Explorer 7.0/8.0/9.0/10.0/11.0, Firefox 10.0.x ESR/16.0.x

## Screen Configuration of the Installation Guide

The Installation Guide is divided into different screens, and the content of each screen varies.

### **Top Page**

This page appears when the Installation Guide is started.



## 👩 Canon logo

Click to return to the top page from any other page.

### [Contents] tab/[Search] tab

-

Click to toggle the display between the [Contents] tab and [Search] tab.

#### 🙆 Contents

Displays the titles of chapters ( $\mathbf{0}$ ). Place the mouse pointer over one of the titles to display the topics in that chapter on the right. Click a topic to display its page.

Contents Search	
Y Introduction	Installing the Driver is
🛨 Installing	Installing from the Supplied Easy!
Setting Up a Print Server	Installing after Downloading from the Canon Website you.
🗘 Updating and Uninstalling	Installing to Use WSD sinstalled before starting. tion, see "Getting Started"
O Troubleshooting	suppreciant your printer.
C Appendix	Sam 10-9-00

### 📵 [Тор]

Click to return to the top page from any other page.

## 🙆 [Site Map]

Click to display the titles of all Installation Guide topics.

#### 🕧 [Help]

Click to display information on how to view the Installation Guide, how to perform a search, and other information.

## 🕚 [Print]


Click to print the currently displayed topic page.

## 🜔 [Notice]

Click to view important information you should know when using the printer.

## **Topic Page**

Topic pages contain information about how to install printer drivers.



#### [Contents]

Chapter icons and topic titles are displayed in this tab.

#### 🕒 🔍 / 🕟

The [Contents] tab can be widened and narrowed.

#### [Expand All]/[Collapse All]

Click [Expand All] to display all of the subsections of all topics. Click [Collapse All] to close all of the subsections of all the topics.

#### 6 Chapter icons

Click a chapter icon to navigate to the top of the corresponding chapter.

#### Copics

Displays the topics of the selected chapter. If "+" is displayed on a topic, clicking it displays the subsections of that topic. Click "-" to close an expanded topic.

#### 🗿 [Print all]

All pages of the selected chapter are opened in a separate window. You can print them as necessary.

#### (i) Navigation

This shows which chapter topic you are currently viewing.

### 6 🖻

Click to return to the page top.

🌖 < / 🗲

Click to display the previous or next topic.

### 00


Click to jump to the corresponding page. To return to the previous page, click the [Back] button on your Web browser.

#### 🚷 🖂

Click to display hidden detailed descriptions. Click again to close the detailed descriptions.

#### **Search Tab**

This tab contains a text box to perform a search and find the page you are looking for.



#### [Enter keyword(s) here]

Enter one or more keywords and click **Q** to display search results in a results list. You can enter a phrase to find pages that contain all of the words in the phrase. To find an exact phrase, enclose it in double quotation marks.

#### [Search options]

Click to specify search conditions such as the scope of the search and case sensitivity.

#### Gearch scope selector

You can use this to select the individual chapters to search. This allows you to search more efficiently, when you can predict the chapters containing the topic that you are looking for.

#### 6 Search options selector

Select the check box to make your search case-sensitive.

#### [Search with these conditions]

**(()** and **(()** specify the conditions. After setting them, press this to perform the search and display the results in the [Result] list.

#### 🗿 Result list

This displays pages that contain the specified keywords. From the results, locate the page you are looking for and click the topic title of the page. If the results cannot be displayed on one page, click ||| or a page number to display the results on the corresponding page.

#### Site Map

This page displays the titles of all topics in the Installation Guide.

Canon Printer Driver Installation Guide	Top Site Map Help Print 🛎
<ul> <li>€</li> <li>Ø</li> <li>Ø</li></ul>	
Introduction       Bystem Requirements	▼ Next
🗄 Installing	▲ Previous ▼ Next d
Installing from the Supplied CD-ROM/DVD-ROM Installing after Downloading from the Canon Website Installing to Use WSD	
En Setting Up a Print Server	A Previous Vext
Configuring Settings on the Print Server Computer Installing Drivers via the Print Server (Client Settings)	

#### 6 Chapter icons

Click to jump to the table of contents of the selected chapter.

### 🚯 Topic titles

Displays titles and topics. Click a title to jump to the corresponding topic page.

## 0 🗈

Click to return to the page top.

## ⓓ ▲/▼

Click to go to the previous or next chapter.

## **Viewing the Installation Guide**

## Marks

Restrictions and cautions regarding the handling of the printer, useful tips, and other information are indicated using the marks below.

IMPORTANT	Indicates operational requirements and restrictions. Be sure to read these items carefully to operate the printer
	correctly and avoid damage to the printer or property.

**NOTE** Indicates a clarification of an operation, or contains additional explanations for a procedure.

#### **Buttons**

Buttons on the computer display are indicated with the following notation:

Example from the Installation Guide: [Next]

#### **Computer Screens**

Depending on the operating system you are using, the appearance of the displays in this guide may differ slightly from the displays that you see. Also, the appearance of printer drivers and software may differ depending on their version.

## Other

This section describes basic Windows operations and includes disclaimers, copyright information, and other information.

## **Basic Windows Operations**

Displaying the Printer Folder
Enabling [Network discovery]
Displaying the [CD-ROM/DVD-ROM Setup] Screen
Checking the Bit Architecture
Displaying [Programs and Features] or [Add or Remove Programs]
Displaying [Device Manager]

## Displaying the Printer Folder

Windows XP Professional/Server 2003 [Start] > select [Printers and Faxes].

Windows XP Home Edition [Start] ▶ select [Control Panel] ▶ [Printers and Other Hardware] ▶ [Printers and Faxes].

Windows Vista [Start] > select [Control Panel] > [Printer].

Windows 7/Server 2008 R2 [Start] > select [Devices and Printers].

### Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [Control Panel] > [View devices and printers].

#### Windows Server 2008

[Start] > select [Control Panel] > double-click [Printers].

### Enabling [Network discovery]

If you are using Windows Vista/7/8/Server 2008/Server 2012, enable [Network discovery] to view the computers on your network.

#### Windows Vista

[Start] > select [Control Panel] > [View network status and tasks] > under [Network discovery], select [Turn on network discovery].

#### Windows 7/Server 2008 R2

[Start] > select [Control Panel] > [View network status and tasks] > [Change advanced sharing settings] > under [Network discovery], select [Turn on network discovery].

#### Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [Control Panel] > [View network status and tasks] > [Change advanced sharing settings] > under [Network discovery], select [Turn on network discovery].

#### Windows Server 2008

[Start] > select [Control Panel] > double-click [Network and Sharing Center] > under [Network discovery], select [Turn on network discovery].

#### Displaying the [CD-ROM/DVD-ROM Setup] Screen

If your computer does not display the [CD-ROM/DVD-ROM Setup] screen after you insert the CD-ROM/DVD-ROM, follow the procedure below. This following example uses "D:" as the name of the CD-ROM/DVD-ROM drive. The CD-ROM/DVD-ROM drive name may be different on your computer.

#### Windows XP/Server 2003

[Start] > select [Run] > enter "D:\MInst.exe" > click [OK].

#### Windows Vista/7/Server 2008

[Start] • enter "D:\MInst.exe" in [Search programs and files] or [Start Search] • press the [ENTER] key on the keyboard.

#### Windows 8/Server 2012

Right-click the lower-left corner of the screen > select [Run] > enter "D:\MInst.exe" > click [OK].

If you are not sure whether your computer is running 32-bit or 64-bit Windows, follow the procedure below to check.



Windows Vista/7/Server 2008 [Start] > select [Control Panel].

Windows 8/Server 2012 Right-click the lower-left corner of the screen > select [Control Panel].

## Display [System].

Windows Vista/7/8/Server 2008 R2/Server 2012 Click [System and Security] or [System and Maintenance] > [System].

Windows Server 2008 Double-click [System].


**3** Check the bit architecture.

#### 32-bit operating systems

[32-bit Operating System] is displayed.

## 64-bit operating systems

[64-bit Operating System] is displayed.



#### Displaying [Programs and Features] or [Add or Remove Programs]

#### Windows XP/Server 2003

[Start] > [Control Panel] > select [Add or Remove Programs].

#### Windows Vista/7/Server 2008 R2

[Start] > [Control Panel] > select [Uninstall a Program].

### Windows 8/Server 2012

Right-click the lower-left corner of the screen > [Control Panel] > select [Uninstall a Program].

#### Windows Server 2008

[Start] > select [Control Panel] > double-click [Programs and Features].

## Displaying [Device Manager]

#### Windows XP

[Start] > [Control Panel] > [Performance and Maintenance] > [System] > [Hardware] > select [Device Manager].

#### Windows Vista/7/Server 2008 R2

[Start] | [Control Panel] | [Hardware and Sound] or [Hardware] | select [Device Manager].

#### Windows 8/Server 2012

Right-click the lower-left corner of the screen | [Control Panel] | [Hardware and Sound] | select [Device Manager].

#### Windows Server 2003

[Start] > [Control Panel] > [System] > [Hardware] > select [Device Manager].

#### Windows Server 2008

[Start] > select [Control Panel] > double-click [Device Manager].

## Notice

## Disclaimers

- The information in this document is subject to change without notice.
- CANON INC. MAKES NO WARRANTY OF ANY KIND WITH REGARD TO THIS MATERIAL, EITHER EXPRESS OR IMPLIED, EXCEPT AS PROVIDED HEREIN, INCLUDING WITHOUT LIMITATION, THEREOF, WARRANTIES AS TO MARKETABILITY, MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OF USE OR NON-INFRINGEMENT. CANON INC. SHALL NOT BE LIABLE FOR ANY DIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES OF ANY NATURE, OR LOSSES OR EXPENSES RESULTING FROM THE USE OF THIS MATERIAL.

## Copyright

Copyright CANON INC. 2013

No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual, or otherwise, without the prior written permission of Canon Inc.

## Trademarks

- Apple, AppleTalk, EtherTalk, LocalTalk, Mac, Mac OS, and Safari are trademarks of Apple Inc., registered in the U.S. and other countries.
- Microsoft, Windows, Windows Vista, Windows Server and Internet Explorer are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- All other product and brand names are registered trademarks, trademarks or service marks of their respective owners.